

TimeTagger

2.8.2.0

Generated by Doxygen 1.8.13

Contents

1	TimeTagger	1
2	Deprecated List	3
3	Module Index	5
3.1	Modules	5
4	Hierarchical Index	7
4.1	Class Hierarchy	7
5	Class Index	9
5.1	Class List	9
6	File Index	11
6.1	File List	11
7	Module Documentation	13
7.1	base iterators	13
7.1.1	Detailed Description	14

8	Class Documentation	15
8.1	Coincidence Class Reference	15
8.1.1	Detailed Description	16
8.1.2	Constructor & Destructor Documentation	16
8.1.2.1	Coincidence()	16
8.1.3	Member Function Documentation	16
8.1.3.1	getChannel()	16
8.2	Coincidences Class Reference	17
8.2.1	Detailed Description	18
8.2.2	Constructor & Destructor Documentation	18
8.2.2.1	Coincidences()	18
8.2.2.2	~Coincidences()	18
8.2.3	Member Function Documentation	18
8.2.3.1	getChannels()	18
8.2.3.2	next_impl()	19
8.2.3.3	setCoincidenceWindow()	19
8.2.4	Friends And Related Function Documentation	19
8.2.4.1	CoincidencesImpl	19
8.3	Combiner Class Reference	20
8.3.1	Detailed Description	20
8.3.2	Constructor & Destructor Documentation	21
8.3.2.1	Combiner()	21
8.3.2.2	~Combiner()	21
8.3.3	Member Function Documentation	21
8.3.3.1	clear_impl()	21
8.3.3.2	getChannel()	21
8.3.3.3	getData()	22
8.3.3.4	next_impl()	22
8.3.4	Friends And Related Function Documentation	22
8.3.4.1	CombinerImpl	22

8.4	ConstantFractionDiscriminator Class Reference	23
8.4.1	Detailed Description	23
8.4.2	Constructor & Destructor Documentation	24
8.4.2.1	ConstantFractionDiscriminator()	24
8.4.2.2	~ConstantFractionDiscriminator()	24
8.4.3	Member Function Documentation	24
8.4.3.1	getChannels()	24
8.4.3.2	next_impl()	24
8.4.3.3	on_start()	25
8.4.4	Friends And Related Function Documentation	25
8.4.4.1	ConstantFractionDiscriminatorImpl	25
8.5	Correlation Class Reference	25
8.5.1	Detailed Description	26
8.5.2	Constructor & Destructor Documentation	26
8.5.2.1	Correlation()	26
8.5.2.2	~Correlation()	27
8.5.3	Member Function Documentation	27
8.5.3.1	clear_impl()	27
8.5.3.2	getData()	27
8.5.3.3	getDataNormalized()	27
8.5.3.4	getIndex()	28
8.5.3.5	next_impl()	28
8.5.4	Friends And Related Function Documentation	28
8.5.4.1	CorrelationImpl	28
8.6	CountBetweenMarkers Class Reference	29
8.6.1	Detailed Description	30
8.6.2	Constructor & Destructor Documentation	30
8.6.2.1	CountBetweenMarkers()	30
8.6.2.2	~CountBetweenMarkers()	30
8.6.3	Member Function Documentation	30

8.6.3.1	clear_impl()	31
8.6.3.2	getBinWidths()	31
8.6.3.3	getData()	31
8.6.3.4	getIndex()	31
8.6.3.5	next_impl()	31
8.6.3.6	ready()	32
8.6.4	Friends And Related Function Documentation	32
8.6.4.1	CountBetweenMarkersImpl	32
8.7	Counter Class Reference	32
8.7.1	Detailed Description	33
8.7.2	Constructor & Destructor Documentation	33
8.7.2.1	Counter()	33
8.7.2.2	~Counter()	34
8.7.3	Member Function Documentation	34
8.7.3.1	clear_impl()	34
8.7.3.2	getData()	34
8.7.3.3	getIndex()	34
8.7.3.4	next_impl()	34
8.7.3.5	on_start()	35
8.7.4	Friends And Related Function Documentation	35
8.7.4.1	CounterImpl	35
8.8	Countrate Class Reference	35
8.8.1	Detailed Description	36
8.8.2	Constructor & Destructor Documentation	36
8.8.2.1	Countrate()	36
8.8.2.2	~Countrate()	37
8.8.3	Member Function Documentation	37
8.8.3.1	clear_impl()	37
8.8.3.2	getCountsTotal()	37
8.8.3.3	getData()	37

8.8.3.4	next_impl()	37
8.8.3.5	on_start()	38
8.8.4	Friends And Related Function Documentation	38
8.8.4.1	CountrateImpl	38
8.9	CustomLogger Class Reference	38
8.9.1	Constructor & Destructor Documentation	39
8.9.1.1	CustomLogger()	39
8.9.1.2	~CustomLogger()	39
8.9.2	Member Function Documentation	39
8.9.2.1	disable()	39
8.9.2.2	enable()	39
8.9.2.3	Log()	39
8.10	CustomMeasurementBase Class Reference	40
8.10.1	Constructor & Destructor Documentation	40
8.10.1.1	CustomMeasurementBase()	41
8.10.2	Member Function Documentation	41
8.10.2.1	_lock()	41
8.10.2.2	_unlock()	41
8.10.2.3	clear_impl()	41
8.10.2.4	finalize_init()	41
8.10.2.5	is_running()	41
8.10.2.6	next_impl()	41
8.10.2.7	on_start()	42
8.10.2.8	on_stop()	42
8.10.2.9	register_channel()	42
8.10.2.10	unregister_channel()	43
8.11	DelayedChannel Class Reference	43
8.11.1	Detailed Description	44
8.11.2	Constructor & Destructor Documentation	44
8.11.2.1	DelayedChannel() [1/2]	44

8.11.2.2	DelayedChannel() [2/2]	44
8.11.2.3	~DelayedChannel()	45
8.11.3	Member Function Documentation	45
8.11.3.1	getChannel()	45
8.11.3.2	getChannels()	45
8.11.3.3	next_impl()	45
8.11.3.4	on_start()	46
8.11.3.5	setDelay()	46
8.11.4	Friends And Related Function Documentation	46
8.11.4.1	DelayedChannelImpl	46
8.12	Dump Class Reference	47
8.12.1	Detailed Description	48
8.12.2	Constructor & Destructor Documentation	48
8.12.2.1	Dump()	48
8.12.2.2	~Dump()	48
8.12.3	Member Function Documentation	48
8.12.3.1	clear_impl()	49
8.12.3.2	next_impl()	49
8.12.3.3	on_start()	49
8.12.3.4	on_stop()	50
8.12.4	Friends And Related Function Documentation	50
8.12.4.1	DumpImpl	50
8.13	Event Struct Reference	50
8.13.1	Member Data Documentation	50
8.13.1.1	state	50
8.13.1.2	time	51
8.14	EventGenerator Class Reference	51
8.14.1	Detailed Description	52
8.14.2	Constructor & Destructor Documentation	52
8.14.2.1	EventGenerator()	52

8.14.2.2	~EventGenerator()	52
8.14.3	Member Function Documentation	53
8.14.3.1	clear_impl()	53
8.14.3.2	getChannel()	53
8.14.3.3	next_impl()	53
8.14.3.4	on_start()	54
8.14.4	Friends And Related Function Documentation	54
8.14.4.1	EventGeneratorImpl	54
8.15	FastBinning Class Reference	54
8.15.1	Detailed Description	54
8.15.2	Member Enumeration Documentation	54
8.15.2.1	Mode	54
8.15.3	Constructor & Destructor Documentation	55
8.15.3.1	FastBinning() [1/2]	55
8.15.3.2	FastBinning() [2/2]	55
8.15.4	Member Function Documentation	55
8.15.4.1	divide()	55
8.15.4.2	getMode()	55
8.16	FileReader Class Reference	56
8.16.1	Detailed Description	56
8.16.2	Constructor & Destructor Documentation	56
8.16.2.1	FileReader() [1/2]	56
8.16.2.2	FileReader() [2/2]	56
8.16.2.3	~FileReader()	57
8.16.3	Member Function Documentation	57
8.16.3.1	getConfiguration()	57
8.16.3.2	getData()	57
8.16.3.3	getDataRaw()	58
8.16.3.4	getLastMarker()	58
8.16.3.5	hasData()	58

8.16.4 Friends And Related Function Documentation	58
8.16.4.1 FileReaderImpl	58
8.17 FileWriter Class Reference	59
8.17.1 Detailed Description	60
8.17.2 Constructor & Destructor Documentation	60
8.17.2.1 FileWriter()	60
8.17.2.2 ~FileWriter()	60
8.17.3 Member Function Documentation	60
8.17.3.1 clear_impl()	60
8.17.3.2 getMaxFileSize()	61
8.17.3.3 getTotalEvents()	61
8.17.3.4 getTotalSize()	61
8.17.3.5 next_impl()	61
8.17.3.6 on_start()	62
8.17.3.7 on_stop()	62
8.17.3.8 setMarker()	62
8.17.3.9 setMaxFileSize()	63
8.17.3.10 split()	63
8.17.4 Friends And Related Function Documentation	63
8.17.4.1 FileWriterImpl	63
8.18 Flim Class Reference	63
8.18.1 Detailed Description	65
8.18.2 Constructor & Destructor Documentation	65
8.18.2.1 Flim()	65
8.18.2.2 ~Flim()	66
8.18.3 Member Function Documentation	66
8.18.3.1 clear_impl()	66
8.18.3.2 frameReady()	66
8.18.3.3 get_ready_index()	67
8.18.3.4 getCurrentFrame()	67

8.18.3.5	getCurrentFrameEx()	67
8.18.3.6	getCurrentFrameIntensity()	67
8.18.3.7	getFramesAcquired()	67
8.18.3.8	getIndex()	67
8.18.3.9	getReadyFrame()	68
8.18.3.10	getReadyFrameEx()	68
8.18.3.11	getReadyFrameIntensity()	68
8.18.3.12	getSummedFrames()	69
8.18.3.13	getSummedFramesEx()	69
8.18.3.14	getSummedFramesIntensity()	69
8.18.3.15	initialize()	70
8.18.3.16	on_frame_end()	70
8.18.4	Member Data Documentation	70
8.18.4.1	accum_diffs	70
8.18.4.2	back_frames	70
8.18.4.3	captured_frames	71
8.18.4.4	frame_begins	71
8.18.4.5	frame_ends	71
8.18.4.6	last_frame	71
8.18.4.7	pixels_completed	71
8.18.4.8	summed_frames	71
8.18.4.9	swap_chain_lock	71
8.18.4.10	total_frames	72
8.19	FlimAbstract Class Reference	72
8.19.1	Constructor & Destructor Documentation	73
8.19.1.1	FlimAbstract()	73
8.19.1.2	~FlimAbstract()	74
8.19.2	Member Function Documentation	74
8.19.2.1	clear_impl()	74
8.19.2.2	isAcquiring()	75

8.19.2.3	<code>next_impl()</code>	75
8.19.2.4	<code>on_frame_end()</code>	75
8.19.2.5	<code>on_start()</code>	76
8.19.2.6	<code>process_tags()</code>	76
8.19.3	Member Data Documentation	76
8.19.3.1	<code>acquiring</code>	76
8.19.3.2	<code>acquisition_lock</code>	76
8.19.3.3	<code>binner</code>	76
8.19.3.4	<code>binwidth</code>	76
8.19.3.5	<code>click_channel</code>	77
8.19.3.6	<code>current_frame_begin</code>	77
8.19.3.7	<code>current_frame_end</code>	77
8.19.3.8	<code>data_base</code>	77
8.19.3.9	<code>finish_after_outputframe</code>	77
8.19.3.10	<code>frame</code>	77
8.19.3.11	<code>frame_acquisition</code>	77
8.19.3.12	<code>frame_begin_channel</code>	77
8.19.3.13	<code>frames_completed</code>	78
8.19.3.14	<code>initialized</code>	78
8.19.3.15	<code>n_bins</code>	78
8.19.3.16	<code>n_frame_average</code>	78
8.19.3.17	<code>n_pixels</code>	78
8.19.3.18	<code>pixel_acquisition</code>	78
8.19.3.19	<code>pixel_begin_channel</code>	78
8.19.3.20	<code>pixel_begins</code>	78
8.19.3.21	<code>pixel_end_channel</code>	79
8.19.3.22	<code>pixel_ends</code>	79
8.19.3.23	<code>pixels_processed</code>	79
8.19.3.24	<code>previous_starts</code>	79
8.19.3.25	<code>start_channel</code>	79

8.19.3.26 ticks	79
8.19.3.27 time_window	79
8.20 FlimBase Class Reference	80
8.20.1 Constructor & Destructor Documentation	80
8.20.1.1 FlimBase()	81
8.20.1.2 ~FlimBase()	81
8.20.2 Member Function Documentation	81
8.20.2.1 frameReady()	82
8.20.2.2 initialize()	82
8.20.2.3 on_frame_end()	82
8.20.3 Member Data Documentation	82
8.20.3.1 total_frames	82
8.21 FlimFrameInfo Class Reference	82
8.21.1 Member Function Documentation	83
8.21.1.1 getFrameNumber()	83
8.21.1.2 getHistograms()	83
8.21.1.3 getIntensities()	84
8.21.1.4 getPixelBegins()	84
8.21.1.5 getPixelEnds()	84
8.21.1.6 getPixelPosition()	84
8.21.1.7 getSummedCounts()	84
8.21.1.8 isValid()	84
8.21.2 Friends And Related Function Documentation	84
8.21.2.1 Flim	85
8.21.3 Member Data Documentation	85
8.21.3.1 bins	85
8.21.3.2 frame_number	85
8.21.3.3 pixel_position	85
8.21.3.4 pixels	85
8.22 FrequencyMultiplier Class Reference	85

8.22.1 Detailed Description	86
8.22.2 Constructor & Destructor Documentation	86
8.22.2.1 FrequencyMultiplier()	86
8.22.2.2 ~FrequencyMultiplier()	87
8.22.3 Member Function Documentation	87
8.22.3.1 getChannel()	87
8.22.3.2 getMultiplier()	87
8.22.3.3 next_impl()	87
8.22.4 Friends And Related Function Documentation	88
8.22.4.1 FrequencyMultiplierImpl	88
8.23 GatedChannel Class Reference	88
8.23.1 Detailed Description	89
8.23.2 Constructor & Destructor Documentation	89
8.23.2.1 GatedChannel()	89
8.23.2.2 ~GatedChannel()	89
8.23.3 Member Function Documentation	90
8.23.3.1 getChannel()	90
8.23.3.2 next_impl()	90
8.23.4 Friends And Related Function Documentation	90
8.23.4.1 GatedChannelImpl	90
8.24 Histogram Class Reference	91
8.24.1 Detailed Description	92
8.24.2 Constructor & Destructor Documentation	92
8.24.2.1 Histogram()	92
8.24.2.2 ~Histogram()	92
8.24.3 Member Function Documentation	92
8.24.3.1 clear_impl()	93
8.24.3.2 getData()	93
8.24.3.3 getIndex()	93
8.24.3.4 next_impl()	93

8.24.3.5	on_start()	94
8.24.4	Friends And Related Function Documentation	94
8.24.4.1	TimeDifferencesImpl< Histogram >	94
8.25	Histogram2D Class Reference	94
8.25.1	Detailed Description	95
8.25.2	Constructor & Destructor Documentation	95
8.25.2.1	Histogram2D()	95
8.25.2.2	~Histogram2D()	96
8.25.3	Member Function Documentation	96
8.25.3.1	clear_impl()	96
8.25.3.2	getData()	96
8.25.3.3	getIndex()	96
8.25.3.4	getIndex_1()	97
8.25.3.5	getIndex_2()	97
8.25.3.6	next_impl()	97
8.25.4	Friends And Related Function Documentation	97
8.25.4.1	Histogram2DImpl	97
8.26	HistogramLogBins Class Reference	98
8.26.1	Detailed Description	99
8.26.2	Constructor & Destructor Documentation	99
8.26.2.1	HistogramLogBins()	99
8.26.2.2	~HistogramLogBins()	99
8.26.3	Member Function Documentation	99
8.26.3.1	clear_impl()	100
8.26.3.2	getBinEdges()	100
8.26.3.3	getData()	100
8.26.3.4	getDataNormalizedCountsPerPs()	100
8.26.3.5	getDataNormalizedG2()	100
8.26.3.6	next_impl()	100
8.26.4	Friends And Related Function Documentation	101

8.26.4.1	HistogramLogBinsImpl	101
8.27	Iterator Class Reference	101
8.27.1	Detailed Description	102
8.27.2	Constructor & Destructor Documentation	102
8.27.2.1	Iterator()	102
8.27.2.2	~Iterator()	103
8.27.3	Member Function Documentation	103
8.27.3.1	clear_impl()	103
8.27.3.2	next()	103
8.27.3.3	next_impl()	103
8.27.3.4	size()	104
8.27.4	Friends And Related Function Documentation	104
8.27.4.1	IteratorImpl	104
8.28	IteratorBase Class Reference	104
8.28.1	Detailed Description	107
8.28.2	Constructor & Destructor Documentation	107
8.28.2.1	IteratorBase()	107
8.28.2.2	~IteratorBase()	107
8.28.3	Member Function Documentation	107
8.28.3.1	clear()	107
8.28.3.2	clear_impl()	108
8.28.3.3	finish_running()	108
8.28.3.4	finishInitialization()	108
8.28.3.5	getCaptureDuration()	108
8.28.3.6	getLock()	109
8.28.3.7	getNewVirtualChannel()	109
8.28.3.8	isRunning()	109
8.28.3.9	lock()	109
8.28.3.10	next_impl()	109
8.28.3.11	on_start()	110

8.28.3.12 on_stop()	110
8.28.3.13 parallelize()	110
8.28.3.14 registerChannel()	111
8.28.3.15 start()	112
8.28.3.16 startFor()	112
8.28.3.17 stop()	112
8.28.3.18 unlock()	112
8.28.3.19 unregisterChannel()	113
8.28.3.20 waitUntilFinished()	113
8.28.4 Friends And Related Function Documentation	113
8.28.4.1 SynchronizedMeasurements	113
8.28.4.2 TimeTaggerProxy	113
8.28.4.3 TimeTaggerRunner	113
8.28.5 Member Data Documentation	114
8.28.5.1 autostart	114
8.28.5.2 capture_duration	114
8.28.5.3 channels_registered	114
8.28.5.4 running	114
8.28.5.5 tagger	114
8.29 OrderedBarrier Class Reference	114
8.29.1 Constructor & Destructor Documentation	115
8.29.1.1 OrderedBarrier()	115
8.29.1.2 ~OrderedBarrier()	115
8.29.2 Member Function Documentation	115
8.29.2.1 queue()	115
8.29.2.2 waitUntilFinished()	115
8.29.3 Friends And Related Function Documentation	116
8.29.3.1 OrderInstance	116
8.30 OrderedPipeline Class Reference	116
8.30.1 Constructor & Destructor Documentation	116

8.30.1.1	OrderedPipeline()	116
8.30.1.2	~OrderedPipeline()	116
8.30.2	Friends And Related Function Documentation	116
8.30.2.1	IteratorBase	117
8.31	OrderedBarrier::OrderInstance Class Reference	117
8.31.1	Constructor & Destructor Documentation	117
8.31.1.1	OrderInstance() [1/2]	117
8.31.1.2	OrderInstance() [2/2]	117
8.31.1.3	~OrderInstance()	117
8.31.2	Member Function Documentation	118
8.31.2.1	release()	118
8.31.2.2	sync()	118
8.31.3	Friends And Related Function Documentation	118
8.31.3.1	OrderedBarrier	118
8.32	Scope Class Reference	118
8.32.1	Constructor & Destructor Documentation	119
8.32.1.1	Scope()	119
8.32.1.2	~Scope()	120
8.32.2	Member Function Documentation	120
8.32.2.1	clear_impl()	120
8.32.2.2	getData()	120
8.32.2.3	getWindowSize()	120
8.32.2.4	next_impl()	120
8.32.2.5	ready()	121
8.32.2.6	triggered()	121
8.32.3	Friends And Related Function Documentation	121
8.32.3.1	ScopeImpl	121
8.33	StartStop Class Reference	122
8.33.1	Detailed Description	122
8.33.2	Constructor & Destructor Documentation	123

8.33.2.1	StartStop()	123
8.33.2.2	~StartStop()	123
8.33.3	Member Function Documentation	123
8.33.3.1	clear_impl()	123
8.33.3.2	getData()	123
8.33.3.3	next_impl()	124
8.33.3.4	on_start()	124
8.33.4	Friends And Related Function Documentation	124
8.33.4.1	StartStopImpl	124
8.34	SynchronizedMeasurements Class Reference	125
8.34.1	Detailed Description	125
8.34.2	Constructor & Destructor Documentation	126
8.34.2.1	SynchronizedMeasurements()	126
8.34.2.2	~SynchronizedMeasurements()	126
8.34.3	Member Function Documentation	126
8.34.3.1	clear()	126
8.34.3.2	getTagger()	126
8.34.3.3	isRunning()	126
8.34.3.4	registerMeasurement()	127
8.34.3.5	runCallback()	127
8.34.3.6	start()	127
8.34.3.7	startFor()	127
8.34.3.8	stop()	127
8.34.3.9	unregisterMeasurement()	127
8.34.3.10	waitUntilFinished()	127
8.34.4	Friends And Related Function Documentation	128
8.34.4.1	TimeTaggerProxy	128
8.35	Tag Struct Reference	128
8.35.1	Detailed Description	128
8.35.2	Member Enumeration Documentation	129

8.35.2.1	Type	129
8.35.3	Member Data Documentation	129
8.35.3.1	channel	129
8.35.3.2	missed_events	129
8.35.3.3	reserved	129
8.35.3.4	time	130
8.35.3.5	type	130
8.36	TimeDifferences Class Reference	130
8.36.1	Detailed Description	131
8.36.2	Constructor & Destructor Documentation	131
8.36.2.1	TimeDifferences()	132
8.36.2.2	~TimeDifferences()	132
8.36.3	Member Function Documentation	132
8.36.3.1	clear_impl()	132
8.36.3.2	getCounts()	133
8.36.3.3	getData()	133
8.36.3.4	getIndex()	133
8.36.3.5	next_impl()	133
8.36.3.6	on_start()	134
8.36.3.7	ready()	134
8.36.3.8	setMaxCounts()	134
8.36.4	Friends And Related Function Documentation	134
8.36.4.1	TimeDifferencesImpl< TimeDifferences >	134
8.37	TimeDifferencesImpl< T > Class Template Reference	135
8.38	TimeDifferencesND Class Reference	135
8.38.1	Detailed Description	136
8.38.2	Constructor & Destructor Documentation	136
8.38.2.1	TimeDifferencesND()	136
8.38.2.2	~TimeDifferencesND()	137
8.38.3	Member Function Documentation	137

8.38.3.1	clear_impl()	137
8.38.3.2	getData()	137
8.38.3.3	getIndex()	137
8.38.3.4	next_impl()	137
8.38.3.5	on_start()	138
8.38.4	Friends And Related Function Documentation	138
8.38.4.1	TimeDifferencesNDImpl	138
8.39	TimeTagger Class Reference	138
8.39.1	Detailed Description	140
8.39.2	Member Function Documentation	140
8.39.2.1	autoCalibration()	140
8.39.2.2	clearConditionalFilter()	141
8.39.2.3	factoryAccess()	141
8.39.2.4	getChannelList()	141
8.39.2.5	getChannelNumberScheme()	141
8.39.2.6	getConditionalFilterFiltered()	141
8.39.2.7	getConditionalFilterTrigger()	142
8.39.2.8	getDACRange()	142
8.39.2.9	getDistributionCount()	142
8.39.2.10	getDistributionPSEcs()	142
8.39.2.11	getEventDivider()	142
8.39.2.12	getFirmwareVersion()	143
8.39.2.13	getHardwareBufferSize()	143
8.39.2.14	getHardwareDelayCompensation()	143
8.39.2.15	getInputMux()	144
8.39.2.16	getLicenseInfo()	144
8.39.2.17	getModel()	144
8.39.2.18	getNormalization()	144
8.39.2.19	getPcbVersion()	145
8.39.2.20	getPsPerClock()	145

8.39.2.21	getSensorData()	145
8.39.2.22	getSerial()	145
8.39.2.23	getStreamBlockSizeEvents()	145
8.39.2.24	getStreamBlockSizeLatency()	146
8.39.2.25	getTestSignalDivider()	146
8.39.2.26	getTriggerLevel()	146
8.39.2.27	reset()	146
8.39.2.28	setConditionalFilter()	146
8.39.2.29	setEventDivider()	147
8.39.2.30	setHardwareBufferSize()	147
8.39.2.31	setInputMux()	147
8.39.2.32	setLED()	148
8.39.2.33	setNormalization()	148
8.39.2.34	setSoundFrequency()	148
8.39.2.35	setStreamBlockSize()	150
8.39.2.36	setTestSignalDivider()	150
8.39.2.37	setTriggerLevel()	150
8.40	TimeTaggerBase Class Reference	151
8.40.1	Member Typedef Documentation	153
8.40.1.1	IteratorCallback	153
8.40.1.2	IteratorCallbackMap	153
8.40.2	Constructor & Destructor Documentation	153
8.40.2.1	TimeTaggerBase() [1/2]	153
8.40.2.2	~TimeTaggerBase()	153
8.40.2.3	TimeTaggerBase() [2/2]	153
8.40.3	Member Function Documentation	153
8.40.3.1	addChild()	154
8.40.3.2	addIterator()	154
8.40.3.3	clearOverflows()	154
8.40.3.4	freeIterator()	154

8.40.3.5	freeVirtualChannel()	154
8.40.3.6	getConfiguration()	154
8.40.3.7	getDeadtime()	154
8.40.3.8	getDelayHardware()	155
8.40.3.9	getDelaySoftware()	155
8.40.3.10	getFence()	155
8.40.3.11	getInputDelay()	156
8.40.3.12	getInvertedChannel()	156
8.40.3.13	getNewVirtualChannel()	156
8.40.3.14	getOverflows()	156
8.40.3.15	getOverflowsAndClear()	157
8.40.3.16	getTestSignal()	157
8.40.3.17	isUnusedChannel()	157
8.40.3.18	operator=()	157
8.40.3.19	registerChannel()	157
8.40.3.20	release()	158
8.40.3.21	removeChild()	158
8.40.3.22	runSynchronized()	158
8.40.3.23	setDeadtime()	158
8.40.3.24	setDelayHardware()	159
8.40.3.25	setDelaySoftware()	159
8.40.3.26	setInputDelay()	160
8.40.3.27	setTestSignal() [1/2]	160
8.40.3.28	setTestSignal() [2/2]	160
8.40.3.29	sync()	161
8.40.3.30	unregisterChannel()	161
8.40.3.31	waitForFence()	161
8.40.4	Friends And Related Function Documentation	162
8.40.4.1	IteratorBase	162
8.40.4.2	TimeTaggerProxy	162

8.40.4.3	TimeTaggerRunner	162
8.41	TimeTaggerVirtual Class Reference	162
8.41.1	Detailed Description	163
8.41.2	Member Function Documentation	163
8.41.2.1	clearConditionalFilter()	163
8.41.2.2	getConditionalFilterFiltered()	164
8.41.2.3	getConditionalFilterTrigger()	164
8.41.2.4	getReplaySpeed()	164
8.41.2.5	replay()	164
8.41.2.6	reset()	165
8.41.2.7	setConditionalFilter()	165
8.41.2.8	setReplaySpeed()	165
8.41.2.9	stop()	166
8.41.2.10	waitForCompletion()	166
8.42	TimeTagStream Class Reference	166
8.42.1	Detailed Description	167
8.42.2	Constructor & Destructor Documentation	168
8.42.2.1	TimeTagStream()	168
8.42.2.2	~TimeTagStream()	168
8.42.3	Member Function Documentation	168
8.42.3.1	clear_impl()	168
8.42.3.2	getCounts()	169
8.42.3.3	getData()	169
8.42.3.4	next_impl()	169
8.42.4	Friends And Related Function Documentation	169
8.42.4.1	TimeTagStreamImpl	170
8.43	TimeTagStreamBuffer Class Reference	170
8.43.1	Member Function Documentation	170
8.43.1.1	getChannels()	170
8.43.1.2	getEventTypes()	171

8.43.1.3	getMissedEvents()	171
8.43.1.4	getOverflows()	171
8.43.1.5	getTimestamps()	171
8.43.2	Friends And Related Function Documentation	171
8.43.2.1	FileReaderImpl	171
8.43.2.2	TimeTagStreamImpl	171
8.43.3	Member Data Documentation	171
8.43.3.1	hasOverflows	172
8.43.3.2	size	172
8.43.3.3	tGetData	172
8.43.3.4	tStart	172
8.44	TriggerOnCountrate Class Reference	172
8.44.1	Detailed Description	173
8.44.2	Constructor & Destructor Documentation	174
8.44.2.1	TriggerOnCountrate()	174
8.44.2.2	~TriggerOnCountrate()	174
8.44.3	Member Function Documentation	174
8.44.3.1	getChannelAbove()	174
8.44.3.2	getChannelBelow()	175
8.44.3.3	getChannels()	175
8.44.3.4	getCurrentCountrate()	175
8.44.3.5	injectCurrentState()	175
8.44.3.6	isAbove()	175
8.44.3.7	isBelow()	175
8.44.3.8	next_impl()	175
8.44.3.9	on_start()	176
8.44.4	Friends And Related Function Documentation	176
8.44.4.1	TriggerOnCountrateImpl	176

9 File Documentation	177
9.1 Iterators.h File Reference	177
9.1.1 Macro Definition Documentation	179
9.1.1.1 BINNING_TEMPLATE_HELPER	179
9.1.2 Enumeration Type Documentation	180
9.1.2.1 CoincidenceTimestamp	180
9.1.2.2 State	180
9.2 TimeTagger.h File Reference	180
9.2.1 Macro Definition Documentation	183
9.2.1.1 channel_t	183
9.2.1.2 ErrorLog	183
9.2.1.3 GET_DATA_1D	183
9.2.1.4 GET_DATA_1D_OP1	184
9.2.1.5 GET_DATA_1D_OP2	184
9.2.1.6 GET_DATA_2D	184
9.2.1.7 GET_DATA_2D_OP1	185
9.2.1.8 GET_DATA_2D_OP2	185
9.2.1.9 GET_DATA_3D	185
9.2.1.10 InfoLog	186
9.2.1.11 LogMessage	186
9.2.1.12 timestamp_t	186
9.2.1.13 TIMETAGGER_VERSION	186
9.2.1.14 TT_API	186
9.2.1.15 WarningLog	186
9.2.2 Typedef Documentation	186
9.2.2.1 _Iterator	186
9.2.2.2 logger_callback	187
9.2.3 Enumeration Type Documentation	187
9.2.3.1 ChannelEdge	187
9.2.3.2 LogLevel	187

9.2.3.3	Resolution	188
9.2.4	Function Documentation	188
9.2.4.1	createTimeTagger()	188
9.2.4.2	createTimeTaggerVirtual()	189
9.2.4.3	extractLicenseInfo()	189
9.2.4.4	flashLicense()	189
9.2.4.5	freeTimeTagger()	189
9.2.4.6	getTimeTaggerChannelNumberScheme()	190
9.2.4.7	getTimeTaggerModel()	190
9.2.4.8	getVersion()	190
9.2.4.9	hasTimeTaggerVirtualLicense()	190
9.2.4.10	LogBase()	190
9.2.4.11	scanTimeTagger()	191
9.2.4.12	setCustomBitFileName()	191
9.2.4.13	setLogger()	191
9.2.4.14	setTimeTaggerChannelNumberScheme()	191
9.2.5	Variable Documentation	192
9.2.5.1	CHANNEL_UNUSED	192
9.2.5.2	CHANNEL_UNUSED_OLD	192
9.2.5.3	TT_CHANNEL_FALLING_EDGES	192
9.2.5.4	TT_CHANNEL_NUMBER_SCHEME_AUTO	192
9.2.5.5	TT_CHANNEL_NUMBER_SCHEME_ONE	193
9.2.5.6	TT_CHANNEL_NUMBER_SCHEME_ZERO	193
9.2.5.7	TT_CHANNEL_RISING_AND_FALLING_EDGES	193
9.2.5.8	TT_CHANNEL_RISING_EDGES	193

Chapter 1

TimeTagger

backend for [TimeTagger](#), an OpalKelly based single photon counting library

Author

Markus Wick markus@swabianinstruments.com

Helmut Fedder helmut@swabianinstruments.com

Michael Schlagmüller michael@swabianinstruments.com

[TimeTagger](#) provides an easy to use and cost effective hardware solution for time-resolved single photon counting applications.

This document describes the C++ native interface to the [TimeTagger](#) device.

Chapter 2

Deprecated List

Class **Dump**

use [FileWriter](#)

Class **Iterator**

use [TimeTagStream](#)

Member **IteratorBase::lock** ()

use `getLock`

Member **IteratorBase::unlock** ()

use `getLock`

Member **TimeTagger::getDistributionPSecs** (std::function< long long *(size_t, size_t)> array_out)=0

Chapter 3

Module Index

3.1 Modules

Here is a list of all modules:

base iterators	13
--------------------------	----

Chapter 4

Hierarchical Index

4.1 Class Hierarchy

This inheritance list is sorted roughly, but not completely, alphabetically:

CustomLogger	38
Event	50
FastBinning	54
FileReader	56
FlimFrameInfo	82
IteratorBase	104
Coincidences	17
Coincidence	15
Combiner	20
ConstantFractionDiscriminator	23
Correlation	25
CountBetweenMarkers	29
Counter	32
Countrate	35
CustomMeasurementBase	40
DelayedChannel	43
Dump	47
EventGenerator	51
FileWriter	59
FlimAbstract	72
Flim	63
FlimBase	80
FrequencyMultiplier	85
GatedChannel	88
Histogram	91
Histogram2D	94
HistogramLogBins	98
Iterator	101
Scope	118
StartStop	122
TimeDifferences	130
TimeDifferencesND	135
TimeTagStream	166
TriggerOnCountrate	172
OrderedBarrier	114

OrderedPipeline	116
OrderedBarrier::OrderInstance	117
SynchronizedMeasurements	125
Tag	128
TimeDifferencesImpl< T >	135
TimeTaggerBase	151
TimeTagger	138
TimeTaggerVirtual	162
TimeTagStreamBuffer	170

Chapter 5

Class Index

5.1 Class List

Here are the classes, structs, unions and interfaces with brief descriptions:

Coincidence	
Coincidence	monitor for one or more channel groups 15
Coincidences	
Coincidence	monitor for one or more channel groups 17
Combiner	
Combine	some channels in a virtual channel which has a tick for each tick in the input channels 20
ConstantFractionDiscriminator	
Virtual CFD	implementation which returns the mean time between a raising and a falling pair of edges 23
Correlation	
Cross-correlation	between two channels 25
CountBetweenMarkers	
Simple counter	where external marker signals determine the bins 29
Counter	
Simple counter	on one or more channels 32
Countrate	
Count rate	on one or more channels 35
CustomLogger 38
CustomMeasurementBase 40
DelayedChannel	
Simple delayed queue 43
Dump	
Dump	all time tags to a file 47
Event 50
EventGenerator	
Generate predefined events	in a virtual channel relative to a trigger event 51
FastBinning 54
FileReader 56
FileWriter	
Compresses and stores	all time tags to a file 59
Flim	
Fluorescence lifetime imaging 63
FlimAbstract 72
FlimBase 80
FlimFrameInfo 82

FrequencyMultiplier	
The signal of an input channel is scaled up to a higher frequency according to the multiplier passed as a parameter	85
GatedChannel	
An input channel is gated by a gate channel	88
Histogram	
Accumulate time differences into a histogram	91
Histogram2D	
A 2-dimensional histogram of time differences. This can be used in measurements similar to 2D NRM spectroscopy	94
HistogramLogBins	
Accumulate time differences into a histogram with logarithmic increasing bin sizes	98
Iterator	
Simple event queue	101
IteratorBase	
Base class for all iterators	104
OrderedBarrier	114
OrderedPipeline	116
OrderedBarrier::OrderInstance	117
Scope	118
StartStop	
Simple start-stop measurement	122
SynchronizedMeasurements	
Start, stop and clear several measurements synchronized	125
Tag	
Single event on a channel	128
TimeDifferences	
Accumulates the time differences between clicks on two channels in one or more histograms .	130
TimeDifferencesImpl< T >	135
TimeDifferencesND	
Accumulates the time differences between clicks on two channels in a multi-dimensional histogram	135
TimeTagger	
Backend for the TimeTagger	138
TimeTaggerBase	151
TimeTaggerVirtual	
Virtual TimeTagger based on dump files	162
TimeTagStream	
Access the time tag stream	166
TimeTagStreamBuffer	170
TriggerOnCountrate	
Inject trigger events when exceeding or falling below a given count rate within a rolling time window	172

Chapter 6

File Index

6.1 File List

Here is a list of all files with brief descriptions:

Iterators.h	177
TimeTagger.h	180

Chapter 7

Module Documentation

7.1 base iterators

base iterators for photon counting applications

Classes

- class [Combiner](#)
Combine some channels in a virtual channel which has a tick for each tick in the input channels.
- class [CountBetweenMarkers](#)
a simple counter where external marker signals determine the bins
- class [Counter](#)
a simple counter on one or more channels
- class [Coincidences](#)
a coincidence monitor for one or more channel groups
- class [Coincidence](#)
a coincidence monitor for one or more channel groups
- class [Countrate](#)
count rate on one or more channels
- class [DelayedChannel](#)
a simple delayed queue
- class [TriggerOnCountrate](#)
Inject trigger events when exceeding or falling below a given count rate within a rolling time window.
- class [GatedChannel](#)
An input channel is gated by a gate channel.
- class [FrequencyMultiplier](#)
The signal of an input channel is scaled up to a higher frequency according to the multiplier passed as a parameter.
- class [Iterator](#)
a simple event queue
- class [TimeTagStream](#)
access the time tag stream
- class [Dump](#)
dump all time tags to a file
- class [StartStop](#)
simple start-stop measurement

- class [TimeDifferences](#)
Accumulates the time differences between clicks on two channels in one or more histograms.
- class [Histogram2D](#)
A 2-dimensional histogram of time differences. This can be used in measurements similar to 2D NRM spectroscopy.
- class [TimeDifferencesND](#)
Accumulates the time differences between clicks on two channels in a multi-dimensional histogram.
- class [Histogram](#)
Accumulate time differences into a histogram.
- class [HistogramLogBins](#)
Accumulate time differences into a histogram with logarithmic increasing bin sizes.
- class [Correlation](#)
cross-correlation between two channels
- class [Scope](#)
- class [SynchronizedMeasurements](#)
start, stop and clear several measurements synchronized
- class [ConstantFractionDiscriminator](#)
a virtual CFD implementation which returns the mean time between a raising and a falling pair of edges
- class [FileWriter](#)
compresses and stores all time tags to a file
- class [EventGenerator](#)
Generate predefined events in a virtual channel relative to a trigger event.
- class [Flim](#)
Fluorescence lifetime imaging.

7.1.1 Detailed Description

base iterators for photon counting applications

Chapter 8


Class Documentation

8.1 Coincidence Class Reference

a coincidence monitor for one or more channel groups

```
#include <Iterators.h>
```

Inheritance diagram for Coincidence:



Public Member Functions

- `Coincidence (TimeTaggerBase *tagger, std::vector< channel_t > channels, timestamp_t coincidence←Window=1000, CoincidenceTimestamp timestamp=CoincidenceTimestamp::Last)`
construct a coincidence
- `channel_t getChannel ()`
virtual channel which contains the coincidences

Additional Inherited Members

8.1.1 Detailed Description

a coincidence monitor for one or more channel groups

Monitor coincidences for a given channel groups passed by the constructor. A coincidence is event is detected when all slected channels have a click within the given coincidenceWindow [ps] The coincidence will create a virtual events on a virtual channel with the channel number provided by [getChannel\(\)](#). For multiple coincidence channel combinations use the class [Coincidences](#) which outperforms multiple instances of Conincedence.

8.1.2 Constructor & Destructor Documentation

8.1.2.1 Coincidence()

```
Coincidence::Coincidence (
    TimeTaggerBase * tagger,
    std::vector< channel_t > channels,
    timestamp_t coincidenceWindow = 1000,
    CoincidenceTimestamp timestamp = CoincidenceTimestamp::Last ) [inline]
```

construct a coincidence

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>channels</i>	vector of channels to match
<i>coincidenceWindow</i>	max distance between all clicks for a coincidence [ps]
<i>timestamp</i>	type of timestamp for virtual channel (Last, Average, First, ListedFirst)

8.1.3 Member Function Documentation

8.1.3.1 getChannel()

```
channel_t Coincidence::getChannel ( ) [inline]
```

virtual channel which contains the coincidences

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.2 Coincidences Class Reference

a coincidence monitor for one or more channel groups

```
#include <Iterators.h>
```

Inheritance diagram for Coincidences:



Public Member Functions

- [Coincidences](#) ([TimeTaggerBase](#) *tagger, std::vector< std::vector< [channel_t](#) >> coincidenceGroups, [timestamp_t](#) coincidenceWindow, [CoincidenceTimestamp](#) timestamp=[CoincidenceTimestamp::Last](#))
construct a [Coincidences](#)
- [~Coincidences](#) ()
- std::vector< [channel_t](#) > [getChannels](#) ()
fetches the block of virtual channels for those coincidence groups
- void [setCoincidenceWindow](#) ([timestamp_t](#) coincidenceWindow)

Protected Member Functions

- bool [next_impl](#) (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state

Friends

- class [CoincidencesImpl](#)

Additional Inherited Members

8.2.1 Detailed Description

a coincidence monitor for one or more channel groups

Monitor coincidences for given coincidence groups passed by the constructor. A coincidence is hereby defined as for a given coincidence group a) the incoming is part of this group b) at least tag arrived within the coincidenceWindow [ps] for all other channels of this coincidence group Each coincidence will create a virtual event. The block of event IDs for those coincidence group can be fetched.

8.2.2 Constructor & Destructor Documentation

8.2.2.1 Coincidences()

```
Coincidences::Coincidences (
    TimeTaggerBase * tagger,
    std::vector< std::vector< channel_t >> coincidenceGroups,
    timestamp_t coincidenceWindow,
    CoincidenceTimestamp timestamp = CoincidenceTimestamp::Last )
```

construct a [Coincidences](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>coincidenceGroups</i>	a vector of channels defining the coincidences
<i>coincidenceWindow</i>	the size of the coincidence window in picoseconds
<i>timestamp</i>	type of timestamp for virtual channel (Last, Average, First, ListedFirst)

8.2.2.2 ~Coincidences()

```
Coincidences::~Coincidences ( )
```

8.2.3 Member Function Documentation

8.2.3.1 getChannels()

```
std::vector<channel_t> Coincidences::getChannels ( )
```

fetches the block of virtual channels for those coincidence groups

8.2.3.2 next_impl()

```
bool Coincidences::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.2.3.3 setCoincidenceWindow()

```
void Coincidences::setCoincidenceWindow (
    timestamp_t coincidenceWindow )
```

8.2.4 Friends And Related Function Documentation

8.2.4.1 CoincidencesImpl

```
friend class CoincidencesImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.3 Combiner Class Reference

Combine some channels in a virtual channel which has a tick for each tick in the input channels.

```
#include <Iterators.h>
```

Inheritance diagram for Combiner:



Public Member Functions

- `Combiner` (`TimeTaggerBase` *tagger, `std::vector`< `channel_t` > channels)
construct a combiner
- `~Combiner` ()
- `void` `getData` (`std::function`< `int64_t` *(`size_t`)> array_out)
get sum of counts
- `channel_t` `getChannel` ()
the new virtual channel

Protected Member Functions

- `bool` `next_impl` (`std::vector`< `Tag` > &incoming_tags, `timestamp_t` begin_time, `timestamp_t` end_time) override
update iterator state
- `void` `clear_impl` () override
clear `Iterator` state.

Friends

- class `CombinerImpl`

Additional Inherited Members

8.3.1 Detailed Description

Combine some channels in a virtual channel which has a tick for each tick in the input channels.

This iterator can be used to get aggregation channels, eg if you want to monitor the countrate of the sum of two channels.

8.3.2 Constructor & Destructor Documentation

8.3.2.1 Combiner()

```
Combiner::Combiner (
    TimeTaggerBase * tagger,
    std::vector< channel_t > channels )
```

construct a combiner

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>channels</i>	vector of channels to combine

8.3.2.2 ~Combiner()

```
Combiner::~Combiner ( )
```

8.3.3 Member Function Documentation

8.3.3.1 clear_impl()

```
void Combiner::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.3.3.2 getChannel()

```
channel_t Combiner::getChannel ( )
```

the new virtual channel

This function returns the new allocated virtual channel. It can be used now in any new iterator.

8.3.3.3 getData()

```
void Combiner::getData (
    std::function< int64_t *(size_t)> array_out )
```

get sum of counts

For reference, this iterators sums up how much ticks are generated because of which input channel. So this functions returns an array with one value per input channel.

8.3.3.4 next_impl()

```
bool Combiner::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.3.4 Friends And Related Function Documentation

8.3.4.1 CombinerImpl

```
friend class CombinerImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.4 ConstantFractionDiscriminator Class Reference

a virtual CFD implementation which returns the mean time between a raising and a falling pair of edges

```
#include <Iterators.h>
```

Inheritance diagram for ConstantFractionDiscriminator:



Public Member Functions

- [ConstantFractionDiscriminator](#) ([TimeTaggerBase](#) *tagger, [std::vector](#)< [channel_t](#) > channels, [timestamp_t](#) search_window)
constructor of a [ConstantFractionDiscriminator](#)
- [~ConstantFractionDiscriminator](#) ()
- [std::vector](#)< [channel_t](#) > [getChannels](#) ()
the list of new virtual channels

Protected Member Functions

- [bool](#) [next_impl](#) ([std::vector](#)< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- [void](#) [on_start](#) () override
callback when the measurement class is started

Friends

- class [ConstantFractionDiscriminatorImpl](#)

Additional Inherited Members

8.4.1 Detailed Description

a virtual CFD implementation which returns the mean time between a raising and a falling pair of edges

8.4.2 Constructor & Destructor Documentation

8.4.2.1 ConstantFractionDiscriminator()

```
ConstantFractionDiscriminator::ConstantFractionDiscriminator (
    TimeTaggerBase * tagger,
    std::vector< channel_t > channels,
    timestamp_t search_window )
```

constructor of a [ConstantFractionDiscriminator](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>channels</i>	list of channels for the CFD, the formers of the raising+falling pairs must be given
<i>search_window</i>	interval for the CFD window, must be positive

8.4.2.2 ~ConstantFractionDiscriminator()

```
ConstantFractionDiscriminator::~~ConstantFractionDiscriminator ( )
```

8.4.3 Member Function Documentation

8.4.3.1 getChannels()

```
std::vector<channel_t> ConstantFractionDiscriminator::getChannels ( )
```

the list of new virtual channels

This function returns the list of new allocated virtual channels. It can be used now in any new measurement class.

8.4.3.2 next_impl()

```
bool ConstantFractionDiscriminator::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.4.3.3 on_start()

```
void ConstantFractionDiscriminator::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.4.4 Friends And Related Function Documentation

8.4.4.1 ConstantFractionDiscriminatorImpl

```
friend class ConstantFractionDiscriminatorImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.5 Correlation Class Reference

cross-correlation between two channels

```
#include <Iterators.h>
```

Inheritance diagram for Correlation:



Public Member Functions

- [Correlation](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) channel_1, [channel_t](#) channel_2=[CHANNEL_UNUSED](#), [timestamp_t](#) binwidth=1000, int n_bins=1000)
constructor of a correlation measurement
- [~Correlation](#) ()
- void [getData](#) (std::function< int32_t *(size_t)> array_out)
returns a one-dimensional array of size n_bins containing the histogram
- void [getDataNormalized](#) (std::function< double *(size_t)> array_out)
get the histogram - normalized such that a perfectly uncorrelated signals would be flat at a height of one
- void [getIndex](#) (std::function< long long *(size_t)> array_out)
returns a vector of size n_bins containing the time bins in ps

Protected Member Functions

- bool [next_impl](#) (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- void [clear_impl](#) () override
clear [Iterator](#) state.

Friends

- class [CorrelationImpl](#)

Additional Inherited Members

8.5.1 Detailed Description

cross-correlation between two channels

Accumulates time differences between clicks on two channels into a histogram, where all ticks are considered both as start and stop clicks and both positive and negative time differences are considered. The histogram is determined by the number of total bins and the binwidth.

8.5.2 Constructor & Destructor Documentation

8.5.2.1 Correlation()

```
Correlation::Correlation (
    TimeTaggerBase * tagger,
    channel_t channel_1,
    channel_t channel_2 = CHANNEL_UNUSED,
    timestamp_t binwidth = 1000,
    int n_bins = 1000 )
```

constructor of a correlation measurement

If channel_2 is left empty or set to CHANNEL_UNUSED, an auto-correlation measurement is performed. This is the same as setting channel_2 = channel_1.

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>channel₁</i>	first click channel
<i>channel₂</i>	second click channel
<i>binwidth</i>	width of one histogram bin in ps
<i>n_bins</i>	the number of bins in the resulting histogram

8.5.2.2 [~Correlation\(\)](#)

```
Correlation::~~Correlation ( )
```

8.5.3 Member Function Documentation

8.5.3.1 [clear_impl\(\)](#)

```
void Correlation::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.5.3.2 [getData\(\)](#)

```
void Correlation::getData (
    std::function< int32_t *(size_t)> array_out )
```

returns a one-dimensional array of size `n_bins` containing the histogram

8.5.3.3 [getDataNormalized\(\)](#)

```
void Correlation::getDataNormalized (
    std::function< double *(size_t)> array_out )
```

get the histogram - normalized such that a perfectly uncorrelated signals would be flat at a height of one

8.5.3.4 getIndex()

```
void Correlation::getIndex (
    std::function< long long *(size_t)> array_out )
```

returns a vector of size `n_bins` containing the time bins in ps

8.5.3.5 next_impl()

```
bool Correlation::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.5.4 Friends And Related Function Documentation

8.5.4.1 CorrelationImpl

```
friend class CorrelationImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.6 CountBetweenMarkers Class Reference

a simple counter where external marker signals determine the bins

```
#include <Iterators.h>
```

Inheritance diagram for CountBetweenMarkers:



Public Member Functions

- [CountBetweenMarkers](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) click_channel, [channel_t](#) begin_channel, [channel_t](#) end_channel=[CHANNEL_UNUSED](#), [int32_t](#) n_values=1000)
constructor of [CountBetweenMarkers](#)
- [~CountBetweenMarkers](#) ()
- [bool](#) [ready](#) ()
tbd
- [void](#) [getData](#) ([std::function](#)< [int32_t](#) *([size_t](#))> array_out)
tbd
- [void](#) [getBinWidths](#) ([std::function](#)< [long long](#) *([size_t](#))> array_out)
fetches the widths of each bins
- [void](#) [getIndex](#) ([std::function](#)< [long long](#) *([size_t](#))> array_out)
fetches the starting time of each bin

Protected Member Functions

- [bool](#) [next_impl](#) ([std::vector](#)< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- [void](#) [clear_impl](#) () override
clear [Iterator](#) state.

Friends

- class [CountBetweenMarkersImpl](#)

Additional Inherited Members

8.6.1 Detailed Description

a simple counter where external marker signals determine the bins

[Counter](#) with external signals that trigger beginning and end of each counter accumulation. This can be used to implement counting triggered by a pixel clock and gated counting. The thread waits for the first time tag on the 'begin_channel', then begins counting time tags on the 'click_channel'. It ends counting when a tag on the 'end_channel' is detected.

8.6.2 Constructor & Destructor Documentation

8.6.2.1 CountBetweenMarkers()

```
CountBetweenMarkers::CountBetweenMarkers (
    TimeTaggerBase * tagger,
    channel_t click_channel,
    channel_t begin_channel,
    channel_t end_channel = CHANNEL_UNUSED,
    int32_t n_values = 1000 )
```

constructor of [CountBetweenMarkers](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>click_channel</i>	channel that increases the count
<i>begin_channel</i>	channel that triggers beginning of counting and stepping to the next value
<i>end_channel</i>	channel that triggers end of counting
<i>n_values</i>	the number of counter values to be stored

8.6.2.2 ~CountBetweenMarkers()

```
CountBetweenMarkers::~CountBetweenMarkers ( )
```

8.6.3 Member Function Documentation

8.6.3.1 clear_impl()

```
void CountBetweenMarkers::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.6.3.2 getBinWidths()

```
void CountBetweenMarkers::getBinWidths (
    std::function< long long *(size_t)> array_out )
```

fetches the widths of each bins

8.6.3.3 getData()

```
void CountBetweenMarkers::getData (
    std::function< int32_t *(size_t)> array_out )
```

tbd

8.6.3.4 getIndex()

```
void CountBetweenMarkers::getIndex (
    std::function< long long *(size_t)> array_out )
```

fetches the starting time of each bin

8.6.3.5 next_impl()

```
bool CountBetweenMarkers::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp\_t begin_time,
    timestamp\_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.6.3.6 ready()

```
bool CountBetweenMarkers::ready ( )
```

tbd

8.6.4 Friends And Related Function Documentation**8.6.4.1 CountBetweenMarkersImpl**

```
friend class CountBetweenMarkersImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.7 Counter Class Reference

a simple counter on one or more channels

```
#include <Iterators.h>
```

Inheritance diagram for Counter:



Public Member Functions

- [Counter](#) ([TimeTaggerBase](#) *tagger, std::vector< [channel_t](#) > channels, [timestamp_t](#) binwidth=1000000000, int32_t n_values=1)
construct a counter
- [~Counter](#) ()
- void [getData](#) (std::function< int32_t *(size_t, size_t)> array_out)
get counts
- void [getIndex](#) (std::function< long long *(size_t)> array_out)

Protected Member Functions

- bool [next_impl](#) (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- void [clear_impl](#) () override
clear [Iterator](#) state.
- void [on_start](#) () override
callback when the measurement class is started

Friends

- class [CounterImpl](#)

Additional Inherited Members

8.7.1 Detailed Description

a simple counter on one or more channels

[Counter](#) with fixed binwidth and circular buffer output. This class is suitable to generate a time trace of the count rate on one or more channels. The thread repeatedly counts clicks on a single channel over a given time interval and stores the results in a two-dimensional array. The array is treated as a circular buffer. I.e., once the array is full, each new value shifts all previous values one element to the left.

8.7.2 Constructor & Destructor Documentation

8.7.2.1 Counter()

```
Counter::Counter (
    TimeTaggerBase * tagger,
    std::vector< channel\_t > channels,
    timestamp\_t binwidth = 1000000000,
    int32_t n_values = 1 )
```

construct a counter

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>channels</i>	channels to count on
<i>binwidth</i>	counts are accumulated for binwidth picoseconds
<i>n_values</i>	number of counter values stored (for each channel)

8.7.2.2 ~Counter()

```
Counter::~Counter ( )
```

8.7.3 Member Function Documentation

8.7.3.1 clear_impl()

```
void Counter::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.7.3.2 getData()

```
void Counter::getData (
    std::function< int32_t *(size_t, size_t)> array_out )
```

get counts

the counts are copied to a newly allocated allocated memory, an the pointer to this location is returned.

8.7.3.3 getIndex()

```
void Counter::getIndex (
    std::function< long long *(size_t)> array_out )
```

8.7.3.4 next_impl()

```
bool Counter::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.7.3.5 on_start()

```
void Counter::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.7.4 Friends And Related Function Documentation

8.7.4.1 CounterImpl

```
friend class CounterImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.8 Countrate Class Reference

count rate on one or more channels

```
#include <Iterators.h>
```

Inheritance diagram for Countrate:



Public Member Functions

- [Countrate](#) ([TimeTaggerBase](#) *[tagger](#), [std::vector](#)< [channel_t](#) > [channels](#))
constructor of [Countrate](#)
- [~Countrate](#) ()
- void [getData](#) ([std::function](#)< double *([size_t](#))> [array_out](#))
get the count rates
- void [getCountsTotal](#) ([std::function](#)< [int64_t](#) *([size_t](#))> [array_out](#))
get the total amount of events

Protected Member Functions

- bool [next_impl](#) ([std::vector](#)< [Tag](#) > &[incoming_tags](#), [timestamp_t](#) [begin_time](#), [timestamp_t](#) [end_time](#)) override
update iterator state
- void [clear_impl](#) () override
*clear *Iterator* state.*
- void [on_start](#) () override
callback when the measurement class is started

Friends

- class [CountrateImpl](#)

Additional Inherited Members

8.8.1 Detailed Description

count rate on one or more channels

Measures the average count rate on one or more channels. Specifically, it counts incoming clicks and determines the time between the initial click and the latest click. The number of clicks divided by the time corresponds to the average countrate since the initial click.

8.8.2 Constructor & Destructor Documentation

8.8.2.1 Countrate()

```
Countrate::Countrate (
    TimeTaggerBase * tagger,
    std::vector< channel_t > channels )
```

constructor of [Countrate](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>channels</i>	the channels to count on

8.8.2.2 ~Countrate()

```
Countrate::~~Countrate ( )
```

8.8.3 Member Function Documentation

8.8.3.1 clear_impl()

```
void Countrate::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.8.3.2 getCountsTotal()

```
void Countrate::getCountsTotal (
    std::function< int64_t *(size_t)> array_out )
```

get the total amount of events

Returns the total amount of events per channel as an array.

8.8.3.3 getData()

```
void Countrate::getData (
    std::function< double *(size_t)> array_out )
```

get the count rates

Returns the average rate of events per second per channel as an array.

8.8.3.4 next_impl()

```
bool Countrate::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.8.3.5 on_start()

```
void Countrate::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.8.4 Friends And Related Function Documentation**8.8.4.1 CountrateImpl**

```
friend class CountrateImpl [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.9 CustomLogger Class Reference

```
#include <TimeTagger.h>
```

Public Member Functions

- [CustomLogger](#) ()
- virtual [~CustomLogger](#) ()
- void [enable](#) ()
- void [disable](#) ()
- virtual void [Log](#) (int level, const std::string &msg)=0

8.9.1 Constructor & Destructor Documentation

8.9.1.1 CustomLogger()

```
CustomLogger::CustomLogger ( )
```

8.9.1.2 ~CustomLogger()

```
virtual CustomLogger::~~CustomLogger ( ) [virtual]
```

8.9.2 Member Function Documentation

8.9.2.1 disable()

```
void CustomLogger::disable ( )
```

8.9.2.2 enable()

```
void CustomLogger::enable ( )
```

8.9.2.3 Log()

```
virtual void CustomLogger::Log (
    int level,
    const std::string & msg ) [pure virtual]
```


The documentation for this class was generated from the following file:

- [TimeTagger.h](#)

8.10 CustomMeasurementBase Class Reference

```
#include <Iterators.h>
```

Inheritance diagram for CustomMeasurementBase:



Public Member Functions

- void [register_channel](#) ([channel_t](#) channel)
- void [unregister_channel](#) ([channel_t](#) channel)
- void [finalize_init](#) ()
- bool [is_running](#) () const
- void [_lock](#) ()
- void [_unlock](#) ()

Protected Member Functions

- [CustomMeasurementBase](#) ([TimeTaggerBase](#) *tagger)
- virtual bool [next_impl](#) (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- virtual void [clear_impl](#) () override
clear [Iterator](#) state.
- virtual void [on_start](#) () override
callback when the measurement class is started
- virtual void [on_stop](#) () override
callback when the measurement class is stopped

Additional Inherited Members

8.10.1 Constructor & Destructor Documentation

8.10.1.1 CustomMeasurementBase()

```
CustomMeasurementBase::CustomMeasurementBase (
    TimeTaggerBase * tagger ) [inline], [protected]
```

8.10.2 Member Function Documentation

8.10.2.1 _lock()

```
void CustomMeasurementBase::_lock ( ) [inline]
```

8.10.2.2 _unlock()

```
void CustomMeasurementBase::_unlock ( ) [inline]
```

8.10.2.3 clear_impl()

```
virtual void CustomMeasurementBase::clear_impl ( ) [inline], [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.10.2.4 finalize_init()

```
void CustomMeasurementBase::finalize_init ( ) [inline]
```

8.10.2.5 is_running()

```
bool CustomMeasurementBase::is_running ( ) const [inline]
```

8.10.2.6 next_impl()

```
virtual bool CustomMeasurementBase::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp\_t begin_time,
    timestamp\_t end_time ) [inline], [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.10.2.7 on_start()

```
virtual void CustomMeasurementBase::on_start ( ) [inline], [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.10.2.8 on_stop()

```
virtual void CustomMeasurementBase::on_stop ( ) [inline], [override], [protected], [virtual]
```

callback when the measurement class is stopped

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.10.2.9 register_channel()

```
void CustomMeasurementBase::register_channel (
    channel\_t channel ) [inline]
```

8.10.2.10 unregister_channel()

```
void CustomMeasurementBase::unregister_channel (
    channel_t channel ) [inline]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.11 DelayedChannel Class Reference

a simple delayed queue

```
#include <Iterators.h>
```

Inheritance diagram for DelayedChannel:



Public Member Functions

- [DelayedChannel](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) input_channel, [timestamp_t](#) delay)
constructor of a [DelayedChannel](#)
- [DelayedChannel](#) ([TimeTaggerBase](#) *tagger, [std::vector](#)< [channel_t](#) > input_channels, [timestamp_t](#) delay)
constructor of a [DelayedChannel](#) for delaying many channels at once
- [~DelayedChannel](#) ()
- [channel_t](#) [getChannel](#) ()
the first new virtual channel
- [std::vector](#)< [channel_t](#) > [getChannels](#) ()
the new virtual channels
- void [setDelay](#) ([timestamp_t](#) delay)
set the delay time delay for the cloned tags in the virtual channels. A negative delay will delay all other events.

Protected Member Functions

- bool [next_impl](#) ([std::vector](#)< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- void [on_start](#) () override
callback when the measurement class is started

Friends

- class [DelayedChannelImpl](#)

Additional Inherited Members

8.11.1 Detailed Description

a simple delayed queue

A simple first-in first-out queue of delayed event timestamps.

8.11.2 Constructor & Destructor Documentation

8.11.2.1 DelayedChannel() [1/2]

```
DelayedChannel::DelayedChannel (
    TimeTaggerBase * tagger,
    channel_t input_channel,
    timestamp_t delay )
```

constructor of a [DelayedChannel](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>input_channel</i>	channel which is delayed
<i>delay</i>	amount of time to delay

8.11.2.2 DelayedChannel() [2/2]

```
DelayedChannel::DelayedChannel (
    TimeTaggerBase * tagger,
    std::vector< channel_t > input_channels,
    timestamp_t delay )
```

constructor of a [DelayedChannel](#) for delaying many channels at once

This function is not exposed to Python/C#/Matlab/Labview

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>input_channels</i>	channels which will be delayed
<i>delay</i>	amount of time to delay

8.11.2.3 ~DelayedChannel()

```
DelayedChannel::~~DelayedChannel ( )
```

8.11.3 Member Function Documentation

8.11.3.1 getChannel()

```
channel_t DelayedChannel::getChannel ( )
```

the first new virtual channel

This function returns the first of the new allocated virtual channels. It can be used now in any new iterator.

8.11.3.2 getChannels()

```
std::vector<channel_t> DelayedChannel::getChannels ( )
```

the new virtual channels

This function returns the new allocated virtual channels. It can be used now in any new iterator.

8.11.3.3 next_impl()

```
bool DelayedChannel::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.11.3.4 on_start()

```
void DelayedChannel::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.11.3.5 setDelay()

```
void DelayedChannel::setDelay (
    timestamp_t delay )
```

set the delay time delay for the cloned tags in the virtual channels. A negative delay will delay all other events.

Note: When the delay is the same or greater than the previous value all incoming tags will be visible at virtual channel. By applying a shorter delay time, the tags stored in the local buffer will be flushed and won't be visible in the virtual channel.

8.11.4 Friends And Related Function Documentation

8.11.4.1 DelayedChannelImpl

```
friend class DelayedChannelImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.12 Dump Class Reference

dump all time tags to a file

```
#include <Iterators.h>
```

Inheritance diagram for Dump:



Public Member Functions

- `Dump (TimeTaggerBase *tagger, std::string filename, int64_t max_tags, std::vector< channel_t > channels=std::vector< channel_t >())`
constructor of a `Dump` thread
- `~Dump ()`
tbd

Protected Member Functions

- `bool next_impl (std::vector< Tag > &incoming_tags, timestamp_t begin_time, timestamp_t end_time) override`
update iterator state
- `void clear_impl () override`
clear `Iterator` state.
- `void on_start () override`
callback when the measurement class is started
- `void on_stop () override`
callback when the measurement class is stopped

Friends

- class `DumpImpl`

Additional Inherited Members

8.12.1 Detailed Description

dump all time tags to a file

Deprecated use [FileWriter](#)

8.12.2 Constructor & Destructor Documentation

8.12.2.1 Dump()

```
Dump::Dump (
    TimeTaggerBase * tagger,
    std::string filename,
    int64_t max_tags,
    std::vector< channel_t > channels = std::vector< channel_t >() )
```

constructor of a [Dump](#) thread

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>filename</i>	name of the file to dump to
<i>max_tags</i>	stop after this number of tags has been dumped. Negative values will dump forever
<i>channels</i>	channels which are dumped to the file (when empty or not passed all active channels are dumped)

8.12.2.2 ~Dump()

```
Dump::~Dump ( )
```

tbd

8.12.3 Member Function Documentation

8.12.3.1 `clear_impl()`

```
void Dump::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.12.3.2 `next_impl()`

```
bool Dump::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp\_t begin_time,
    timestamp\_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.12.3.3 `on_start()`

```
void Dump::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.12.3.4 on_stop()

```
void Dump::on_stop ( ) [override], [protected], [virtual]
```

callback when the measurement class is stopped

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.12.4 Friends And Related Function Documentation

8.12.4.1 DumpImpl

```
friend class DumpImpl [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.13 Event Struct Reference

```
#include <Iterators.h>
```

Public Attributes

- [timestamp_t](#) time
- [State](#) state

8.13.1 Member Data Documentation

8.13.1.1 state

[State](#) Event::state

8.13.1.2 time

```
timestamp_t Event::time
```

The documentation for this struct was generated from the following file:


- [Iterators.h](#)

8.14 EventGenerator Class Reference

Generate predefined events in a virtual channel relative to a trigger event.

```
#include <Iterators.h>
```

Inheritance diagram for EventGenerator:



Public Member Functions

- [EventGenerator](#) ([TimeTaggerBase](#) *[tagger](#), [channel_t](#) trigger_channel, std::vector< [timestamp_t](#) > pattern, uint64_t trigger_divider=1, uint64_t divider_offset=0, [channel_t](#) stop_channel=[CHANNEL_UNUSED](#))
construct a event generator
- [~EventGenerator](#) ()
- [channel_t](#) [getChannel](#) ()
the new virtual channel

Protected Member Functions

- bool [next_impl](#) (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- void [clear_impl](#) () override
clear [Iterator](#) state.
- void [on_start](#) () override
callback when the measurement class is started

Friends

- class [EventGeneratorImpl](#)

Additional Inherited Members

8.14.1 Detailed Description

Generate predefined events in a virtual channel relative to a trigger event.

This iterator can be used to generate a predefined series of events, the pattern, relative to a trigger event on a defined channel. A `trigger_divider` can be used to fire the pattern not on every, but on every *n*'th trigger received. The `trigger_offset` can be used to select on which of the triggers the pattern will be generated when `trigger_divider` is greater than 1. To abort the pattern being generated, a `stop_channel` can be defined. In case it is the very same as the `trigger_channel`, the subsequent generated patterns will not overlap.

8.14.2 Constructor & Destructor Documentation

8.14.2.1 EventGenerator()

```
EventGenerator::EventGenerator (
    TimeTaggerBase * tagger,
    channel_t trigger_channel,
    std::vector< timestamp_t > pattern,
    uint64_t trigger_divider = 1,
    uint64_t divider_offset = 0,
    channel_t stop_channel = CHANNEL_UNUSED )
```

construct a event generator

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>trigger_channel</i>	trigger for generating the pattern
<i>pattern</i>	vector of time stamp generated relativ to the trigger event
<i>trigger_divider</i>	establishes every how many trigger events a pattern is generated
<i>divider_offset</i>	the offset of the divided trigger when the pattern shall be emitted
<i>stop_channel</i>	channel on which a received event will stop all pending patterns from being generated

8.14.2.2 ~EventGenerator()

```
EventGenerator::~EventGenerator ( )
```


8.14.3 Member Function Documentation

8.14.3.1 clear_impl()

```
void EventGenerator::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.14.3.2 getChannel()

```
channel_t EventGenerator::getChannel ( )
```

the new virtual channel

This function returns the new allocated virtual channel. It can be used now in any new iterator.

8.14.3.3 next_impl()

```
bool EventGenerator::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.14.3.4 on_start()

```
void EventGenerator::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.14.4 Friends And Related Function Documentation

8.14.4.1 EventGeneratorImpl

```
friend class EventGeneratorImpl [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.15 FastBinning Class Reference

```
#include <Iterators.h>
```

Public Types

- enum [Mode](#) {
[Mode::ConstZero](#), [Mode::Dividend](#), [Mode::PowerOfTwo](#), [Mode::FixedPoint_32](#),
[Mode::FixedPoint_64](#), [Mode::Divide_32](#), [Mode::Divide_64](#) }

Public Member Functions

- [FastBinning](#) ()
- [FastBinning](#) (uint64_t divisor, uint64_t max_duration_)
- template<Mode mode>
[uint64_t divide](#) (uint64_t duration) const
- [Mode getMode](#) () const

8.15.1 Detailed Description

Helper class for fast division with a constant divisor. It chooses the method on initialization time and precompile the evaluation functions for all methods.

8.15.2 Member Enumeration Documentation

8.15.2.1 Mode

```
enum FastBinning::Mode [strong]
```

Enumerator

ConstZero	
Dividend	
PowerOfTwo	
FixedPoint_32	
FixedPoint_64	
Divide_32	
Divide_64	

8.15.3 Constructor & Destructor Documentation

8.15.3.1 FastBinning() [1/2]

```
FastBinning::FastBinning ( ) [inline]
```

8.15.3.2 FastBinning() [2/2]

```
FastBinning::FastBinning (
    uint64_t divisor,
    uint64_t max_duration_ )
```

8.15.4 Member Function Documentation

8.15.4.1 divide()

```
template<Mode mode>
uint64_t FastBinning::divide (
    uint64_t duration ) const [inline]
```

8.15.4.2 getMode()

```
Mode FastBinning::getMode ( ) const [inline]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.16 FileReader Class Reference

```
#include <Iterators.h>
```

Public Member Functions

- [FileReader](#) (std::vector< std::string > filenames)
- [FileReader](#) (const std::string &filename)
- [~FileReader](#) ()
- bool [hasData](#) ()
- [TimeTagStreamBuffer](#) [getData](#) (uint64_t n_events)
- bool [getDataRaw](#) (std::vector< [Tag](#) > &tag_buffer)
- std::string [getConfiguration](#) ()
- std::string [getLastMarker](#) ()

Friends

- class [FileReaderImpl](#)

8.16.1 Detailed Description

Reads tags from the disk files, which has been created by [FileWriter](#). Its usage is compatible with the [TimeTagStream](#).

8.16.2 Constructor & Destructor Documentation

8.16.2.1 [FileReader\(\)](#) [1/2]

```
FileReader::FileReader (
    std::vector< std::string > filenames )
```

Creates a file reader with the given filename. The file reader automatically continues to read split [FileWriter](#) Streams. In case multiple filenames are given, the files will be read in successively.

Parameters

<i>filenames</i>	list of files to read
------------------	-----------------------

8.16.2.2 [FileReader\(\)](#) [2/2]

```
FileReader::FileReader (
    const std::string & filename )
```

Creates a file reader with the given filename. The file reader automatically continues to read split [FileWriter](#) Streams

Parameters

<i>filename</i>	file to read
-----------------	--------------

8.16.2.3 ~FileReader()

```
FileReader::~FileReader ( )
```

8.16.3 Member Function Documentation

8.16.3.1 getConfiguration()

```
std::string FileReader::getConfiguration ( )
```

Fetches the overall configuration status of the Time Tagger object, which was serialized in the current file.

Returns

a JSON serialized string with all configuration and status flags.

8.16.3.2 getData()

```
TimeTagStreamBuffer FileReader::getData (
    uint64_t n_events )
```

Fetches and delete the next tags from the internal buffer. Every tag is returned exactly once. If less than `n_events` are returned, the reader is at the end-of-files.

Parameters

<i>n_events</i>	maximum amount of elements to fetch
-----------------	-------------------------------------

Returns

a [TimeTagStreamBuffer](#) with up to `n_events` events

8.16.3.3 getDataRaw()

```
bool FileReader::getDataRaw (
    std::vector< Tag > & tag_buffer )
```

Low level file reading. This function will return the next non-empty buffer in a raw format.

Parameters

<i>tag_buffer</i>	a buffer, which will be filled with the new events
-------------------	--

Returns

true if fetching the data was successfully

8.16.3.4 getLastMarker()

```
std::string FileReader::getLastMarker ( )
```

return the last processed marker from the file.

Returns

the last marker from the file

8.16.3.5 hasData()

```
bool FileReader::hasData ( )
```

Checks if there are still events in the [FileReader](#)

Returns

false if no more events can be read from this [FileReader](#)

8.16.4 Friends And Related Function Documentation

8.16.4.1 FileReaderImpl

```
friend class FileReaderImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.17 FileWriter Class Reference

compresses and stores all time tags to a file

```
#include <Iterators.h>
```

Inheritance diagram for FileWriter:



Public Member Functions

- `FileWriter (TimeTaggerBase *tagger, const std::string &filename, std::vector< channel_t > channels)`
constructor of a `FileWriter`
- `~FileWriter ()`
- void `split` (const std::string &new_filename="")
- void `setMaxFileSize` (uint64_t max_file_size)
- uint64_t `getMaxFileSize` ()
- uint64_t `getTotalEvents` ()
- uint64_t `getTotalSize` ()
- void `setMarker` (const std::string &marker)

Protected Member Functions

- bool `next_impl` (std::vector< Tag > &incoming_tags, timestamp_t begin_time, timestamp_t end_time) override
update iterator state
- void `clear_impl` () override
clear `Iterator` state.
- void `on_start` () override
callback when the measurement class is started
- void `on_stop` () override
callback when the measurement class is stopped

Friends

- class `FileWriterImpl`

Additional Inherited Members

8.17.1 Detailed Description

compresses and stores all time tags to a file

8.17.2 Constructor & Destructor Documentation

8.17.2.1 FileWriter()

```
FileWriter::FileWriter (
    TimeTaggerBase * tagger,
    const std::string & filename,
    std::vector< channel_t > channels )
```

constructor of a [FileWriter](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>filename</i>	name of the file to store to
<i>channels</i>	channels which are stored to the file

8.17.2.2 ~FileWriter()

```
FileWriter::~FileWriter ( )
```

8.17.3 Member Function Documentation

8.17.3.1 clear_impl()

```
void FileWriter::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.17.3.2 getMaxFileSize()

```
uint64_t FileWriter::getMaxFileSize ( )
```

fetches the maximum file size. Please see `setMaxFileSize` for more details.

Returns

the maximum file size in bytes

8.17.3.3 getTotalEvents()

```
uint64_t FileWriter::getTotalEvents ( )
```

queries the total amount of events stored in all files

Returns

the total amount of events stored

8.17.3.4 getTotalSize()

```
uint64_t FileWriter::getTotalSize ( )
```

queries the total amount of bytes stored in all files

Returns

the total amount of bytes stored

8.17.3.5 next_impl()

```
bool FileWriter::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each `Iterator` must implement the `next_impl()` method. The `next_impl()` function is guarded by the update lock.

The backend delivers each `Tag` on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.17.3.6 on_start()

```
void FileWriter::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.17.3.7 on_stop()

```
void FileWriter::on_stop ( ) [override], [protected], [virtual]
```

callback when the measurement class is stopped

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.17.3.8 setMarker()

```
void FileWriter::setMarker (
    const std::string & marker )
```

writes a marker in the file. While parsing the file, the last marker can be extracted again.

Parameters

<i>marker</i>	the marker to write into the file
---------------	-----------------------------------

8.17.3.9 setMaxFileSize()

```
void FileWriter::setMaxFileSize (
    uint64_t max_file_size )
```

Set the maximum file size on disk and so when the automatical split happens. Note: This is a rough limit, the actual file might be larger by one block.

Parameters

<i>max_file_size</i>	new maximum file size in bytes
----------------------	--------------------------------

8.17.3.10 split()

```
void FileWriter::split (
    const std::string & new_filename = "" )
```

Close the current file and create a new one

Parameters

<i>new_filename</i>	filename of the new file. If empty, the old one will be used.
---------------------	---

8.17.4 Friends And Related Function Documentation

8.17.4.1 FileWriterImpl

```
friend class FileWriterImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.18 Flim Class Reference

Fluorescence lifetime imaging.

```
#include <Iterators.h>
```

Inheritance diagram for Flim:



Public Member Functions

- [Flim](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) start_channel, [channel_t](#) click_channel, [channel_t](#) pixel_begin_channel, [uint32_t](#) n_pixels, [uint32_t](#) n_bins, [timestamp_t](#) binwidth, [channel_t](#) pixel_end_channel=CHANNEL_UNUSED, [channel_t](#) frame_begin_channel=CHANNEL_UNUSED, [uint32_t](#) finish_after_outputframe=0, [uint32_t](#) n_frame_average=1, [bool](#) pre_initialize=true)
construct a [Flim](#) measurement with a variety of high-level functionality
- [~Flim](#) ()
- [void initialize](#) ()
initializes and starts measuring this [Flim](#) measurement
- [void getReadyFrame](#) ([std::function](#)< [uint32_t](#) *([size_t](#), [size_t](#))> array_out, [int32_t](#) index=-1)
obtain for each pixel the histogram for the given frame index
- [void getReadyFrameIntensity](#) ([std::function](#)< [float](#) *([size_t](#))> array_out, [int32_t](#) index=-1)
obtain an array of the pixel intensity of the given frame index
- [void getCurrentFrame](#) ([std::function](#)< [uint32_t](#) *([size_t](#), [size_t](#))> array_out)
obtain for each pixel the histogram for the frame currently active
- [void getCurrentFrameIntensity](#) ([std::function](#)< [float](#) *([size_t](#))> array_out)
obtain the array of the pixel intensities of the frame currently active
- [void getSummedFrames](#) ([std::function](#)< [uint32_t](#) *([size_t](#), [size_t](#))> array_out, [bool](#) only_ready_frames=true, [bool](#) clear_summed=false)
obtain for each pixel the histogram from all frames acquired so far
- [void getSummedFramesIntensity](#) ([std::function](#)< [float](#) *([size_t](#))> array_out, [bool](#) only_ready_frames=true, [bool](#) clear_summed=false)
obtain the array of the pixel intensities from all frames acquired so far
- [FlimFrameInfo getReadyFrameEx](#) ([int32_t](#) index=-1)
obtain a frame information object, for the given frame index
- [FlimFrameInfo getCurrentFrameEx](#) ()
obtain a frame information object, for the currently active frame
- [FlimFrameInfo getSummedFramesEx](#) ([bool](#) only_ready_frames=true, [bool](#) clear_summed=false)
obtain a frame information object, that represents the sum of all frames acquired so far.
- [uint32_t getFramesAcquired](#) () const
total number of frames completed so far
- [void getIndex](#) ([std::function](#)< [long long](#) *([size_t](#))> array_out)
a vector of size n_bins containing the time bins in ps

Protected Member Functions

- void `on_frame_end` () override
- void `clear_impl` () override
clear `Iterator` state.
- uint32_t `get_ready_index` (int32_t index)
- virtual void `frameReady` (uint32_t frame_number, std::vector< uint32_t > &data, std::vector< timestamp_t > &pixel_begin_times, std::vector< timestamp_t > &pixel_end_times, timestamp_t frame_begin_time, timestamp_t frame_end_time)

Protected Attributes

- std::vector< std::vector< uint32_t > > `back_frames`
- std::vector< std::vector< timestamp_t > > `frame_begins`
- std::vector< std::vector< timestamp_t > > `frame_ends`
- std::vector< uint32_t > `pixels_completed`
- std::vector< uint32_t > `summed_frames`
- std::vector< timestamp_t > `accum_diffs`
- uint32_t `captured_frames`
- uint32_t `total_frames`
- int32_t `last_frame`
- std::mutex `swap_chain_lock`

8.18.1 Detailed Description

Fluorescence lifetime imaging.

Successively acquires n histograms (one for each pixel in the image), where each histogram is determined by the number of bins and the binwidth. Clicks that fall outside the histogram range are ignored.

Fluorescence-lifetime imaging microscopy or [Flim](#) is an imaging technique for producing an image based on the differences in the exponential decay rate of the fluorescence from a fluorescent sample.

Fluorescence lifetimes can be determined in the time domain by using a pulsed source. When a population of fluorophores is excited by an ultrashort or delta pulse of light, the time-resolved fluorescence will decay exponentially.

8.18.2 Constructor & Destructor Documentation

8.18.2.1 Flim()

```
Flim::Flim (
    TimeTaggerBase * tagger,
    channel_t start_channel,
    channel_t click_channel,
    channel_t pixel_begin_channel,
    uint32_t n_pixels,
    uint32_t n_bins,
    timestamp_t binwidth,
    channel_t pixel_end_channel = CHANNEL_UNUSED,
    channel_t frame_begin_channel = CHANNEL_UNUSED,
    uint32_t finish_after_outputframe = 0,
    uint32_t n_frame_average = 1,
    bool pre_initialize = true )
```

construct a [Flim](#) measurement with a variety of high-level functionality

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>start_channel</i>	channel on which start clicks are received for the time differences histogramming
<i>click_channel</i>	channel on which clicks are received for the time differences histogramming
<i>pixel_begin_channel</i>	start of a pixel (histogram)
<i>n_pixels</i>	number of pixels (histograms) of one frame
<i>n_bins</i>	number of histogram bins for each pixel
<i>binwidth</i>	bin size in picoseconds
<i>pixel_end_channel</i>	end marker of a pixel - incoming clicks on the click_channel will be ignored afterwards
<i>frame_begin_channel</i>	(optional) start the frame, or reset the pixel index
<i>finish_after_outputframe</i>	(optional) sets the number of frames stored within the measurement class. After reaching the number, the measurement will stop. If the number is 0 (default value), one frame is stored and the measurement runs continuously.
<i>n_frame_average</i>	(optional) average multiple input frames into one output frame, default: 1
<i>pre_initialize</i>	(optional) initializes the measurement on constructing.

8.18.2.2 ~Flim()

```
Flim::~~Flim ( )
```

8.18.3 Member Function Documentation

8.18.3.1 clear_impl()

```
void Flim::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [FlimAbstract](#).

8.18.3.2 frameReady()

```
virtual void Flim::frameReady (
    uint32_t frame_number,
    std::vector< uint32_t > & data,
    std::vector< timestamp_t > & pixel_begin_times,
    std::vector< timestamp_t > & pixel_end_times,
    timestamp_t frame_begin_time,
    timestamp_t frame_end_time ) [protected], [virtual]
```

8.18.3.3 get_ready_index()

```
uint32_t Flim::get_ready_index (
    int32_t index ) [protected]
```

8.18.3.4 getCurrentFrame()

```
void Flim::getCurrentFrame (
    std::function< uint32_t *(size_t, size_t)> array_out )
```

obtain for each pixel the histogram for the frame currently active

This function returns the histograms for all pixels of the currently active frame

8.18.3.5 getCurrentFrameEx()

```
FlimFrameInfo Flim::getCurrentFrameEx ( )
```

obtain a frame information object, for the currently active frame

This function returns the frame information object for the currently active frame

8.18.3.6 getCurrentFrameIntensity()

```
void Flim::getCurrentFrameIntensity (
    std::function< float *(size_t)> array_out )
```

obtain the array of the pixel intensities of the frame currently active

This function returns the intensities of all pixels of the currently active frame

The pixel intensity is defined by the number of counts acquired within the pixel divided by the respective integration time.

8.18.3.7 getFramesAcquired()

```
uint32_t Flim::getFramesAcquired ( ) const [inline]
```

total number of frames completed so far

This function returns the amount of frames that have been completed so far, since the creation / last clear of the object.

8.18.3.8 getIndex()

```
void Flim::getIndex (
    std::function< long long *(size_t)> array_out )
```

a vector of size n_bins containing the time bins in ps

This function returns a vector of size n_bins containing the time bins in ps.

8.18.3.9 getReadyFrame()

```
void Flim::getReadyFrame (
    std::function< uint32_t *(size_t, size_t)> array_out,
    int32_t index = -1 )
```

obtain for each pixel the histogram for the given frame index

This function returns the histograms for all pixels according to the frame index given. If the index is -1, it will return the last frame, which has been completed. When finish_after_outputframe is 0, the index value must be -1. If index \geq finish_after_outputframe, it will throw an error.

Parameters

<i>array_out</i>	callback for the array output allocation
<i>index</i>	index of the frame to be obtained. if -1, the last frame which has been completed is returned

8.18.3.10 getReadyFrameEx()

```
FlimFrameInfo Flim::getReadyFrameEx (
    int32_t index = -1 )
```

obtain a frame information object, for the given frame index

This function returns a frame information object according to the index given. If the index is -1, it will return the last completed frame. When finish_after_outputframe is 0, index must be -1. If index \geq finish_after_outputframe, it will throw an error.

Parameters

<i>index</i>	index of the frame to be obtained. if -1, last completed frame will be returned
--------------	---

8.18.3.11 getReadyFrameIntensity()

```
void Flim::getReadyFrameIntensity (
    std::function< float *(size_t)> array_out,
    int32_t index = -1 )
```

obtain an array of the pixel intensity of the given frame index

This function returns the intensities according to the frame index given. If the index is -1, it will return the intensity of the last frame, which has been completed. When finish_after_outputframe is 0, the index value must be -1. If index \geq finish_after_outputframe, it will throw an error.

The pixel intensity is defined by the number of counts acquired within the pixel divided by the respective integration time.

Parameters

<i>array_out</i>	callback for the array output allocation
<i>index</i>	index of the frame to be obtained. if -1, the last frame which has been completed is returned

8.18.3.12 `getSummedFrames()`

```
void Flim::getSummedFrames (
    std::function< uint32_t *(size_t, size_t)> array_out,
    bool only_ready_frames = true,
    bool clear_summed = false )
```

obtain for each pixel the histogram from all frames acquired so far

This function returns the histograms for all pixels. The counts within the histograms are integrated since the start or the last clear of the measurement.

Parameters

<i>array_out</i>	callback for the array output allocation
<i>only_ready_frames</i>	if true, only the finished frames are added. On false, the currently active frame is aggregated.
<i>clear_summed</i>	if true, the summed frames memory will be cleared.

8.18.3.13 `getSummedFramesEx()`

```
FlimFrameInfo Flim::getSummedFramesEx (
    bool only_ready_frames = true,
    bool clear_summed = false )
```

obtain a frame information object, that represents the sum of all frames acquired so far.

This function returns the frame information object that represents the sum of all acquired frames.

Parameters

<i>only_ready_frames</i>	if true only the finished frames are added. On false, the currently active is aggregated.
<i>clear_summed</i>	if true, the summed frames memory will be reset and all frames stored prior will be unaccounted in the future.

8.18.3.14 `getSummedFramesIntensity()`

```
void Flim::getSummedFramesIntensity (
    std::function< float *(size_t)> array_out,
```

```
bool only_ready_frames = true,
bool clear_summed = false )
```

obtain the array of the pixel intensities from all frames acquired so far

The pixel intensity is the number of counts within the pixel divided by the integration time.

This function returns the intensities of all pixels summed over all acquired frames.

Parameters

<i>array_out</i>	callback for the array output allocation
<i>only_ready_frames</i>	if true only the finished frames are added. On false, the currently active frame is aggregated.
<i>clear_summed</i>	if true, the summed frames memory will be cleared.

8.18.3.15 initialize()

```
void Flim::initialize ( )
```

initializes and starts measuring this [Flim](#) measurement

This function initializes the [Flim](#) measurement and starts executing it. It does nothing if preinitialized in the constructor is set to true.

8.18.3.16 on_frame_end()

```
void Flim::on_frame_end ( ) [override], [protected], [virtual]
```

Implements [FlimAbstract](#).

8.18.4 Member Data Documentation

8.18.4.1 accum_diffs

```
std::vector<timestamp_t> Flim::accum_diffs [protected]
```

8.18.4.2 back_frames

```
std::vector<std::vector<uint32_t> > Flim::back_frames [protected]
```

8.18.4.3 captured_frames

uint32_t Flim::captured_frames [protected]

8.18.4.4 frame_begins

std::vector<std::vector<timestamp_t> > Flim::frame_begins [protected]

8.18.4.5 frame_ends

std::vector<std::vector<timestamp_t> > Flim::frame_ends [protected]

8.18.4.6 last_frame

int32_t Flim::last_frame [protected]

8.18.4.7 pixels_completed

std::vector<uint32_t> Flim::pixels_completed [protected]

8.18.4.8 summed_frames

std::vector<uint32_t> Flim::summed_frames [protected]

8.18.4.9 swap_chain_lock

std::mutex Flim::swap_chain_lock [protected]

8.18.4.10 total_frames

```
uint32_t Flim::total_frames [protected]
```


The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.19 FlimAbstract Class Reference

```
#include <Iterators.h>
```

Inheritance diagram for FlimAbstract:



Public Member Functions

- [FlimAbstract](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) start_channel, [channel_t](#) click_channel, [channel_t](#) pixel_begin_channel, [uint32_t](#) n_pixels, [uint32_t](#) n_bins, [timestamp_t](#) binwidth, [channel_t](#) pixel_end_channel=[CHANNEL_UNUSED](#), [channel_t](#) frame_begin_channel=[CHANNEL_UNUSED](#), [uint32_t](#) finish_after_outputframe=0, [uint32_t](#) n_frame_average=1, [bool](#) pre_initialize=true)

construct a [FlimAbstract](#) object, [Flim](#) and [FlimBase](#) classes inherit from it

- [~FlimAbstract](#) ()
- [bool isAcquiring](#) () const

tells if the data aquisition has finished reaching finish_after_outputframe

Protected Member Functions

- [template](#)<[FastBinning::Mode](#) bin_mode>
void [process_tags](#) (const [std::vector](#)< [Tag](#) > &incoming_tags)
- [bool next_impl](#) ([std::vector](#)< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- void [clear_impl](#) () override
clear [Iterator](#) state.
- void [on_start](#) () override
callback when the measurement class is started
- virtual void [on_frame_end](#) ()=0

Protected Attributes

- const [channel_t](#) [start_channel](#)
- const [channel_t](#) [click_channel](#)
- const [channel_t](#) [pixel_begin_channel](#)
- const [uint32_t](#) [n_pixels](#)
- const [uint32_t](#) [n_bins](#)
- const [timestamp_t](#) [binwidth](#)
- const [channel_t](#) [pixel_end_channel](#)
- const [channel_t](#) [frame_begin_channel](#)
- const [uint32_t](#) [finish_after_outputframe](#)
- const [uint32_t](#) [n_frame_average](#)
- const [timestamp_t](#) [time_window](#)
- [timestamp_t](#) [current_frame_begin](#)
- [timestamp_t](#) [current_frame_end](#)
- bool [acquiring](#) {}
- bool [frame_acquisition](#) {}
- bool [pixel_acquisition](#) {}
- [uint32_t](#) [pixels_processed](#) {}
- [uint32_t](#) [frames_completed](#) {}
- [uint32_t](#) [ticks](#) {}
- [size_t](#) [data_base](#) {}
- [std::vector< uint32_t >](#) [frame](#)
- [std::vector< timestamp_t >](#) [pixel_begins](#)
- [std::vector< timestamp_t >](#) [pixel_ends](#)
- [std::deque< timestamp_t >](#) [previous_starts](#)
- [FastBinning](#) [binner](#)
- [std::recursive_mutex](#) [acquisition_lock](#)
- bool [initialized](#)

8.19.1 Constructor & Destructor Documentation

8.19.1.1 FlimAbstract()

```

FlimAbstract::FlimAbstract (
    TimeTaggerBase * tagger,
    channel\_t start\_channel,
    channel\_t click\_channel,
    channel\_t pixel\_begin\_channel,
    uint32\_t n\_pixels,
    uint32\_t n\_bins,
    timestamp\_t binwidth,
    channel\_t pixel\_end\_channel = CHANNEL\_UNUSED,
    channel\_t frame\_begin\_channel = CHANNEL\_UNUSED,
    uint32\_t finish\_after\_outputframe = 0,
    uint32\_t n\_frame\_average = 1,
    bool pre\_initialize = true )

```

construct a [FlimAbstract](#) object, [Flim](#) and [FlimBase](#) classes inherit from it

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>start_channel</i>	channel on which start clicks are received for the time differences histogramming
<i>click_channel</i>	channel on which clicks are received for the time differences histogramming
<i>pixel_begin_channel</i>	start of a pixel (histogram)
<i>n_pixels</i>	number of pixels (histograms) of one frame
<i>n_bins</i>	number of histogram bins for each pixel
<i>binwidth</i>	bin size in picoseconds
<i>pixel_end_channel</i>	end marker of a pixel - incoming clicks on the click_channel will be ignored afterwards
<i>frame_begin_channel</i>	(optional) start the frame, or reset the pixel index
<i>finish_after_outputframe</i>	(optional) sets the number of frames stored within the measurement class. After reaching the number, the measurement will stop. If the number is 0 (default value), one frame is stored and the measurement runs continuously.
<i>n_frame_average</i>	(optional) average multiple input frames into one output frame, default: 1
<i>pre_initialize</i>	(optional) initializes the measurement on constructing.

8.19.1.2 ~FlimAbstract()

```
FlimAbstract::~~FlimAbstract ( )
```

8.19.2 Member Function Documentation

8.19.2.1 clear_impl()

```
void FlimAbstract::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

Reimplemented in [Flim](#).

8.19.2.2 isAcquiring()

```
bool FlimAbstract::isAcquiring ( ) const [inline]
```

tells if the data acquisition has finished reaching finish_after_outputframe

This function returns a boolean which tells the user if the class is still acquiring data. It can only reach the false state for finish_after_outputframe > 0.

Note

This can differ from isRunning. The return value of isRunning state depends only on start/startFor/stop.

8.19.2.3 next_impl()

```
bool FlimAbstract::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.19.2.4 on_frame_end()

```
virtual void FlimAbstract::on_frame_end ( ) [protected], [pure virtual]
```

Implemented in [Flim](#), and [FlimBase](#).

8.19.2.5 on_start()

```
void FlimAbstract::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.19.2.6 process_tags()

```
template<FastBinning::Mode bin_mode>
void FlimAbstract::process_tags (
    const std::vector< Tag > & incoming_tags ) [protected]
```

8.19.3 Member Data Documentation

8.19.3.1 acquiring

```
bool FlimAbstract::acquiring {} [protected]
```

8.19.3.2 acquisition_lock

```
std::recursive_mutex FlimAbstract::acquisition_lock [protected]
```

8.19.3.3 binner

```
FastBinning FlimAbstract::binner [protected]
```

8.19.3.4 binwidth

```
const timestamp\_t FlimAbstract::binwidth [protected]
```


8.19.3.5 click_channel

```
const channel_t FlimAbstract::click_channel [protected]
```

8.19.3.6 current_frame_begin

```
timestamp_t FlimAbstract::current_frame_begin [protected]
```

8.19.3.7 current_frame_end

```
timestamp_t FlimAbstract::current_frame_end [protected]
```

8.19.3.8 data_base

```
size_t FlimAbstract::data_base {} [protected]
```

8.19.3.9 finish_after_outputframe

```
const uint32_t FlimAbstract::finish_after_outputframe [protected]
```

8.19.3.10 frame

```
std::vector<uint32_t> FlimAbstract::frame [protected]
```

8.19.3.11 frame_acquisition

```
bool FlimAbstract::frame_acquisition {} [protected]
```

8.19.3.12 frame_begin_channel

```
const channel_t FlimAbstract::frame_begin_channel [protected]
```

8.19.3.13 frames_completed

```
uint32_t FlimAbstract::frames_completed {} [protected]
```

8.19.3.14 initialized

```
bool FlimAbstract::initialized [protected]
```

8.19.3.15 n_bins

```
const uint32_t FlimAbstract::n_bins [protected]
```

8.19.3.16 n_frame_average

```
const uint32_t FlimAbstract::n_frame_average [protected]
```

8.19.3.17 n_pixels

```
const uint32_t FlimAbstract::n_pixels [protected]
```

8.19.3.18 pixel_acquisition

```
bool FlimAbstract::pixel_acquisition {} [protected]
```

8.19.3.19 pixel_begin_channel

```
const channel_t FlimAbstract::pixel_begin_channel [protected]
```

8.19.3.20 pixel_begins

```
std::vector<timestamp_t> FlimAbstract::pixel_begins [protected]
```

8.19.3.21 pixel_end_channel

```
const channel_t FlimAbstract::pixel_end_channel [protected]
```

8.19.3.22 pixel_ends

```
std::vector<timestamp_t> FlimAbstract::pixel_ends [protected]
```

8.19.3.23 pixels_processed

```
uint32_t FlimAbstract::pixels_processed {} [protected]
```

8.19.3.24 previous_starts

```
std::deque<timestamp_t> FlimAbstract::previous_starts [protected]
```

8.19.3.25 start_channel

```
const channel_t FlimAbstract::start_channel [protected]
```

8.19.3.26 ticks

```
uint32_t FlimAbstract::ticks {} [protected]
```

8.19.3.27 time_window

```
const timestamp_t FlimAbstract::time_window [protected]
```


The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.20 FlimBase Class Reference

```
#include <Iterators.h>
```

Inheritance diagram for FlimBase:



Public Member Functions

- `FlimBase (TimeTaggerBase *tagger, channel_t start_channel, channel_t click_channel, channel_t pixel_begin_channel, uint32_t n_pixels, uint32_t n_bins, timestamp_t binwidth, channel_t pixel_end_channel=CHANNEL_UNUSED, channel_t frame_begin_channel=CHANNEL_UNUSED, uint32_t finish_after_outputframe=0, uint32_t n_frame_average=1, bool pre_initialize=true)`
*construct a basic *Flim* measurement, containing a minimum featureset for efficiency purposes*
- `~FlimBase ()`
- `void initialize ()`
*initializes and starts measuring this *Flim* measurement*

Protected Member Functions

- `void on_frame_end ()` override
- `virtual void frameReady (uint32_t frame_number, std::vector< uint32_t > &data, std::vector< timestamp_t > &pixel_begin_times, std::vector< timestamp_t > &pixel_end_times, timestamp_t frame_begin_time, timestamp_t frame_end_time)`

Protected Attributes

- `uint32_t total_frames`

8.20.1 Constructor & Destructor Documentation

8.20.1.1 FlimBase()

```

FlimBase::FlimBase (
    TimeTaggerBase * tagger,
    channel_t start_channel,
    channel_t click_channel,
    channel_t pixel_begin_channel,
    uint32_t n_pixels,
    uint32_t n_bins,
    timestamp_t binwidth,
    channel_t pixel_end_channel = CHANNEL_UNUSED,
    channel_t frame_begin_channel = CHANNEL_UNUSED,
    uint32_t finish_after_outputframe = 0,
    uint32_t n_frame_average = 1,
    bool pre_initialize = true )

```

construct a basic [Flim](#) measurement, containing a minimum featureset for efficiently purposes

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>start_channel</i>	channel on which start clicks are received for the time differences histogramming
<i>click_channel</i>	channel on which clicks are received for the time differences histogramming
<i>pixel_begin_channel</i>	start of a pixel (histogram)
<i>n_pixels</i>	number of pixels (histograms) of one frame
<i>n_bins</i>	number of histogram bins for each pixel
<i>binwidth</i>	bin size in picoseconds
<i>pixel_end_channel</i>	end marker of a pixel - incoming clicks on the click_channel will be ignored afterwards
<i>frame_begin_channel</i>	(optional) start the frame, or reset the pixel index
<i>finish_after_outputframe</i>	(optional) sets the number of frames stored within the measurement class. After reaching the number, the measurement will stop. If the number is 0 (default value), one frame is stored and the measurement runs continuously.
<i>n_frame_average</i>	(optional) average multiple input frames into one output frame, default: 1
<i>pre_initialize</i>	(optional) initializes the measurement on constructing.

8.20.1.2 ~FlimBase()

```

FlimBase::~FlimBase ( )

```

8.20.2 Member Function Documentation

8.20.2.1 frameReady()

```
virtual void FlimBase::frameReady (
    uint32_t frame_number,
    std::vector< uint32_t > & data,
    std::vector< timestamp_t > & pixel_begin_times,
    std::vector< timestamp_t > & pixel_end_times,
    timestamp_t frame_begin_time,
    timestamp_t frame_end_time ) [protected], [virtual]
```

8.20.2.2 initialize()

```
void FlimBase::initialize ( )
```

initializes and starts measuring this [Flim](#) measurement

This function initializes the [Flim](#) measurement and starts executing it. It does nothing if preinitialized in the constructor is set to true.

8.20.2.3 on_frame_end()

```
void FlimBase::on_frame_end ( ) [override], [protected], [virtual]
```

Implements [FlimAbstract](#).

8.20.3 Member Data Documentation

8.20.3.1 total_frames

```
uint32_t FlimBase::total_frames [protected]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.21 FlimFrameInfo Class Reference

```
#include <Iterators.h>
```

Public Member Functions

- `int32_t getFrameNumber () const`
index of this frame
- `bool isValid () const`
tells if this frame is valid
- `uint32_t getPixelPosition () const`
number of pixels aquired on this frame
- `void getHistograms (std::function< uint32_t *(size_t, size_t)> array_out)`
- `void getIntensities (std::function< float *(size_t)> array_out)`
- `void getSummedCounts (std::function< uint64_t *(size_t)> array_out)`
- `void getPixelBegins (std::function< long long *(size_t)> array_out)`
- `void getPixelEnds (std::function< long long *(size_t)> array_out)`

Public Attributes

- `uint32_t pixels`
- `uint32_t bins`
- `int32_t frame_number`
- `uint32_t pixel_position`

Friends

- class `Flim`

8.21.1 Member Function Documentation

8.21.1.1 getFrameNumber()

```
int32_t FlimFrameInfo::getFrameNumber ( ) const [inline]
```

index of this frame

This function returns the frame number, starting from 0 for the very first frame acquired. If the index is -1, it is an invalid frame which is returned on error.

8.21.1.2 getHistograms()

```
void FlimFrameInfo::getHistograms (
    std::function< uint32_t *(size_t, size_t)> array_out )
```

8.21.1.3 get Intensities()

```
void FlimFrameInfo::get Intensities (
    std::function< float *(size_t)> array_out )
```

8.21.1.4 get Pixel Begins()

```
void FlimFrameInfo::get Pixel Begins (
    std::function< long long *(size_t)> array_out )
```

8.21.1.5 get Pixel Ends()

```
void FlimFrameInfo::get Pixel Ends (
    std::function< long long *(size_t)> array_out )
```

8.21.1.6 get Pixel Position()

```
uint32_t FlimFrameInfo::get Pixel Position ( ) const [inline]
```

number of pixels aquired on this frame

This function returns a value which tells how many pixels were processed for this frame.

8.21.1.7 get Summed Counts()

```
void FlimFrameInfo::get Summed Counts (
    std::function< uint64_t *(size_t)> array_out )
```

8.21.1.8 isValid()

```
bool FlimFrameInfo::isValid ( ) const [inline]
```

tells if this frame is valid

This function returns a boolean which tells if this frame is valid or not. Invalid frames are possible on errors, such as asking for the last completed frame when no frame has been completed so far.

8.21.2 Friends And Related Function Documentation

8.21.2.1 Flim

```
friend class Flim [friend]
```

8.21.3 Member Data Documentation

8.21.3.1 bins

```
uint32_t FlimFrameInfo::bins
```

8.21.3.2 frame_number

```
int32_t FlimFrameInfo::frame_number
```

8.21.3.3 pixel_position

```
uint32_t FlimFrameInfo::pixel_position
```

8.21.3.4 pixels

```
uint32_t FlimFrameInfo::pixels
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.22 FrequencyMultiplier Class Reference

The signal of an input channel is scaled up to a higher frequency according to the multiplier passed as a parameter.

```
#include <Iterators.h>
```

Inheritance diagram for FrequencyMultiplier:



Public Member Functions

- [FrequencyMultiplier](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) input_channel, [int32_t](#) multiplier)
constructor of a [FrequencyMultiplier](#)
- [~FrequencyMultiplier](#) ()
- [channel_t](#) getChannel ()
- [int32_t](#) getMultiplier ()

Protected Member Functions

- [bool](#) next_impl (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state

Friends

- class [FrequencyMultiplierImpl](#)

Additional Inherited Members

8.22.1 Detailed Description

The signal of an input channel is scaled up to a higher frequency according to the multiplier passed as a parameter.

The [FrequencyMultiplier](#) inserts copies the original input events from the input_channel and adds additional events to match the upscaling factor. The algorithm used assumes a constant frequency and calculates out of the last two incoming events linearly the intermediate timestamps to match the upscaled frequency given by the multiplier parameter.

The [FrequencyMultiplier](#) can be used to restore the actual frequency applied to an input_channel which was reduces via the EventDivider to lower the effective data rate. For example a 80 MHz laser sync signal can be scaled down via setEventDivider(..., 80) to 1 MHz (hardware side) and an 80 MHz signal can be restored via [FrequencyMultiplier](#)(..., 80) on the software side with some loss in precision. The [FrequencyMultiplier](#) is an alternative way to reduce the data rate in comparison to the EventFilter, which has a higher precision but can be more difficult to use.

8.22.2 Constructor & Destructor Documentation

8.22.2.1 FrequencyMultiplier()

```
FrequencyMultiplier::FrequencyMultiplier (
    TimeTaggerBase * tagger,
    channel_t input_channel,
    int32_t multiplier )
```

constructor of a [FrequencyMultiplier](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>input_channel</i>	channel on which the upscaling of the frequency is based on
<i>multiplier</i>	frequency upscaling factor

8.22.2.2 ~FrequencyMultiplier()

```
FrequencyMultiplier::~FrequencyMultiplier ( )
```

8.22.3 Member Function Documentation

8.22.3.1 getChannel()

```
channel_t FrequencyMultiplier::getChannel ( )
```

8.22.3.2 getMultiplier()

```
int32_t FrequencyMultiplier::getMultiplier ( )
```

8.22.3.3 next_impl()

```
bool FrequencyMultiplier::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.22.4 Friends And Related Function Documentation**8.22.4.1 FrequencyMultiplierImpl**

```
friend class FrequencyMultiplierImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.23 GatedChannel Class Reference

An input channel is gated by a gate channel.

```
#include <Iterators.h>
```

Inheritance diagram for GatedChannel:

**Public Member Functions**

- [GatedChannel](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) input_channel, [channel_t](#) gate_start_channel, [channel_t](#) gate_stop_channel)
constructor of a [GatedChannel](#)
- [~GatedChannel](#) ()
- [channel_t](#) getChannel ()
the new virtual channel

Protected Member Functions

- bool [next_impl](#) (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state

Friends

- class [GatedChannelImpl](#)

Additional Inherited Members

8.23.1 Detailed Description

An input channel is gated by a gate channel.

Note: The gate is edge sensitive and not level sensitive. That means that the gate will transfer data only when an appropriate level change is detected on the `gate_start_channel`.

8.23.2 Constructor & Destructor Documentation

8.23.2.1 GatedChannel()

```
GatedChannel::GatedChannel (
    TimeTaggerBase * tagger,
    channel_t input_channel,
    channel_t gate_start_channel,
    channel_t gate_stop_channel )
```

constructor of a [GatedChannel](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>input_channel</i>	channel which is gated
<i>gate_start_channel</i>	channel on which a signal detected will start the transmission of the input_channel through the gate
<i>gate_stop_channel</i>	channel on which a signal detected will stop the transmission of the input_channel through the gate

8.23.2.2 ~GatedChannel()

```
GatedChannel::~GatedChannel ( )
```

8.23.3 Member Function Documentation

8.23.3.1 `getChannel()`

```
channel_t GatedChannel::getChannel ( )
```

the new virtual channel

This function returns the new allocated virtual channel. It can be used now in any new iterator.

8.23.3.2 `next_impl()`

```
bool GatedChannel::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the `next_impl()` method. The `next_impl()` function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.23.4 Friends And Related Function Documentation

8.23.4.1 `GatedChannelImpl`

```
friend class GatedChannelImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.24 Histogram Class Reference

Accumulate time differences into a histogram.

```
#include <Iterators.h>
```

Inheritance diagram for Histogram:



Public Member Functions

- `Histogram` (`TimeTaggerBase` *tagger, `channel_t` click_channel, `channel_t` start_channel=CHANNEL_UNU↵ SED, `timestamp_t` binwidth=1000, `int32_t` n_bins=1000)
constructor of a `Histogram` measurement
- `~Histogram` ()
- void `getData` (`std::function`< `int32_t` *(`size_t`)> array_out)
- void `getIndex` (`std::function`< long long *(`size_t`)> array_out)

Protected Member Functions

- bool `next_impl` (`std::vector`< `Tag` > &incoming_tags, `timestamp_t` begin_time, `timestamp_t` end_time) override
update iterator state
- void `clear_impl` () override
clear `Iterator` state.
- void `on_start` () override
callback when the measurement class is started

Friends

- class `TimeDifferencesImpl`< `Histogram` >

Additional Inherited Members

8.24.1 Detailed Description

Accumulate time differences into a histogram.

This is a simple multiple start, multiple stop measurement. This is a special case of the more general '[Time↔Differences](#)' measurement. Specifically, the thread waits for clicks on a first channel, the 'start channel', then measures the time difference between the last start click and all subsequent clicks on a second channel, the 'click channel', and stores them in a histogram. The histogram range and resolution is specified by the number of bins and the binwidth. Clicks that fall outside the histogram range are ignored. Data accumulation is performed independently for all start clicks. This type of measurement is frequently referred to as 'multiple start, multiple stop' measurement and corresponds to a full auto- or cross-correlation measurement.

8.24.2 Constructor & Destructor Documentation

8.24.2.1 Histogram()

```

Histogram::Histogram (
    TimeTaggerBase * tagger,
    channel_t click_channel,
    channel_t start_channel = CHANNEL_UNUSED,
    timestamp_t binwidth = 1000,
    int32_t n_bins = 1000 )

```

constructor of a [Histogram](#) measurement

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>click_channel</i>	channel that increments the count in a bin
<i>start_channel</i>	channel that sets start times relative to which clicks on the click channel are measured
<i>binwidth</i>	width of one histogram bin in ps
<i>n_bins</i>	number of bins in the histogram

8.24.2.2 ~Histogram()

```

Histogram::~Histogram ( )

```

8.24.3 Member Function Documentation

8.24.3.1 clear_impl()

```
void Histogram::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.24.3.2 getData()

```
void Histogram::getData (
    std::function< int32_t *(size_t)> array_out )
```

8.24.3.3 getIndex()

```
void Histogram::getIndex (
    std::function< long long *(size_t)> array_out )
```

8.24.3.4 next_impl()

```
bool Histogram::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.24.3.5 on_start()

```
void Histogram::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.24.4 Friends And Related Function Documentation

8.24.4.1 TimeDifferencesImpl< Histogram >

```
friend class TimeDifferencesImpl< Histogram > [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.25 Histogram2D Class Reference

A 2-dimensional histogram of time differences. This can be used in measurements similar to 2D NRM spectroscopy.

```
#include <Iterators.h>
```

Inheritance diagram for Histogram2D:



Public Member Functions

- [Histogram2D](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) start_channel, [channel_t](#) stop_channel_1, [channel_t](#) stop_channel_2, [timestamp_t](#) binwidth_1, [timestamp_t](#) binwidth_2, [int32_t](#) n_bins_1, [int32_t](#) n_bins_2)
constructor of a [Histogram2D](#) measurement
- [~Histogram2D](#) ()
- void [getData](#) (std::function< [int32_t](#) *([size_t](#), [size_t](#))> array_out)
- void [getIndex](#) (std::function< long long *([size_t](#), [size_t](#), [size_t](#))> array_out)
- void [getIndex_1](#) (std::function< long long *([size_t](#))> array_out)
- void [getIndex_2](#) (std::function< long long *([size_t](#))> array_out)

Protected Member Functions

- bool [next_impl](#) (std::vector< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- void [clear_impl](#) () override
clear [iterator](#) state.

Friends

- class [Histogram2DImpl](#)

Additional Inherited Members

8.25.1 Detailed Description

A 2-dimensional histogram of time differences. This can be used in measurements similar to 2D NMR spectroscopy.

This measurement is a 2-dimensional version of the [Histogram](#) measurement. The measurement accumulates two-dimensional histogram where stop signals from two separate channels define the bin coordinate. For instance, this kind of measurement is similar to that of typical 2D NMR spectroscopy.

8.25.2 Constructor & Destructor Documentation

8.25.2.1 Histogram2D()

```
Histogram2D::Histogram2D (
    TimeTaggerBase * tagger,
    channel\_t start_channel,
    channel\_t stop_channel_1,
    channel\_t stop_channel_2,
    timestamp\_t binwidth_1,
    timestamp\_t binwidth_2,
    int32\_t n_bins_1,
    int32\_t n_bins_2 )
```

constructor of a [Histogram2D](#) measurement

Parameters

<i>tagger</i>	time tagger object
<i>start_channel</i>	channel on which start clicks are received
<i>stop_channel_1</i>	channel on which stop clicks for the time axis 1 are received
<i>stop_channel_2</i>	channel on which stop clicks for the time axis 2 are received
<i>binwidth_1</i>	bin width in ps for the time axis 1
<i>binwidth_2</i>	bin width in ps for the time axis 2
<i>n_bins_1</i>	the number of bins along the time axis 1
<i>n_bins_2</i>	the number of bins along the time axis 2

8.25.2.2 ~Histogram2D()

```
Histogram2D::~~Histogram2D ( )
```

8.25.3 Member Function Documentation

8.25.3.1 clear_impl()

```
void Histogram2D::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.25.3.2 getData()

```
void Histogram2D::getData (
    std::function< int32_t *(size_t, size_t)> array_out )
```

Returns a two-dimensional array of size `n_bins_1` by `n_bins_2` containing the 2D histogram.

8.25.3.3 getIndex()

```
void Histogram2D::getIndex (
    std::function< long long *(size_t, size_t, size_t)> array_out )
```

Returns a 3D array containing two coordinate matrices (meshgrid) for time bins in ps for the time axes 1 and 2. For details on meshgrid please take a look at the respective documentation either for Matlab or Python NumPy

8.25.3.4 `getIndex_1()`

```
void Histogram2D::getIndex_1 (
    std::function< long long *(size_t)> array_out )
```

Returns a vector of size `n_bins_1` containing the bin locations in ps for the time axis 1.

8.25.3.5 `getIndex_2()`

```
void Histogram2D::getIndex_2 (
    std::function< long long *(size_t)> array_out )
```

Returns a vector of size `n_bins_2` containing the bin locations in ps for the time axis 2.

8.25.3.6 `next_impl()`

```
bool Histogram2D::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the `next_impl()` method. The `next_impl()` function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.25.4 Friends And Related Function Documentation

8.25.4.1 `Histogram2DImpl`

```
friend class Histogram2DImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.26 HistogramLogBins Class Reference

Accumulate time differences into a histogram with logarithmic increasing bin sizes.

```
#include <Iterators.h>
```

Inheritance diagram for HistogramLogBins:



Public Member Functions

- `HistogramLogBins` (`TimeTaggerBase` *tagger, `channel_t` click_channel, `channel_t` start_channel, double exp_start, double exp_stop, `int32_t` n_bins)
constructor of a `HistogramLogBins` measurement
- `~HistogramLogBins` ()
- void `getData` (`std::function`< `uint64_t` *(`size_t`)> array_out)
- void `getDataNormalizedCountsPerPs` (`std::function`< double *(`size_t`)> array_out)
- void `getDataNormalizedG2` (`std::function`< double *(`size_t`)> array_out)
- void `getBinEdges` (`std::function`< long long *(`size_t`)> array_out)

Protected Member Functions

- bool `next_impl` (`std::vector`< `Tag` > &incoming_tags, `timestamp_t` begin_time, `timestamp_t` end_time) override
update iterator state
- void `clear_impl` () override
clear `Iterator` state.

Friends

- class `HistogramLogBinsImpl`

Additional Inherited Members

8.26.1 Detailed Description

Accumulate time differences into a histogram with logarithmic increasing bin sizes.

This is a multiple start, multiple stop measurement, and works the very same way as the histogram measurement but with logarithmic increasing bin widths. After initializing the measurement (or after an overflow) no data is accumulated in the histogram until the full histogram duration has passed to ensure a balanced count accumulation over the full histogram.

8.26.2 Constructor & Destructor Documentation

8.26.2.1 HistogramLogBins()

```
HistogramLogBins::HistogramLogBins (
    TimeTaggerBase * tagger,
    channel_t click_channel,
    channel_t start_channel,
    double exp_start,
    double exp_stop,
    int32_t n_bins )
```

constructor of a [HistogramLogBins](#) measurement

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>click_channel</i>	channel that increments the count in a bin
<i>start_channel</i>	channel that sets start times relative to which clicks on the click channel are measured
<i>exp_start</i>	exponent for the lowest time differences in the histogram: $10^{\text{exp_start}}$ s, lowest exp_start: -12 => 1ps
<i>exp_stop</i>	exponent for the highest time differences in the histogram: $10^{\text{exp_stop}}$ s
<i>n_bins</i>	total number of bins in the histogram

8.26.2.2 ~HistogramLogBins()

```
HistogramLogBins::~~HistogramLogBins ( )
```

8.26.3 Member Function Documentation

8.26.3.1 clear_impl()

```
void HistogramLogBins::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.26.3.2 getBinEdges()

```
void HistogramLogBins::getBinEdges (
    std::function< long long *(size_t)> array_out )
```

returns the edges of the bins in ps

8.26.3.3 getData()

```
void HistogramLogBins::getData (
    std::function< uint64_t *(size_t)> array_out )
```

returns the absolute counts for the bins

8.26.3.4 getDataNormalizedCountsPerPs()

```
void HistogramLogBins::getDataNormalizedCountsPerPs (
    std::function< double *(size_t)> array_out )
```

returns the counts normalized by the binwidth of each bin

8.26.3.5 getDataNormalizedG2()

```
void HistogramLogBins::getDataNormalizedG2 (
    std::function< double *(size_t)> array_out )
```

returns the counts normalized by the binwidth and the average count rate. This matches the implementation of [Correlation::getDataNormalized](#)

8.26.3.6 next_impl()

```
bool HistogramLogBins::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.26.4 Friends And Related Function Documentation

8.26.4.1 HistogramLogBinsImpl

```
friend class HistogramLogBinsImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.27 Iterator Class Reference

a simple event queue

```
#include <Iterators.h>
```

Inheritance diagram for Iterator:



Public Member Functions

- [Iterator](#) ([TimeTaggerBase](#) *[tagger](#), [channel_t](#) [channel](#))
standard constructor
- [~Iterator](#) ()
- [timestamp_t](#) [next](#) ()
get next timestamp
- [uint64_t](#) [size](#) ()
get queue size

Protected Member Functions

- [bool](#) [next_impl](#) ([std::vector](#)< [Tag](#) > &[incoming_tags](#), [timestamp_t](#) [begin_time](#), [timestamp_t](#) [end_time](#)) [override](#)
update iterator state
- [void](#) [clear_impl](#) () [override](#)
clear [Iterator](#) state.

Friends

- [class](#) [IteratorImpl](#)

Additional Inherited Members

8.27.1 Detailed Description

a simple event queue

A simple [Iterator](#), just keeping a first-in first-out queue of event timestamps.

Deprecated use [TimeTagStream](#)

8.27.2 Constructor & Destructor Documentation

8.27.2.1 [Iterator](#)()

```
Iterator::Iterator (
    TimeTaggerBase * tagger,
    channel_t channel )
```

standard constructor

Parameters

<i>tagger</i>	the backend
<i>channel</i>	the channel to get events from

8.27.2.2 ~Iterator()

```
Iterator::~~Iterator ( )
```

8.27.3 Member Function Documentation

8.27.3.1 clear_impl()

```
void Iterator::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.27.3.2 next()

```
timestamp_t Iterator::next ( )
```

get next timestamp

get the next timestamp from the queue.

8.27.3.3 next_impl()

```
bool Iterator::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.27.3.4 size()

```
uint64_t Iterator::size ( )
```

get queue size

8.27.4 Friends And Related Function Documentation**8.27.4.1 IteratorImpl**

```
friend class IteratorImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.28 IteratorBase Class Reference

Base class for all iterators.

```
#include <TimeTagger.h>
```

Inheritance diagram for IteratorBase:



Public Member Functions

- virtual `~IteratorBase()`
destructor
- void `start()`
start the iterator
- void `startFor(timestamp_t capture_duration, bool clear=true)`

- *start the iterator, and stops it after the capture_duration*
- bool `waitUntilFinished` (int64_t timeout=-1)
wait until the iterator has finished running.
- void `stop` ()
stop the iterator
- void `clear` ()
*clear *Iterator* state.*
- bool `isRunning` ()
*query the *Iterator* state.*
- `timestamp_t` `getCaptureDuration` ()
query the evaluation time

Protected Member Functions

- `IteratorBase` (`TimeTaggerBase` *tagger)
standard constructor
- void `registerChannel` (`channel_t` channel)
register a channel
- void `unregisterChannel` (`channel_t` channel)
unregister a channel
- `channel_t` `getNewVirtualChannel` ()
allocate a new virtual output channel for this iterator
- void `finishInitialization` ()
method to call after finishing the initialization of the measurement
- virtual void `clear_impl` ()
*clear *Iterator* state.*
- virtual void `on_start` ()
callback when the measurement class is started
- virtual void `on_stop` ()
callback when the measurement class is stopped
- void `lock` ()
acquire update lock
- void `unlock` ()
release update lock
- `OrderedBarrier::OrderInstance` `parallelize` (`OrderedPipeline` &pipeline)
release lock and continue work in parallel
- std::unique_lock< std::mutex > `getLock` ()
acquire update lock
- virtual bool `next_impl` (std::vector< `Tag` > &incoming_tags, `timestamp_t` begin_time, `timestamp_t` end_time)=0
update iterator state
- void `finish_running` ()

Protected Attributes

- std::set< `channel_t` > `channels_registered`
list of channels used by the iterator
- bool `running`
running state of the iterator
- bool `autostart`
- `TimeTaggerBase` * `tagger`
- `timestamp_t` `capture_duration`

Friends

- class [TimeTaggerRunner](#)
- class [TimeTaggerProxy](#)
- class [SynchronizedMeasurements](#)

8.28.1 Detailed Description

Base class for all iterators.

8.28.2 Constructor & Destructor Documentation

8.28.2.1 IteratorBase()

```
IteratorBase::IteratorBase (
    TimeTaggerBase * tagger ) [protected]
```

standard constructor

will register with the [TimeTagger](#) backend.

8.28.2.2 ~IteratorBase()

```
virtual IteratorBase::~~IteratorBase ( ) [virtual]
```

destructor

will stop and unregister prior finalization.

8.28.3 Member Function Documentation

8.28.3.1 clear()

```
void IteratorBase::clear ( )
```

clear [iterator](#) state.

8.28.3.2 clear_impl()

```
virtual void IteratorBase::clear_impl ( ) [inline], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented in [Flim](#), [FlimAbstract](#), [CustomMeasurementBase](#), [EventGenerator](#), [FileWriter](#), [Scope](#), [Correlation](#), [HistogramLogBins](#), [Histogram](#), [TimeDifferencesND](#), [Histogram2D](#), [TimeDifferences](#), [StartStop](#), [Dump](#), [TimeTagStream](#), [Iterator](#), [Countrate](#), [Counter](#), [CountBetweenMarkers](#), and [Combiner](#).

8.28.3.3 finish_running()

```
void IteratorBase::finish_running ( ) [protected]
```

8.28.3.4 finishInitialization()

```
void IteratorBase::finishInitialization ( ) [protected]
```

method to call after finishing the initialization of the measurement

8.28.3.5 getCaptureDuration()

```
timestamp_t IteratorBase::getCaptureDuration ( )
```

query the evaluation time

Query the total capture duration since the last call to clear. This might have a wrong amount of time if there were some overflows within this range.

Returns

capture duration of the data

8.28.3.6 getLock()

```
std::unique_lock<std::mutex> IteratorBase::getLock ( ) [protected]
```

acquire update lock

All mutable operations on a iterator are guarded with an update mutex. Implementers are adviced to lock an iterator, whenever internal state is queried or changed.

Returns

a lock object, which releases the lock when this instance is freed

8.28.3.7 getNewVirtualChannel()

```
channel_t IteratorBase::getNewVirtualChannel ( ) [protected]
```

allocate a new virtual output channel for this iterator

8.28.3.8 isRunning()

```
bool IteratorBase::isRunning ( )
```

query the [Iterator](#) state.

Fetches if this iterator is running.

8.28.3.9 lock()

```
void IteratorBase::lock ( ) [protected]
```

acquire update lock

All mutable operations on a iterator are guarded with an update mutex. Implementers are adviced to [lock\(\)](#) an iterator, whenever internal state is queried or changed.

Deprecated use [getLock](#)

8.28.3.10 next_impl()

```
virtual bool IteratorBase::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [protected], [pure virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implemented in [FlimAbstract](#), [CustomMeasurementBase](#), [EventGenerator](#), [FileWriter](#), [ConstantFractionDiscriminator](#), [Scope](#), [Correlation](#), [HistogramLogBins](#), [Histogram](#), [TimeDifferencesND](#), [Histogram2D](#), [TimeDifferences](#), [StartStop](#), [Dump](#), [TimeTagStream](#), [Iterator](#), [FrequencyMultiplier](#), [GatedChannel](#), [TriggerOnCountrate](#), [DelayedChannel](#), [Countrate](#), [Coincidences](#), [Counter](#), [CountBetweenMarkers](#), and [Combiner](#).

8.28.3.11 on_start()

```
virtual void IteratorBase::on_start ( ) [inline], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented in [FlimAbstract](#), [CustomMeasurementBase](#), [EventGenerator](#), [FileWriter](#), [ConstantFractionDiscriminator](#), [Histogram](#), [TimeDifferencesND](#), [TimeDifferences](#), [StartStop](#), [Dump](#), [TriggerOnCountrate](#), [DelayedChannel](#), [Countrate](#), and [Counter](#).

8.28.3.12 on_stop()

```
virtual void IteratorBase::on_stop ( ) [inline], [protected], [virtual]
```

callback when the measurement class is stopped

This function is guarded by the update lock.

Reimplemented in [CustomMeasurementBase](#), [FileWriter](#), and [Dump](#).

8.28.3.13 parallelize()

```
OrderedBarrier::OrderInstance IteratorBase::parallelize (
    OrderedPipeline & pipeline ) [protected]
```

release lock and continue work in parallel

The measurement's lock is released, allowing this measurement to continue, while still executing work in parallel.

Returns

a ordered barrier instance that can be synced afterwards.

8.28.3.14 registerChannel()

```
void IteratorBase::registerChannel (  
    channel_t channel ) [protected]
```

register a channel

Only channels registered by any iterator attached to a backend are delivered over the usb.

Parameters

<i>channel</i>	the channel
----------------	-------------

8.28.3.15 start()

```
void IteratorBase::start ( )
```

start the iterator

The default behavior for iterators is to start automatically on creation.

8.28.3.16 startFor()

```
void IteratorBase::startFor (
    timestamp_t capture_duration,
    bool clear = true )
```

start the iterator, and stops it after the capture_duration

Parameters

<i>capture_duration</i>	capture duration until the measurement is stopped
<i>clear</i>	resets the data acquired

When the startFor is called before the previous measurement has ended and the clear parameter is set to false, then the passed capture_duration will be added on top to the current max_capture_duration

8.28.3.17 stop()

```
void IteratorBase::stop ( )
```

stop the iterator

The iterator is put into the STOPPED state, but will still be registered with the backend.

8.28.3.18 unlock()

```
void IteratorBase::unlock ( ) [protected]
```

release update lock

see [lock\(\)](#)

Deprecated use getLock

8.28.3.19 unregisterChannel()

```
void IteratorBase::unregisterChannel (
    channel_t channel ) [protected]
```

unregister a channel

Parameters

<i>channel</i>	the channel
----------------	-------------

8.28.3.20 waitUntilFinished()

```
bool IteratorBase::waitUntilFinished (
    int64_t timeout = -1 )
```

wait until the iterator has finished running.

Parameters

<i>timeout</i>	time in milliseconds to wait for the measurements. If negative, wait until finished.
----------------	--

waitUntilFinished will wait according to the timeout and return true if the iterator finished or false if not. Furthermore, when waitUntilFinished is called on a iterator running indefinitely, it will log an error and return immediately.

8.28.4 Friends And Related Function Documentation**8.28.4.1 SynchronizedMeasurements**

```
friend class SynchronizedMeasurements [friend]
```

8.28.4.2 TimeTaggerProxy

```
friend class TimeTaggerProxy [friend]
```

8.28.4.3 TimeTaggerRunner

```
friend class TimeTaggerRunner [friend]
```

8.28.5 Member Data Documentation

8.28.5.1 autostart

```
bool IteratorBase::autostart [protected]
```

8.28.5.2 capture_duration

```
timestamp_t IteratorBase::capture_duration [protected]
```

8.28.5.3 channels_registered

```
std::set<channel_t> IteratorBase::channels_registered [protected]
```

list of channels used by the iterator

8.28.5.4 running

```
bool IteratorBase::running [protected]
```

running state of the iterator

8.28.5.5 tagger

```
TimeTaggerBase* IteratorBase::tagger [protected]
```

The documentation for this class was generated from the following file:

- [TimeTagger.h](#)

8.29 OrderedBarrier Class Reference

```
#include <TimeTagger.h>
```

Classes

- class [OrderInstance](#)

Public Member Functions

- [OrderedBarrier](#) ()
- [~OrderedBarrier](#) ()
- [OrderInstance queue](#) ()
- void [waitUntilFinished](#) ()

Friends

- class [OrderInstance](#)

8.29.1 Constructor & Destructor Documentation

8.29.1.1 OrderedBarrier()

```
OrderedBarrier::OrderedBarrier ( )
```

8.29.1.2 ~OrderedBarrier()

```
OrderedBarrier::~~OrderedBarrier ( )
```

8.29.2 Member Function Documentation

8.29.2.1 queue()

```
OrderInstance OrderedBarrier::queue ( )
```

8.29.2.2 waitUntilFinished()

```
void OrderedBarrier::waitUntilFinished ( )
```

8.29.3 Friends And Related Function Documentation

8.29.3.1 OrderInstance

```
friend class OrderInstance [friend]
```

The documentation for this class was generated from the following file:

- [TimeTagger.h](#)

8.30 OrderedPipeline Class Reference

```
#include <TimeTagger.h>
```

Public Member Functions

- [OrderedPipeline](#) ()
- [~OrderedPipeline](#) ()

Friends

- class [IteratorBase](#)

8.30.1 Constructor & Destructor Documentation

8.30.1.1 OrderedPipeline()

```
OrderedPipeline::OrderedPipeline ( )
```

8.30.1.2 ~OrderedPipeline()

```
OrderedPipeline::~~OrderedPipeline ( )
```

8.30.2 Friends And Related Function Documentation

8.30.2.1 IteratorBase

```
friend class IteratorBase [friend]
```

The documentation for this class was generated from the following file:

- [TimeTagger.h](#)

8.31 OrderedBarrier::OrderInstance Class Reference

```
#include <TimeTagger.h>
```

Public Member Functions

- [OrderInstance](#) ()
- [OrderInstance](#) ([OrderedBarrier](#) *parent, uint64_t instance_id)
- [~OrderInstance](#) ()
- void [sync](#) ()
- void [release](#) ()

Friends

- class [OrderedBarrier](#)

8.31.1 Constructor & Destructor Documentation

8.31.1.1 OrderInstance() [1/2]

```
OrderedBarrier::OrderInstance::OrderInstance ( )
```

8.31.1.2 OrderInstance() [2/2]

```
OrderedBarrier::OrderInstance::OrderInstance (
    OrderedBarrier * parent,
    uint64_t instance_id )
```

8.31.1.3 ~OrderInstance()

```
OrderedBarrier::OrderInstance::~~OrderInstance ( )
```

8.31.2 Member Function Documentation

8.31.2.1 `release()`

```
void OrderedBarrier::OrderInstance::release ( )
```

8.31.2.2 `sync()`

```
void OrderedBarrier::OrderInstance::sync ( )
```

8.31.3 Friends And Related Function Documentation

8.31.3.1 `OrderedBarrier`

```
friend class OrderedBarrier [friend]
```


The documentation for this class was generated from the following file:

- [TimeTagger.h](#)

8.32 Scope Class Reference

```
#include <Iterators.h>
```

Inheritance diagram for Scope:



Public Member Functions

- [Scope](#) ([TimeTaggerBase](#) *[tagger](#), [std::vector](#)< [channel_t](#) > [event_channels](#), [channel_t](#) [trigger_channel](#), [timestamp_t](#) [window_size](#)=1000000000, [int32_t](#) [n_traces](#)=1, [int32_t](#) [n_max_events](#)=1000)
constructor of a [Scope](#) measurement
- [~Scope](#) ()
- [bool](#) [ready](#) ()
- [int32_t](#) [triggered](#) ()
- [std::vector](#)< [std::vector](#)< [Event](#) > > [getData](#) ()
- [timestamp_t](#) [getWindowSize](#) ()

Protected Member Functions

- [bool](#) [next_impl](#) ([std::vector](#)< [Tag](#) > &[incoming_tags](#), [timestamp_t](#) [begin_time](#), [timestamp_t](#) [end_time](#)) override
update iterator state
- [void](#) [clear_impl](#) () override
clear [Iterator](#) state.

Friends

- class [ScopeImpl](#)

Additional Inherited Members

8.32.1 Constructor & Destructor Documentation

8.32.1.1 Scope()

```
Scope::Scope (
    TimeTaggerBase * tagger,
    std::vector< channel\_t > event\_channels,
    channel\_t trigger\_channel,
    timestamp\_t window\_size = 1000000000,
    int32\_t n\_traces = 1,
    int32\_t n\_max\_events = 1000 )
```

constructor of a [Scope](#) measurement

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>event_channels</i>	channels which are captured
<i>trigger_channel</i>	channel that starts a new trace
<i>window_size</i>	window time of each trace
<i>n_traces</i>	amount of traces (n_traces < 1, automatic retrigger)
<i>n_max_events</i>	maximum number of tags in each trace

8.32.1.2 ~Scope()

```
Scope::~~Scope ( )
```

8.32.2 Member Function Documentation

8.32.2.1 clear_impl()

```
void Scope::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.32.2.2 getData()

```
std::vector<std::vector<Event> > Scope::getData ( )
```

8.32.2.3 getWindowSize()

```
timestamp\_t Scope::getWindowSize ( )
```

8.32.2.4 next_impl()

```
bool Scope::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp\_t begin_time,
    timestamp\_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.32.2.5 ready()

```
bool Scope::ready ( )
```

8.32.2.6 triggered()

```
int32_t Scope::triggered ( )
```

8.32.3 Friends And Related Function Documentation**8.32.3.1 ScopeImpl**

```
friend class ScopeImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.33 StartStop Class Reference

simple start-stop measurement

```
#include <Iterators.h>
```

Inheritance diagram for StartStop:



Public Member Functions

- `StartStop` (`TimeTaggerBase` *tagger, `channel_t` click_channel, `channel_t` start_channel=CHANNEL_UNU↔SED, `timestamp_t` binwidth=1000)
constructor of `StartStop`
- `~StartStop` ()
- `void getData` (`std::function`< long long *(size_t, size_t)> array_out)

Protected Member Functions

- `bool next_impl` (`std::vector`< `Tag` > &incoming_tags, `timestamp_t` begin_time, `timestamp_t` end_time) override
update iterator state
- `void clear_impl` () override
clear `Iterator` state.
- `void on_start` () override
callback when the measurement class is started

Friends

- class `StartStopImpl`

Additional Inherited Members

8.33.1 Detailed Description

simple start-stop measurement

This class performs a start-stop measurement between two channels and stores the time differences in a histogram. The histogram resolution is specified beforehand (binwidth) but the histogram range is unlimited. It is adapted to the largest time difference that was detected. Thus all pairs of subsequent clicks are registered.

Be aware, on long-running measurements this may considerably slow down system performance and even crash the system entirely when attached to an unsuitable signal source.

8.33.2 Constructor & Destructor Documentation

8.33.2.1 StartStop()

```
StartStop::StartStop (
    TimeTaggerBase * tagger,
    channel_t click_channel,
    channel_t start_channel = CHANNEL_UNUSED,
    timestamp_t binwidth = 1000 )
```

constructor of [StartStop](#)

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>click_channel</i>	channel for stop clicks
<i>start_channel</i>	channel for start clicks
<i>binwidth</i>	width of one histogram bin in ps

8.33.2.2 ~StartStop()

```
StartStop::~~StartStop ( )
```

8.33.3 Member Function Documentation

8.33.3.1 clear_impl()

```
void StartStop::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.33.3.2 getData()

```
void StartStop::getData (
    std::function< long long *(size_t, size_t)> array_out )
```

8.33.3.3 next_impl()

```
bool StartStop::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.33.3.4 on_start()

```
void StartStop::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.33.4 Friends And Related Function Documentation

8.33.4.1 StartStopImpl

```
friend class StartStopImpl [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.34 SynchronizedMeasurements Class Reference

start, stop and clear several measurements synchronized

```
#include <Iterators.h>
```

Public Member Functions

- [SynchronizedMeasurements](#) ([TimeTaggerBase](#) *tagger)
construct a [SynchronizedMeasurements](#) object
- [~SynchronizedMeasurements](#) ()
- void [registerMeasurement](#) ([IteratorBase](#) *measurement)
register a measurement (iterator) to the SynchronizedMeasurements-group.
- void [unregisterMeasurement](#) ([IteratorBase](#) *measurement)
unregister a measurement (iterator) from the SynchronizedMeasurements-group.
- void [clear](#) ()
clear all registered measurements synchronously
- void [start](#) ()
start all registered measurements synchronously
- void [stop](#) ()
stop all registered measurements synchronously
- void [startFor](#) ([timestamp_t](#) capture_duration, bool [clear](#)=true)
start all registered measurements synchronously, and stops them after the capture_duration
- bool [waitUntilFinished](#) ([int64_t](#) timeout=-1)
wait until all registered measurements have finished running.
- bool [isRunning](#) ()
check if any iterator is running
- [TimeTaggerBase](#) * [getTagger](#) ()

Protected Member Functions

- void [runCallback](#) ([TimeTaggerBase::IteratorCallback](#) callback, [std::unique_lock](#)< [std::mutex](#) > &lk, bool block=true)
run a callback on all registered measurements synchronously

Friends

- class [TimeTaggerProxy](#)

8.34.1 Detailed Description

start, stop and clear several measurements synchronized

For the case that several measurements should be started, stopped or cleared at the very same time, a [SynchronizedMeasurements](#) object can be create to which all the measurements (also called iterators) can be registered with [.registerMeasurement\(measurement\)](#). Calling [.stop\(\)](#), [.start\(\)](#) or [.clear\(\)](#) on the [SynchronizedMeasurements](#) object will call the respective method on each of the registered measurements at the very same time. That means that all measurements taking part will have processed the very same time tags.

8.34.2 Constructor & Destructor Documentation

8.34.2.1 SynchronizedMeasurements()

```
SynchronizedMeasurements::SynchronizedMeasurements (
    TimeTaggerBase * tagger )
```

construct a [SynchronizedMeasurements](#) object

Parameters

<i>tagger</i>	reference to a TimeTagger
---------------	---

8.34.2.2 ~SynchronizedMeasurements()

```
SynchronizedMeasurements::~~SynchronizedMeasurements ( )
```

8.34.3 Member Function Documentation

8.34.3.1 clear()

```
void SynchronizedMeasurements::clear ( )
```

clear all registered measurements synchronously

8.34.3.2 getTagger()

```
TimeTaggerBase* SynchronizedMeasurements::getTagger ( )
```

Returns a proxy tagger object, which shall be used to create immediately registered measurements. Those measurements will not start automatically.

8.34.3.3 isRunning()

```
bool SynchronizedMeasurements::isRunning ( )
```

check if any iterator is running

8.34.3.4 registerMeasurement()

```
void SynchronizedMeasurements::registerMeasurement (
    IteratorBase * measurement )
```

register a measurement (iterator) to the SynchronizedMeasurements-group.

All available methods called on the [SynchronizedMeasurements](#) will happen at the very same time for all the registered measurements.

8.34.3.5 runCallback()

```
void SynchronizedMeasurements::runCallback (
    TimeTaggerBase::IteratorCallback callback,
    std::unique_lock< std::mutex > & lk,
    bool block = true ) [protected]
```

run a callback on all registered measurements synchronously

Please keep in mind that the callback is copied for each measurement. So please avoid big captures.

8.34.3.6 start()

```
void SynchronizedMeasurements::start ( )
```

start all registered measurements synchronously

8.34.3.7 startFor()

```
void SynchronizedMeasurements::startFor (
    timestamp_t capture_duration,
    bool clear = true )
```

start all registered measurements synchronously, and stops them after the capture_duration

8.34.3.8 stop()

```
void SynchronizedMeasurements::stop ( )
```

stop all registered measurements synchronously

8.34.3.9 unregisterMeasurement()

```
void SynchronizedMeasurements::unregisterMeasurement (
    IteratorBase * measurement )
```

unregister a measurement (iterator) from the SynchronizedMeasurements-group.

Stops synchronizing calls on the selected measurement, if the measurement is not within this synchronized group, the method does nothing.

8.34.3.10 waitUntilFinished()

```
bool SynchronizedMeasurements::waitUntilFinished (
    int64_t timeout = -1 )
```

wait until all registered measurements have finished running.

Parameters

<i>timeout</i>	time in milliseconds to wait for the measurements. If negative, wait until finished.
----------------	--

waitUntilFinished will wait according to the timeout and return true if all measurements finished or false if not. Furthermore, when waitUntilFinished is called on a set running indefinitely, it will log an error and return immediately.

8.34.4 Friends And Related Function Documentation**8.34.4.1 TimeTaggerProxy**

```
friend class TimeTaggerProxy [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.35 Tag Struct Reference

a single event on a channel

```
#include <TimeTagger.h>
```

Public Types

- enum [Type](#) : unsigned char {
[Type::TimeTag](#) = 0, [Type::Error](#) = 1, [Type::OverflowBegin](#) = 2, [Type::OverflowEnd](#) = 3,
[Type::MissedEvents](#) = 4 }

Public Attributes

- enum [Tag::Type](#) type
- char [reserved](#)
- unsigned short [missed_events](#)
- [channel_t](#) channel
- [timestamp_t](#) time

8.35.1 Detailed Description

a single event on a channel

Channel events are passed from the backend to registered iterators by the `IteratorBase::next()` callback function.

A [Tag](#) describes a single event on a channel.

8.35.2 Member Enumeration Documentation

8.35.2.1 Type

```
enum Tag::Type : unsigned char [strong]
```

This enum marks what kind of event this object represents: TimeTag: a normal event from any input channel
Error: an error in the internal data processing, e.g. on plugging the external clock. This invalidates the global time
OverflowBegin: this marks the begin of an interval with incomplete data because of too high data rates
OverflowEnd: this marks the end of the interval. All events, which were lost in this interval, have been handled
MissedEvents: this virtual event signals the amount of lost events per channel within an overflow interval. Repeated usage for higher amounts of events

Enumerator

TimeTag	
Error	
OverflowBegin	
OverflowEnd	
MissedEvents	

8.35.3 Member Data Documentation

8.35.3.1 channel

```
channel_t Tag::channel
```

8.35.3.2 missed_events

```
unsigned short Tag::missed_events
```

8.35.3.3 reserved

```
char Tag::reserved
```

8.35.3.4 time

```
timestamp_t Tag::time
```

8.35.3.5 type

```
enum Tag::Type Tag::type
```

The documentation for this struct was generated from the following file:


- [TimeTagger.h](#)

8.36 TimeDifferences Class Reference

Accumulates the time differences between clicks on two channels in one or more histograms.

```
#include <Iterators.h>
```

Inheritance diagram for TimeDifferences:



Public Member Functions

- [TimeDifferences](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) click_channel, [channel_t](#) start_channel=[CHANNEL_UNUSED](#), [channel_t](#) next_channel=[CHANNEL_UNUSED](#), [channel_t](#) sync_channel=[CHANNEL_UNUSED](#), [timestamp_t](#) binwidth=1000, [int32_t](#) n_bins=1000, [int32_t](#) n_histograms=1)
constructor of a [TimeDifferences](#) measurement
- [~TimeDifferences](#) ()
- void [getData](#) (std::function< [int32_t](#) *([size_t](#), [size_t](#))> array_out)
returns a two-dimensional array of size 'n_bins' by 'n_histograms' containing the histograms
- void [getIndex](#) (std::function< long long *([size_t](#))> array_out)
returns a vector of size 'n_bins' containing the time bins in ps
- void [setMaxCounts](#) ([uint64_t](#) max_counts)
set the number of rollovers at which the measurement stops integrating
- [uint64_t](#) [getCounts](#) ()
returns the number of rollovers (histogram index resets)
- bool [ready](#) ()
returns 'true' when the required number of rollovers set by 'setMaxCounts' has been reached

Protected Member Functions

- bool `next_impl` (std::vector< `Tag` > &incoming_tags, `timestamp_t` begin_time, `timestamp_t` end_time) override
update iterator state
- void `clear_impl` () override
clear `Iterator` state.
- void `on_start` () override
callback when the measurement class is started

Friends

- class `TimeDifferencesImpl`< `TimeDifferences` >

Additional Inherited Members

8.36.1 Detailed Description

Accumulates the time differences between clicks on two channels in one or more histograms.

A multidimensional histogram measurement with the option up to include three additional channels that control how to step through the indices of the histogram array. This is a very powerful and generic measurement. You can use it to record cross-correlation, lifetime measurements, fluorescence lifetime imaging and many more measurements based on pulsed excitation. Specifically, the measurement waits for a tag on the 'start_channel', then measures the time difference between the start tag and all subsequent tags on the 'click_channel' and stores them in a histogram. If no 'start_channel' is specified, the 'click_channel' is used as 'start_channel' corresponding to an auto-correlation measurement. The histogram has a number 'n_bins' of bins of bin width 'binwidth'. Clicks that fall outside the histogram range are discarded. Data accumulation is performed independently for all start tags. This type of measurement is frequently referred to as 'multiple start, multiple stop' measurement and corresponds to a full auto- or cross-correlation measurement.

The data obtained from subsequent start tags can be accumulated into the same histogram (one- dimensional measurement) or into different histograms (two-dimensional measurement). In this way, you can perform more general two-dimensional time-difference measurements. The parameter 'n_histograms' specifies the number of histograms. After each tag on the 'next_channel', the histogram index is incremented by one and reset to zero after reaching the last valid index. The measurement starts with the first tag on the 'next_channel'.

You can also provide a synchronization trigger that resets the histogram index by specifying a 'sync_channel'. The measurement starts when a tag on the 'sync_channel' arrives with a subsequent tag on 'next_channel'. When a rollover occurs, the accumulation is stopped until the next sync and subsequent next signal. A sync signal before a rollover will stop the accumulation, reset the histogram index and a subsequent signal on the 'next_channel' starts the accumulation again.

Typically, you will run the measurement indefinitely until stopped by the user. However, it is also possible to specify the maximum number of rollovers of the histogram index. In this case the measurement stops when the number of rollovers has reached the specified value. This means that for both a one-dimensional and for a two-dimensional measurement, it will measure until the measurement went through the specified number of rollovers / sync tags.

8.36.2 Constructor & Destructor Documentation

8.36.2.1 TimeDifferences()

```
TimeDifferences::TimeDifferences (
    TimeTaggerBase * tagger,
    channel_t click_channel,
    channel_t start_channel = CHANNEL_UNUSED,
    channel_t next_channel = CHANNEL_UNUSED,
    channel_t sync_channel = CHANNEL_UNUSED,
    timestamp_t binwidth = 1000,
    int32_t n_bins = 1000,
    int32_t n_histograms = 1 )
```

constructor of a [TimeDifferences](#) measurement

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>click_channel</i>	channel that increments the count in a bin
<i>start_channel</i>	channel that sets start times relative to which clicks on the click channel are measured
<i>next_channel</i>	channel that increments the histogram index
<i>sync_channel</i>	channel that resets the histogram index to zero
<i>binwidth</i>	width of one histogram bin in ps
<i>n_bins</i>	number of bins in each histogram
<i>n_histograms</i>	number of histograms

8.36.2.2 ~TimeDifferences()

```
TimeDifferences::~~TimeDifferences ( )
```

8.36.3 Member Function Documentation

8.36.3.1 clear_impl()

```
void TimeDifferences::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.36.3.2 getCounts()

```
uint64_t TimeDifferences::getCounts ( )
```

returns the number of rollovers (histogram index resets)

8.36.3.3 getData()

```
void TimeDifferences::getData (
    std::function< int32_t *(size_t, size_t)> array_out )
```

returns a two-dimensional array of size 'n_bins' by 'n_histograms' containing the histograms

8.36.3.4 getIndex()

```
void TimeDifferences::getIndex (
    std::function< long long *(size_t)> array_out )
```

returns a vector of size 'n_bins' containing the time bins in ps

8.36.3.5 next_impl()

```
bool TimeDifferences::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.36.3.6 on_start()

```
void TimeDifferences::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.36.3.7 ready()

```
bool TimeDifferences::ready ( )
```

returns 'true' when the required number of rollovers set by 'setMaxCounts' has been reached

8.36.3.8 setMaxCounts()

```
void TimeDifferences::setMaxCounts (
    uint64_t max_counts )
```

set the number of rollovers at which the measurement stops integrating

Parameters

<i>max_counts</i>	maximum number of sync/next clicks
-------------------	------------------------------------

8.36.4 Friends And Related Function Documentation

8.36.4.1 TimeDifferencesImpl< TimeDifferences >

```
friend class TimeDifferencesImpl< TimeDifferences > [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.37 TimeDifferencesImpl< T > Class Template Reference

```
#include <Iterators.h>
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.38 TimeDifferencesND Class Reference

Accumulates the time differences between clicks on two channels in a multi-dimensional histogram.

```
#include <Iterators.h>
```

Inheritance diagram for TimeDifferencesND:



Public Member Functions

- `TimeDifferencesND` (`TimeTaggerBase` *tagger, `channel_t` click_channel, `channel_t` start_channel, `std::vector`< `channel_t` > next_channels, `std::vector`< `channel_t` > sync_channels, `std::vector`< `int32_t` > n_hists, `timestamp_t` binwidth, `int32_t` n_bins)
constructor of a `TimeDifferencesND` measurement
- `~TimeDifferencesND` ()
- void `getData` (`std::function`< `int32_t` *(`size_t`, `size_t`)> array_out)
returns a two-dimensional array of size n_bins by all n_hists containing the histograms
- void `getIndex` (`std::function`< `long long` *(`size_t`)> array_out)
returns a vector of size n_bins containing the time bins in ps

Protected Member Functions

- bool `next_impl` (`std::vector`< `Tag` > &incoming_tags, `timestamp_t` begin_time, `timestamp_t` end_time) override
update iterator state
- void `clear_impl` () override
clear `Iterator` state.
- void `on_start` () override
callback when the measurement class is started

Friends

- class [TimeDifferencesNDImpl](#)

Additional Inherited Members

8.38.1 Detailed Description

Accumulates the time differences between clicks on two channels in a multi-dimensional histogram.

This is a multidimensional implementation of the [TimeDifferences](#) measurement class. Please read their documentation first.

This measurement class extends the [TimeDifferences](#) interface for a multidimensional amount of histograms. It captures many multiple start - multiple stop histograms, but with many asynchronous next_channel triggers. After each tag on each next_channel, the histogram index of the associated dimension is incremented by one and reset to zero after reaching the last valid index. The elements of the parameter n_histograms specifies the number of histograms per dimension. The accumulation starts when next_channel has been triggered on all dimensions.

You should provide a synchronization trigger by specifying a sync_channel per dimension. It will stop the accumulation when an associated histogram index rollover occurs. A sync event will also stop the accumulation, reset the histogram index of the associated dimension, and a subsequent event on the corresponding next_channel starts the accumulation again. The synchronization is done asynchronous, so an event on the next_channel increases the histogram index even if the accumulation is stopped. The accumulation starts when a tag on the sync_channel arrives with a subsequent tag on next_channel for all dimensions.

Please use setInputDelay to adjust the latency of all channels. In general, the order of the provided triggers including maximum jitter should be: old start trigger – all sync triggers – all next triggers – new start trigger

8.38.2 Constructor & Destructor Documentation

8.38.2.1 TimeDifferencesND()

```
TimeDifferencesND::TimeDifferencesND (
    TimeTaggerBase * tagger,
    channel_t click_channel,
    channel_t start_channel,
    std::vector< channel_t > next_channels,
    std::vector< channel_t > sync_channels,
    std::vector< int32_t > n_histograms,
    timestamp_t binwidth,
    int32_t n_bins )
```

constructor of a [TimeDifferencesND](#) measurement

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>click_channel</i>	channel that increments the count in a bin
<i>start_channel</i>	channel that sets start times relative to which clicks on the click channel are measured
<i>next_channels</i>	vector of channels that increments the histogram index
<i>sync_channels</i>	vector of channels that resets the histogram index to zero
<i>n_histograms</i>	vector of numbers of histograms per dimension.
<i>binwidth</i>	width of one histogram bin in ps

8.38.2.2 ~TimeDifferencesND()

```
TimeDifferencesND::~TimeDifferencesND ( )
```

8.38.3 Member Function Documentation

8.38.3.1 clear_impl()

```
void TimeDifferencesND::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.38.3.2 getData()

```
void TimeDifferencesND::getData (
    std::function< int32_t *(size_t, size_t)> array_out )
```

returns a two-dimensional array of size `n_bins` by all `n_histograms` containing the histograms

8.38.3.3 getIndex()

```
void TimeDifferencesND::getIndex (
    std::function< long long *(size_t)> array_out )
```

returns a vector of size `n_bins` containing the time bins in ps

8.38.3.4 next_impl()

```
bool TimeDifferencesND::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.38.3.5 on_start()

```
void TimeDifferencesND::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.38.4 Friends And Related Function Documentation**8.38.4.1 TimeDifferencesNDImpl**

```
friend class TimeDifferencesNDImpl [friend]
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.39 TimeTagger Class Reference

backend for the [TimeTagger](#).

```
#include <TimeTagger.h>
```

Inheritance diagram for TimeTagger:



Public Member Functions

- virtual void `reset` ()=0
reset the [TimeTagger](#) object to default settings and detach all iterators
- virtual void `setTestSignalDivider` (int divider)=0
set the divider for the frequency of the test signal
- virtual int `getTestSignalDivider` ()=0
get the divider for the frequency of the test signal
- virtual void `setTriggerLevel` ([channel_t](#) channel, double voltage)=0
set the trigger voltage threshold of a channel
- virtual double `getTriggerLevel` ([channel_t](#) channel)=0
get the trigger voltage threshold of a channel
- virtual [timestamp_t](#) `getHardwareDelayCompensation` ([channel_t](#) channel)=0
get hardware delay compensation of a channel
- virtual void `setInputMux` ([channel_t](#) channel, int mux_mode)=0
configures the input multiplexer
- virtual int `getInputMux` ([channel_t](#) channel)=0
fetches the configuration of the input multiplexer
- virtual void `setConditionalFilter` (std::vector< [channel_t](#) > trigger, std::vector< [channel_t](#) > filtered, bool hardwareDelayCompensation=true)=0
configures the conditional filter
- virtual void `clearConditionalFilter` ()=0
deactivates the conditional filter
- virtual std::vector< [channel_t](#) > `getConditionalFilterTrigger` ()=0
fetches the configuration of the conditional filter
- virtual std::vector< [channel_t](#) > `getConditionalFilterFiltered` ()=0
fetches the configuration of the conditional filter
- virtual void `setNormalization` (std::vector< [channel_t](#) > channel, bool state)=0
enables or disables the normalization of the distribution.
- virtual bool `getNormalization` ([channel_t](#) channel)=0
returns the the normalization of the distribution.
- virtual void `setHardwareBufferSize` (int size)=0
sets the maximum USB buffer size
- virtual int `getHardwareBufferSize` ()=0
queries the size of the USB queue
- virtual void `setStreamBlockSize` (int max_events, int max_latency)=0
sets the maximum events and latency for the stream block size
- virtual int `getStreamBlockSizeEvents` ()=0
- virtual int `getStreamBlockSizeLatency` ()=0
- virtual void `setEventDivider` ([channel_t](#) channel, unsigned int divider)=0
Divides the amount of transmitted edge per channel.
- virtual unsigned int `getEventDivider` ([channel_t](#) channel)=0
Returns the factor of the dividing filter.
- virtual void `autoCalibration` (std::function< double *(size_t)> array_out)=0
runs a calibrations based on the on-chip uncorrelated signal generator.
- virtual std::string `getSerial` ()=0
identifies the hardware by serial number
- virtual std::string `getModel` ()=0
identifies the hardware by Time Tagger Model
- virtual int `getChannelNumberScheme` ()=0
Fetch the configured numbering scheme for this [TimeTagger](#) object.

- virtual `std::vector< double > getDACRange ()=0`
returns the minimum and the maximum voltage of the DACs as a trigger reference
- virtual `void getDistributionCount (std::function< uint64_t *(size_t, size_t)> array_out)=0`
get internal calibration data
- virtual `void getDistributionPSEcs (std::function< long long *(size_t, size_t)> array_out)=0`
get internal calibration data This method is not supported any more on the Time Tagger Ultra series
- virtual `std::vector< channel_t > getChannelList (ChannelEdge type=ChannelEdge::All)=0`
fetch a vector of all physical input channel ids
- virtual `timestamp_t getPsPerClock ()=0`
fetch the duration of each clock cycle in picoseconds
- virtual `std::string getPcbVersion ()=0`
Return the hardware version of the PCB board. Version 0 is everything before mid 2018 and with the channel configuration ZERO. version >= 1 is channel configuration ONE.
- virtual `std::string getFirmwareVersion ()=0`
Return an unique identifier for the applied firmware.
- virtual `std::string getSensorData ()=0`
Show the status of the sensor data from the FPGA and peripherals on the console.
- virtual `void setLED (uint32_t bitmask)=0`
Enforce a state to the LEDs 0: led_status[R] 16: led_status[R] - mux 1: led_status[G] 17: led_status[G] - mux 2: led_status[B] 18: led_status[B] - mux 3: led_power[R] 19: led_power[R] - mux 4: led_power[G] 20: led_power[G] - mux 5: led_power[B] 21: led_power[B] - mux 6: led_clock[R] 22: led_clock[R] - mux 7: led_clock[G] 23: led_clock[G] - mux 8: led_clock[B] 24: led_clock[B] - mux.
- virtual `std::string getLicenseInfo ()=0`
- virtual `uint32_t factoryAccess (uint32_t pw, uint32_t addr, uint32_t data, uint32_t mask)=0`
Direct read/write access to WireIn/WireOuts in FPGA (mask==0 for readonly)
- virtual `void setSoundFrequency (uint32_t freq_hz)=0`
Set the Time Taggers internal buzzer to a frequency in Hz (freq_hz==0 to disable)

Additional Inherited Members

8.39.1 Detailed Description

backend for the [TimeTagger](#).

The [TimeTagger](#) class connects to the hardware, and handles the communication over the usb. There may be only one instance of the backend per physical device.

8.39.2 Member Function Documentation

8.39.2.1 autoCalibration()

```
virtual void TimeTagger::autoCalibration (
    std::function< double *(size_t)> array_out ) [pure virtual]
```

runs a calibrations based on the on-chip uncorrelated signal generator.

8.39.2.2 clearConditionalFilter()

```
virtual void TimeTagger::clearConditionalFilter ( ) [pure virtual]
```

deactivates the conditional filter

equivilent to setConditionalFilter({},{})

8.39.2.3 factoryAccess()

```
virtual uint32_t TimeTagger::factoryAccess (
    uint32_t pw,
    uint32_t addr,
    uint32_t data,
    uint32_t mask ) [pure virtual]
```

Direct read/write access to WireIn/WireOuts in FPGA (mask==0 for readonly)

DO NOT USE. Only for internal debug purposes.

8.39.2.4 getChannelList()

```
virtual std::vector<channel_t> TimeTagger::getChannelList (
    ChannelEdge type = ChannelEdge::All ) [pure virtual]
```

fetch a vector of all physical input channel ids

The function returns the channel of all rising and falling edges. For example for the Time Tagger 20 (8 input channels) TT_CHANNEL_NUMBER_SCHEME_ZERO: {0,1,2,3,4,5,6,7,8,9,10,11,12,13,14,15} and for TT_CHANNEL_NUMBER_SCHEME_ONE: {-8,-7,-6,-5,-4,-3,-2,-1,1,2,3,4,5,6,7,8}

TT_CHANNEL_RISING_EDGES returns only the rising edges SCHEME_ONE: {1,2,3,4,5,6,7,8} and TT_CHANNEL_FALLING_EDGES return only the falling edges SCHEME_ONE: {-1,-2,-3,-4,-5,-6,-7,-8} which are the invertedChannels of the rising edges.

8.39.2.5 getChannelNumberScheme()

```
virtual int TimeTagger::getChannelNumberScheme ( ) [pure virtual]
```

Fetch the configured numbering scheme for this [TimeTagger](#) object.

Please see [setTimeTaggerChannelNumberScheme\(\)](#) for details.

8.39.2.6 getConditionalFilterFiltered()

```
virtual std::vector<channel_t> TimeTagger::getConditionalFilterFiltered ( ) [pure virtual]
```

fetches the configuration of the conditional filter

see setConditionalFilter

8.39.2.7 getConditionalFilterTrigger()

```
virtual std::vector<channel_t> TimeTagger::getConditionalFilterTrigger ( ) [pure virtual]
```

fetches the configuration of the conditional filter

see setConditionalFilter

8.39.2.8 getDACRange()

```
virtual std::vector<double> TimeTagger::getDACRange ( ) [pure virtual]
```

returns the minumum and the maximum voltage of the DACs as a trigger reference

8.39.2.9 getDistributionCount()

```
virtual void TimeTagger::getDistributionCount (
    std::function< uint64_t *(size_t, size_t)> array_out ) [pure virtual]
```

get internal calibration data

8.39.2.10 getDistributionPSecs()

```
virtual void TimeTagger::getDistributionPSecs (
    std::function< long long *(size_t, size_t)> array_out ) [pure virtual]
```

get internal calibration data This method is not supported any more on the Time Tagger Ultra series

Deprecated**8.39.2.11 getEventDivider()**

```
virtual unsigned int TimeTagger::getEventDivider (
    channel_t channel ) [pure virtual]
```

Returns the factor of the dividing filter.

See setEventDivider for further details.

Parameters

<i>channel</i>	channel to be queried
----------------	-----------------------

Returns

the configured divider

8.39.2.12 getFirmwareVersion()

```
virtual std::string TimeTagger::getFirmwareVersion ( ) [pure virtual]
```

Return an unique identifier for the applied firmware.

This function returns a comma separated list of the firmware version with

- the device identifier: TT-20 or TT-Ultra
- the firmware identifier: FW 3
- optional the timestamp of the assembling of the firmware
- the firmware identifier of the USB chip: OK 1.30 eg "TT-Ultra, FW 3, TS 2018-11-13 22:57:32, OK 1.30"

8.39.2.13 getHardwareBufferSize()

```
virtual int TimeTagger::getHardwareBufferSize ( ) [pure virtual]
```

queries the size of the USB queue

See setHardwareBufferSize for more information.

Returns

the actual size of the USB queue in events

8.39.2.14 getHardwareDelayCompensation()

```
virtual timestamp_t TimeTagger::getHardwareDelayCompensation (
    channel_t channel ) [pure virtual]
```

get hardware delay compensation of a channel

The physical input delays are calibrated and compensated. However this compensation is implemented after the conditional filter and so affects its result. This function queries the effective input delay, which compensates the hardware delay.

Parameters

<i>channel</i>	the channel
----------------	-------------

Returns

the hardware delay compensation in picoseconds

8.39.2.15 getInputMux()

```
virtual int TimeTagger::getInputMux (
    channel_t channel ) [pure virtual]
```

fetches the configuration of the input multiplexer

Parameters

<i>channel</i>	the physical channel of the input multiplexer
----------------	---

Returns

the configuration mode of the input multiplexer

8.39.2.16 getLicenseInfo()

```
virtual std::string TimeTagger::getLicenseInfo ( ) [pure virtual]
```

Fetches and parses the current installed license on this device

Returns

a human readable string containing all information about the license on this device

8.39.2.17 getModel()

```
virtual std::string TimeTagger::getModel ( ) [pure virtual]
```

identifies the hardware by Time Tagger Model

8.39.2.18 getNormalization()

```
virtual bool TimeTagger::getNormalization (
    channel_t channel ) [pure virtual]
```

returns the the normalization of the distribution.

Refer the Manual for a description of this function.

Parameters

<i>channel</i>	the channel to query
----------------	----------------------

Returns

if the normalization is enabled

8.39.2.19 getPcbVersion()

```
virtual std::string TimeTagger::getPcbVersion ( ) [pure virtual]
```

Return the hardware version of the PCB board. Version 0 is everything before mid 2018 and with the channel configuration ZERO. version ≥ 1 is channel configuration ONE.

8.39.2.20 getPsPerClock()

```
virtual timestamp_t TimeTagger::getPsPerClock ( ) [pure virtual]
```

fetch the duration of each clock cycle in picoseconds

8.39.2.21 getSensorData()

```
virtual std::string TimeTagger::getSensorData ( ) [pure virtual]
```

Show the status of the sensor data from the FPGA and peripherals on the console.

8.39.2.22 getSerial()

```
virtual std::string TimeTagger::getSerial ( ) [pure virtual]
```

identifies the hardware by serial number

8.39.2.23 getStreamBlockSizeEvents()

```
virtual int TimeTagger::getStreamBlockSizeEvents ( ) [pure virtual]
```

8.39.2.24 `getStreamBlockSizeLatency()`

```
virtual int TimeTagger::getStreamBlockSizeLatency ( ) [pure virtual]
```

8.39.2.25 `getTestSignalDivider()`

```
virtual int TimeTagger::getTestSignalDivider ( ) [pure virtual]
```

get the divider for the frequency of the test signal

8.39.2.26 `getTriggerLevel()`

```
virtual double TimeTagger::getTriggerLevel (
    channel\_t channel ) [pure virtual]
```

get the trigger voltage threshold of a channel

Parameters

<i>channel</i>	the channel
----------------	-------------

8.39.2.27 `reset()`

```
virtual void TimeTagger::reset ( ) [pure virtual]
```

reset the [TimeTagger](#) object to default settings and detach all iterators

8.39.2.28 `setConditionalFilter()`

```
virtual void TimeTagger::setConditionalFilter (
    std::vector< channel\_t > trigger,
    std::vector< channel\_t > filtered,
    bool hardwareDelayCompensation = true ) [pure virtual]
```

configures the conditional filter

After each event on the trigger channels, one event per filtered channel will pass afterwards. This is handled in a very early stage in the pipeline, so all event limitations but the deadtime are suppressed. But the accuracy of the order of those events is low.

Refer the Manual for a description of this function.

Parameters

<i>trigger</i>	the channels that sets the condition
<i>filtered</i>	the channels that are filtered by the condition
<i>hardwareDelayCompensation</i>	if false, the physical hardware delay will not be compensated

8.39.2.29 setEventDivider()

```
virtual void TimeTagger::setEventDivider (
    channel_t channel,
    unsigned int divider ) [pure virtual]
```

Divides the amount of transmitted edge per channel.

This filter decimates the events on a given channel by a specified factor. So for a divider n , every n th event is transmitted through the filter and $n-1$ events are skipped between consecutive transmitted events. If a conditional filter is also active, the event divider is applied after the conditional filter, so the conditional is applied to the complete event stream and only events which pass the conditional filter are forwarded to the divider.

As it is a hardware filter, it reduces the required USB bandwidth and CPU processing power, but it cannot be configured for virtual channels.

Parameters

<i>channel</i>	channel to be configured
<i>divider</i>	new divider, must be smaller than 65536

8.39.2.30 setHardwareBufferSize()

```
virtual void TimeTagger::setHardwareBufferSize (
    int size ) [pure virtual]
```

sets the maximum USB buffer size

This option controls the maximum buffer size of the USB connection. This can be used to balance low input latency vs high (peak) throughput.

Parameters

<i>size</i>	the maximum buffer size in events
-------------	-----------------------------------

8.39.2.31 setInputMux()

```
virtual void TimeTagger::setInputMux (
```

```
channel_t channel,
int mux_mode ) [pure virtual]
```

configures the input multiplexer

Every physical input channel has an input multiplexer with 4 modes: 0: normal input mode 1: use the input from channel -1 (left) 2: use the input from channel +1 (right) 3: use the reference oscillator

Mode 1 and 2 cascades, so many inputs can be configured to get the same input events.

Parameters

<i>channel</i>	the physical channel of the input multiplexer
<i>mux_mode</i>	the configuration mode of the input multiplexer

8.39.2.32 setLED()

```
virtual void TimeTagger::setLED (
uint32_t bitmask ) [pure virtual]
```

Enforce a state to the LEDs 0: led_status[R] 16: led_status[R] - mux 1: led_status[G] 17: led_status[G] - mux 2: led_status[B] 18: led_status[B] - mux 3: led_power[R] 19: led_power[R] - mux 4: led_power[G] 20: led_power[G] - mux 5: led_power[B] 21: led_power[B] - mux 6: led_clock[R] 22: led_clock[R] - mux 7: led_clock[G] 23: led_clock[G] - mux 8: led_clock[B] 24: led_clock[B] - mux.

8.39.2.33 setNormalization()

```
virtual void TimeTagger::setNormalization (
std::vector< channel_t > channel,
bool state ) [pure virtual]
```

enables or disables the normalization of the distribution.

Refer the Manual for a description of this function.

Parameters

<i>channel</i>	list of channels to modify
<i>state</i>	the new state

8.39.2.34 setSoundFrequency()

```
virtual void TimeTagger::setSoundFrequency (
uint32_t freq_hz ) [pure virtual]
```


Set the Time Taggers internal buzzer to a frequency in Hz (freq_hz==0 to disable)

Parameters

<i>freq_hz</i>	the generated audio frequency
----------------	-------------------------------

8.39.2.35 setStreamBlockSize()

```
virtual void TimeTagger::setStreamBlockSize (
    int max_events,
    int max_latency ) [pure virtual]
```

sets the maximum events and latency for the stream block size

This option controls the latency and the block size of the data stream. The default values are max_events = 131072 events and max_latency = 20 ms. Depending on which of the two parameters is exceeded first, the block stream size is adjusted accordingly. The block size will be reduced automatically for blocks when no signal is arriving for 512 ns on the Time Tagger Ultra and 1536 ns for the Time Tagger 20. *

Parameters

<i>max_events</i>	maximum number of events
<i>max_latency</i>	maximum latency in ms

8.39.2.36 setTestSignalDivider()

```
virtual void TimeTagger::setTestSignalDivider (
    int divider ) [pure virtual]
```

set the divider for the frequency of the test signal

The base clock of the test signal oscillator for the Time Tagger Ultra is running at 100.8 MHz sampled down by an factor of 2 to have a similar base clock as the Time Tagger 20 (~50 MHz). The default divider is 63 -> ~800 kEvents/s

Parameters

<i>divider</i>	frequency divisor of the oscillator
----------------	-------------------------------------

8.39.2.37 setTriggerLevel()

```
virtual void TimeTagger::setTriggerLevel (
    channel_t channel,
    double voltage ) [pure virtual]
```

set the trigger voltage threshold of a channel

Parameters

<i>channel</i>	the channel to set
<i>voltage</i>	voltage level.. [0..1]


The documentation for this class was generated from the following file:

- [TimeTagger.h](#)

8.40 TimeTaggerBase Class Reference

```
#include <TimeTagger.h>
```

Inheritance diagram for TimeTaggerBase:



Public Types

- typedef std::function< void([IteratorBase](#) *)> [IteratorCallback](#)
- typedef std::map< [IteratorBase](#) *, [IteratorCallback](#) > [IteratorCallbackMap](#)

Public Member Functions

- virtual unsigned int [getFence](#) (bool alloc_fence=true)=0
- virtual bool [waitForFence](#) (unsigned int fence, int64_t timeout=-1)=0
- virtual bool [sync](#) (int64_t timeout=-1)=0
- virtual [channel_t](#) [getInvertedChannel](#) ([channel_t](#) channel)=0
get the falling channel id for a raising channel and vice versa
- virtual bool [isUnusedChannel](#) ([channel_t](#) channel)=0
compares the provided channel with CHANNEL_UNUSED
- virtual void [runSynchronized](#) (const [IteratorCallbackMap](#) &callbacks, bool block=true)=0
Run synchronized callbacks for a list of iterators.
- virtual std::string [getConfiguration](#) ()=0
- virtual void [setInputDelay](#) ([channel_t](#) channel, [timestamp_t](#) delay)=0
set time delay on a channel

- virtual void [setDelayHardware](#) ([channel_t](#) channel, [timestamp_t](#) delay)=0
set time delay on a channel
- virtual void [setDelaySoftware](#) ([channel_t](#) channel, [timestamp_t](#) delay)=0
set time delay on a channel
- virtual [timestamp_t](#) [getInputDelay](#) ([channel_t](#) channel)=0
get time delay of a channel
- virtual [timestamp_t](#) [getDelaySoftware](#) ([channel_t](#) channel)=0
get time delay of a channel
- virtual [timestamp_t](#) [getDelayHardware](#) ([channel_t](#) channel)=0
get time delay of a channel
- virtual [timestamp_t](#) [setDeadtime](#) ([channel_t](#) channel, [timestamp_t](#) deadtime)=0
set the deadtime between two edges on the same channel.
- virtual [timestamp_t](#) [getDeadtime](#) ([channel_t](#) channel)=0
get the deadtime between two edges on the same channel.
- virtual void [setTestSignal](#) ([channel_t](#) channel, bool enabled)=0
enable the calibration on a channel.
- virtual void [setTestSignal](#) (std::vector< [channel_t](#) > channel, bool enabled)=0
- virtual bool [getTestSignal](#) ([channel_t](#) channel)=0
fetch the status of the test signal generator
- virtual long long [getOverflows](#) ()=0
get overflow count
- virtual void [clearOverflows](#) ()=0
clear overflow counter
- virtual long long [getOverflowsAndClear](#) ()=0
get and clear overflow counter

Protected Member Functions

- [TimeTaggerBase](#) ()
abstract interface class
- virtual [~TimeTaggerBase](#) ()
- [TimeTaggerBase](#) (const [TimeTaggerBase](#) &)=delete
- [TimeTaggerBase](#) & operator= (const [TimeTaggerBase](#) &)=delete
- virtual std::shared_ptr< [IteratorBaseListNode](#) > [addIterator](#) ([IteratorBase](#) *it)=0
- virtual void [freeIterator](#) ([IteratorBase](#) *it)=0
- virtual [channel_t](#) [getNewVirtualChannel](#) ()=0
- virtual void [freeVirtualChannel](#) ([channel_t](#) channel)=0
- virtual void [registerChannel](#) ([channel_t](#) channel)=0
register a FPGA channel.
- virtual void [unregisterChannel](#) ([channel_t](#) channel)=0
release a previously registered channel.
- virtual void [addChild](#) ([TimeTaggerBase](#) *child)=0
- virtual void [removeChild](#) ([TimeTaggerBase](#) *child)=0
- virtual void [release](#) ()=0

Friends

- class [IteratorBase](#)
- class [TimeTaggerProxy](#)
- class [TimeTaggerRunner](#)

8.40.1 Member Typedef Documentation

8.40.1.1 IteratorCallback

```
typedef std::function<void(IteratorBase *)> TimeTaggerBase::IteratorCallback
```

8.40.1.2 IteratorCallbackMap

```
typedef std::map<IteratorBase *, IteratorCallback> TimeTaggerBase::IteratorCallbackMap
```

8.40.2 Constructor & Destructor Documentation

8.40.2.1 TimeTaggerBase() [1/2]

```
TimeTaggerBase::TimeTaggerBase ( ) [inline], [protected]
```

abstract interface class

8.40.2.2 ~TimeTaggerBase()

```
virtual TimeTaggerBase::~~TimeTaggerBase ( ) [inline], [protected], [virtual]
```

destructor

8.40.2.3 TimeTaggerBase() [2/2]

```
TimeTaggerBase::TimeTaggerBase (
    const TimeTaggerBase & ) [protected], [delete]
```

8.40.3 Member Function Documentation

8.40.3.1 addChild()

```
virtual void TimeTaggerBase::addChild (
    TimeTaggerBase * child ) [protected], [pure virtual]
```

8.40.3.2 addIterator()

```
virtual std::shared_ptr<IteratorBaseListNode> TimeTaggerBase::addIterator (
    IteratorBase * it ) [protected], [pure virtual]
```

8.40.3.3 clearOverflows()

```
virtual void TimeTaggerBase::clearOverflows ( ) [pure virtual]
```

clear overflow counter

Sets the overflow counter to zero

8.40.3.4 freeIterator()

```
virtual void TimeTaggerBase::freeIterator (
    IteratorBase * it ) [protected], [pure virtual]
```

8.40.3.5 freeVirtualChannel()

```
virtual void TimeTaggerBase::freeVirtualChannel (
    channel_t channel ) [protected], [pure virtual]
```

8.40.3.6 getConfiguration()

```
virtual std::string TimeTaggerBase::getConfiguration ( ) [pure virtual]
```

Fetches the overall configuration status of the Time Tagger object.

Returns

a JSON serialized string with all configuration and status flags.

8.40.3.7 getDeadtime()

```
virtual timestamp_t TimeTaggerBase::getDeadtime (
    channel_t channel ) [pure virtual]
```

get the deadtime between two edges on the same channel.

This function gets the user configureable deadtime.

Parameters

<i>channel</i>	channel to be queried
----------------	-----------------------

Returns

the real configured deadtime

8.40.3.8 getDelayHardware()

```
virtual timestamp_t TimeTaggerBase::getDelayHardware (
    channel_t channel ) [pure virtual]
```

get time delay of a channel

see setDelayHardware

Parameters

<i>channel</i>	the channel
----------------	-------------

8.40.3.9 getDelaySoftware()

```
virtual timestamp_t TimeTaggerBase::getDelaySoftware (
    channel_t channel ) [pure virtual]
```

get time delay of a channel

see setDelaySoftware

Parameters

<i>channel</i>	the channel
----------------	-------------

8.40.3.10 getFence()

```
virtual unsigned int TimeTaggerBase::getFence (
    bool alloc_fence = true ) [pure virtual]
```

Generate a new fence object, which validates the current configuration and the current time. This fence is uploaded to the earliest pipeline stage of the Time Tagger. Waiting on this fence ensures that all hardware settings such as

trigger levels, channel registrations, etc., have propagated to the FPGA and are physically active. Synchronizes the Time Tagger internal memory, so that all tags arriving after the `waitForFence` call were actually produced after the `getFence` call. The `waitForFence` function waits until all tags, which are present at the time of the function call within the internal memory of the Time Tagger, are processed. This call might block to limit the amount of active fences.

Parameters

<i>alloc_fence</i>	if false, a reference to the most recently created fence will be returned instead
--------------------	---

Returns

the allocated fence

8.40.3.11 getInputDelay()

```
virtual timestamp_t TimeTaggerBase::getInputDelay (
    channel_t channel ) [pure virtual]
```

get time delay of a channel

see `setInputDelay`

Parameters

<i>channel</i>	the channel
----------------	-------------

8.40.3.12 getInvertedChannel()

```
virtual channel_t TimeTaggerBase::getInvertedChannel (
    channel_t channel ) [pure virtual]
```

get the falling channel id for a raising channel and vice versa

8.40.3.13 getNewVirtualChannel()

```
virtual channel_t TimeTaggerBase::getNewVirtualChannel ( ) [protected], [pure virtual]
```

8.40.3.14 getOverflows()

```
virtual long long TimeTaggerBase::getOverflows ( ) [pure virtual]
```

get overflow count

Get the number of communication overflows occurred

8.40.3.15 getOverflowsAndClear()

```
virtual long long TimeTaggerBase::getOverflowsAndClear ( ) [pure virtual]
```

get and clear overflow counter

Get the number of communication overflows occurred and sets them to zero

8.40.3.16 getTestSignal()

```
virtual bool TimeTaggerBase::getTestSignal (
    channel_t channel ) [pure virtual]
```

fetch the status of the test signal generator

Parameters

<i>channel</i>	the channel
----------------	-------------

8.40.3.17 isUnusedChannel()

```
virtual bool TimeTaggerBase::isUnusedChannel (
    channel_t channel ) [pure virtual]
```

compares the provided channel with CHANNEL_UNUSED

But also keeps care about the channel number scheme and selects either CHANNEL_UNUSED or CHANNEL_UNUSED_OLD

8.40.3.18 operator=()

```
TimeTaggerBase& TimeTaggerBase::operator= (
    const TimeTaggerBase & ) [protected], [delete]
```

8.40.3.19 registerChannel()

```
virtual void TimeTaggerBase::registerChannel (
    channel_t channel ) [protected], [pure virtual]
```

register a FPGA channel.

Only events on previously registered channels will be transferred over the communication channel.

Parameters

<i>channel</i>	the channel
----------------	-------------

8.40.3.20 release()

```
virtual void TimeTaggerBase::release ( ) [protected], [pure virtual]
```

8.40.3.21 removeChild()

```
virtual void TimeTaggerBase::removeChild (
    TimeTaggerBase * child ) [protected], [pure virtual]
```

8.40.3.22 runSynchronized()

```
virtual void TimeTaggerBase::runSynchronized (
    const IteratorCallbackMap & callbacks,
    bool block = true ) [pure virtual]
```

Run synchronized callbacks for a list of iterators.

This method has a list of callbacks for a list of iterators. Those callbacks are called for a synchronized data set, but in parallel. They are called from an internal worker thread. As the data set is synchronized, this creates a bottleneck for one worker thread, so only fast and non-blocking callbacks are allowed.

Parameters

<i>callbacks</i>	Map of callbacks per iterator
<i>block</i>	Shall this method block until all callbacks are finished

8.40.3.23 setDeadtime()

```
virtual timestamp_t TimeTaggerBase::setDeadtime (
    channel_t channel,
    timestamp_t deadtime ) [pure virtual]
```

set the deadtime between two edges on the same channel.

This function sets the user configureable deadtime. The requested time will be rounded to the nearest multiple of the clock time. The deadtime will also be clamped to device specific limitations.

As the actual deadtime will be altered, the real value will be returned.

Parameters

<i>channel</i>	channel to be configured
<i>deadtime</i>	new deadtime

Returns

the real configured deadtime

8.40.3.24 setDelayHardware()

```
virtual void TimeTaggerBase::setDelayHardware (
    channel_t channel,
    timestamp_t delay ) [pure virtual]
```

set time delay on a channel

When set, every event on this physical input channel is delayed by the given delay in picoseconds. This delay is implemented on the hardware before any filter with no performance overhead. The maximum delay on the Time Tagger Ultra series is 2 us. This affects both the rising and the falling event at the same time.

Parameters

<i>channel</i>	the channel to set
<i>delay</i>	the delay in picoseconds

8.40.3.25 setDelaySoftware()

```
virtual void TimeTaggerBase::setDelaySoftware (
    channel_t channel,
    timestamp_t delay ) [pure virtual]
```

set time delay on a channel

When set, every event on this channel is delayed by the given delay in picoseconds. This happens on the computer and so after the on-device filters. Please use setDelayHardware instead for better performance. This affects either the the rising or the falling event only.

This method has the best performance with "small delays". The delay is considered "small" when less than 100 events arrive within the time of the largest delay set. For example, if the total event-rate over all channels used is 10 Mevent/s, the signal can be delayed efficiently up to 10 microseconds. For large delays, please use [DelayedChannel](#) instead.

Parameters

<i>channel</i>	the channel to set
<i>delay</i>	the delay in picoseconds

8.40.3.26 setInputDelay()

```
virtual void TimeTaggerBase::setInputDelay (
    channel_t channel,
    timestamp_t delay ) [pure virtual]
```

set time delay on a channel

When set, every event on this channel is delayed by the given delay in picoseconds.

This method has the best performance with "small delays". The delay is considered "small" when less than 100 events arrive within the time of the largest delay set. For example, if the total event-rate over all channels used is 10 Mevent/s, the signal can be delayed efficiently up to 10 microseconds. For large delays, please use [DelayedChannel](#) instead.

Parameters

<i>channel</i>	the channel to set
<i>delay</i>	the delay in picoseconds

8.40.3.27 setTestSignal() [1/2]

```
virtual void TimeTaggerBase::setTestSignal (
    channel_t channel,
    bool enabled ) [pure virtual]
```

enable the calibration on a channel.

This will connect or disconnect the channel with the on-chip uncorrelated signal generator.

Parameters

<i>channel</i>	the channel
<i>enabled</i>	enabled / disabled flag

8.40.3.28 setTestSignal() [2/2]

```
virtual void TimeTaggerBase::setTestSignal (
    std::vector< channel_t > channel,
    bool enabled ) [pure virtual]
```

8.40.3.29 sync()

```
virtual bool TimeTaggerBase::sync (
    int64_t timeout = -1 ) [pure virtual]
```

Sync the timetagger pipeline, so that all started iterators and their enabled channels are ready This is a shortcut for calling getFence and waitForFence at once. See getFence for more details.

Parameters

<i>timeout</i>	timeout in milliseconds. Negative means no timeout, zero returns immediately.
----------------	---

Returns

true on success, false on timeout

8.40.3.30 unregisterChannel()

```
virtual void TimeTaggerBase::unregisterChannel (
    channel_t channel ) [protected], [pure virtual]
```

release a previously registered channel.

Parameters

<i>channel</i>	the channel
----------------	-------------

8.40.3.31 waitForFence()

```
virtual bool TimeTaggerBase::waitForFence (
    unsigned int fence,
    int64_t timeout = -1 ) [pure virtual]
```

Wait for a fence in the data stream. See getFence for more details.

Parameters

<i>fence</i>	fence object, which shall be waited on
<i>timeout</i>	timeout in milliseconds. Negative means no timeout, zero returns immediately.

Returns

true if the fence has passed, false on timeout

8.40.4 Friends And Related Function Documentation

8.40.4.1 IteratorBase

```
friend class IteratorBase [friend]
```

8.40.4.2 TimeTaggerProxy

```
friend class TimeTaggerProxy [friend]
```

8.40.4.3 TimeTaggerRunner

```
friend class TimeTaggerRunner [friend]
```

The documentation for this class was generated from the following file:


- [TimeTagger.h](#)

8.41 TimeTaggerVirtual Class Reference

virtual [TimeTagger](#) based on dump files

```
#include <TimeTagger.h>
```

Inheritance diagram for TimeTaggerVirtual:



Public Member Functions

- virtual uint64_t [replay](#) (const std::string &file, [timestamp_t](#) begin=0, [timestamp_t](#) duration=-1, bool queue=true)=0
replay a given dump file on the disc
- virtual void [stop](#) ()=0
stops the current and all queued files.
- virtual void [reset](#) ()=0
stops the all queued files and resets the [TimeTaggerVirtual](#) to its default settings
- virtual bool [waitForCompletion](#) (uint64_t ID=0, int64_t timeout=-1)=0
block the current thread until the replay finish
- virtual void [setReplaySpeed](#) (double speed)=0
configures the speed factor for the virtual tagger.
- virtual double [getReplaySpeed](#) ()=0
fetches the speed factor
- virtual void [setConditionalFilter](#) (std::vector< [channel_t](#) > trigger, std::vector< [channel_t](#) > filtered)=0
configures the conditional filter
- virtual void [clearConditionalFilter](#) ()=0
deactivates the conditional filter
- virtual std::vector< [channel_t](#) > [getConditionalFilterTrigger](#) ()=0
fetches the configuration of the conditional filter
- virtual std::vector< [channel_t](#) > [getConditionalFilterFiltered](#) ()=0
fetches the configuration of the conditional filter

Additional Inherited Members

8.41.1 Detailed Description

virtual [TimeTagger](#) based on dump files

The [TimeTaggerVirtual](#) class represents a virtual Time Tagger. But instead of connecting to Swabians hardware, it replays all tags from a recorded file.

8.41.2 Member Function Documentation

8.41.2.1 [clearConditionalFilter\(\)](#)

```
virtual void TimeTaggerVirtual::clearConditionalFilter ( ) [pure virtual]
```

deactivates the conditional filter

equivilent to [setConditionalFilter\({},{}\)](#)

8.41.2.2 getConditionalFilterFiltered()

```
virtual std::vector<channel_t> TimeTaggerVirtual::getConditionalFilterFiltered ( ) [pure virtual]
```

fetches the configuration of the conditional filter

see setConditionalFilter

8.41.2.3 getConditionalFilterTrigger()

```
virtual std::vector<channel_t> TimeTaggerVirtual::getConditionalFilterTrigger ( ) [pure virtual]
```

fetches the configuration of the conditional filter

see setConditionalFilter

8.41.2.4 getReplaySpeed()

```
virtual double TimeTaggerVirtual::getReplaySpeed ( ) [pure virtual]
```

fetches the speed factor

Please see setReplaySpeed for more details.

Returns

the speed factor

8.41.2.5 replay()

```
virtual uint64_t TimeTaggerVirtual::replay (
    const std::string & file,
    timestamp_t begin = 0,
    timestamp_t duration = -1,
    bool queue = true ) [pure virtual]
```

replay a given dump file on the disc

This method adds the file to the replay queue. If the flag 'queue' is false, the current queue will be flushed and this file will be replayed immediatelly.

Parameters

<i>file</i>	the file to be replayed
<i>begin</i>	amount of ps to skip at the begin of the file. A negativ time will generate a pause in the replay
<i>duration</i>	time period in ps of the file. -1 replays till the last tag
<i>queue</i>	flag if this file shall be queued

Returns

ID of the queued file

8.41.2.6 reset()

```
virtual void TimeTaggerVirtual::reset ( ) [pure virtual]
```

stops the all queued files and resets the [TimeTaggerVirtual](#) to its default settings

This method stops the current file, clears the replay queue and resets the [TimeTaggerVirtual](#) to its default settings.

8.41.2.7 setConditionalFilter()

```
virtual void TimeTaggerVirtual::setConditionalFilter (
    std::vector< channel_t > trigger,
    std::vector< channel_t > filtered ) [pure virtual]
```

configures the conditional filter

After each event on the trigger channels, one event per filtered channel will pass afterwards. This is handled in a very early stage in the pipeline, so all event limitations but the deadtime are suppressed. But the accuracy of the order of those events is low.

Refer the Manual for a description of this function.

Parameters

<i>trigger</i>	the channels that sets the condition
<i>filtered</i>	the channels that are filtered by the condition

8.41.2.8 setReplaySpeed()

```
virtual void TimeTaggerVirtual::setReplaySpeed (
    double speed ) [pure virtual]
```

configures the speed factor for the virtual tagger.

This method configures the speed factor of this virtual Time Tagger. A value of 1.0 will replay in real time. All values < 0.0 will replay the data as fast as possible, but stops at the end of all data. This is the default value.

Parameters

<i>speed</i>	ratio of the replay speed and the real time
--------------	---

8.41.2.9 stop()

```
virtual void TimeTaggerVirtual::stop ( ) [pure virtual]
```

stops the current and all queued files.

This method stops the current file and clears the replay queue.

8.41.2.10 waitForCompletion()

```
virtual bool TimeTaggerVirtual::waitForCompletion (
    uint64_t ID = 0,
    int64_t timeout = -1 ) [pure virtual]
```

block the current thread until the replay finish

This method blocks the current execution and waits till the given file has finished its replay. If no ID is provided, it waits until all queued files are replayed.

This function does not block on a zero timeout. Negative timeouts are interpreted as infinite timeouts.

Parameters

<i>ID</i>	selects which file to wait for
<i>timeout</i>	timeout in milliseconds

Returns

true if the file is complete, false on timeout

The documentation for this class was generated from the following file:


- [TimeTagger.h](#)

8.42 TimeTagStream Class Reference

access the time tag stream

```
#include <Iterators.h>
```

Inheritance diagram for TimeTagStream:



Public Member Functions

- `TimeTagStream (TimeTaggerBase *tagger, uint64_t n_max_events, std::vector< channel_t > channels=std::vector< channel_t >())`
constructor of a `TimeTagStream` thread
- `~TimeTagStream ()`
tbd
- `uint64_t getCounts ()`
get incoming time tags
- `TimeTagStreamBuffer getData ()`
fetches all stored tags and clears the internal state

Protected Member Functions

- `bool next_impl (std::vector< Tag > &incoming_tags, timestamp_t begin_time, timestamp_t end_time) override`
update iterator state
- `void clear_impl () override`
clear `Iterator` state.

Friends

- class `TimeTagStreamImpl`

Additional Inherited Members

8.42.1 Detailed Description

access the time tag stream

8.42.2 Constructor & Destructor Documentation

8.42.2.1 TimeTagStream()

```
TimeTagStream::TimeTagStream (
    TimeTaggerBase * tagger,
    uint64_t n_max_events,
    std::vector< channel_t > channels = std::vector< channel_t >() )
```

constructor of a [TimeTagStream](#) thread

Gives access to the time tag stream

Parameters

<i>tagger</i>	reference to a TimeTagger
<i>n_max_events</i>	maximum number of tags stored
<i>channels</i>	channels which are dumped to the file (when empty or not passed all active channels are dumped)

8.42.2.2 ~TimeTagStream()

```
TimeTagStream::~~TimeTagStream ( )
```

tbd

8.42.3 Member Function Documentation

8.42.3.1 clear_impl()

```
void TimeTagStream::clear_impl ( ) [override], [protected], [virtual]
```

clear [Iterator](#) state.

Each [Iterator](#) should implement the [clear_impl\(\)](#) method to reset its internal state. The [clear_impl\(\)](#) function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.42.3.2 getCounts()

```
uint64_t TimeTagStream::getCounts ( )
```

get incoming time tags

All incoming time tags are stored in a buffer (max size: max_tags). The buffer is cleared after retrieving the data with [getData\(\)](#) return the number of stored tags

8.42.3.3 getData()

```
TimeTagStreamBuffer TimeTagStream::getData ( )
```

fetches all stored tags and clears the internal state

8.42.3.4 next_impl()

```
bool TimeTagStream::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.42.4 Friends And Related Function Documentation

8.42.4.1 TimeTagStreamImpl

```
friend class TimeTagStreamImpl [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

8.43 TimeTagStreamBuffer Class Reference

```
#include <Iterators.h>
```

Public Member Functions

- void [getOverflows](#) (std::function< unsigned char *(size_t)> array_out)
- void [getChannels](#) (std::function< int *(size_t)> array_out)
- void [getTimestamps](#) (std::function< long long *(size_t)> array_out)
- void [getMissedEvents](#) (std::function< unsigned short *(size_t)> array_out)
- void [getEventTypes](#) (std::function< unsigned char *(size_t)> array_out)

Public Attributes

- uint64_t [size](#)
- bool [hasOverflows](#)
- timestamp_t [tStart](#)
- timestamp_t [tGetData](#)

Friends

- class [TimeTagStreamImpl](#)
- class [FileReaderImpl](#)

8.43.1 Member Function Documentation

8.43.1.1 getChannels()

```
void TimeTagStreamBuffer::getChannels (
    std::function< int *(size_t)> array_out )
```

8.43.1.2 getEventTypes()

```
void TimeTagStreamBuffer::getEventTypes (
    std::function< unsigned char *(size_t)> array_out )
```

8.43.1.3 getMissedEvents()

```
void TimeTagStreamBuffer::getMissedEvents (
    std::function< unsigned short *(size_t)> array_out )
```

8.43.1.4 getOverflows()

```
void TimeTagStreamBuffer::getOverflows (
    std::function< unsigned char *(size_t)> array_out )
```

8.43.1.5 getTimestamps()

```
void TimeTagStreamBuffer::getTimestamps (
    std::function< long long *(size_t)> array_out )
```

8.43.2 Friends And Related Function Documentation

8.43.2.1 FileReaderImpl

```
friend class FileReaderImpl [friend]
```

8.43.2.2 TimeTagStreamImpl

```
friend class TimeTagStreamImpl [friend]
```

8.43.3 Member Data Documentation

8.43.3.1 hasOverflows

```
bool TimeTagStreamBuffer::hasOverflows
```

8.43.3.2 size

```
uint64_t TimeTagStreamBuffer::size
```

8.43.3.3 tGetData

```
timestamp_t TimeTagStreamBuffer::tGetData
```

8.43.3.4 tStart

```
timestamp_t TimeTagStreamBuffer::tStart
```

The documentation for this class was generated from the following file:


- [Iterators.h](#)

8.44 TriggerOnCountrate Class Reference

Inject trigger events when exceeding or falling below a given count rate within a rolling time window.

```
#include <Iterators.h>
```

Inheritance diagram for TriggerOnCountrate:



Public Member Functions

- [TriggerOnCountrate](#) ([TimeTaggerBase](#) *tagger, [channel_t](#) input_channel, double reference_countrate, double hysteresis, [timestamp_t](#) time_window)
constructor of a [TriggerOnCountrate](#)
- [~TriggerOnCountrate](#) ()
- [channel_t](#) [getChannelAbove](#) ()
Get the channel number of the above channel.
- [channel_t](#) [getChannelBelow](#) ()
Get the channel number of the below channel.
- [std::vector](#)< [channel_t](#) > [getChannels](#) ()
Get both virtual channel numbers: [[getChannelAbove](#) (), [getChannelBelow](#) ()].
- bool [isAbove](#) ()
Returns whether the Virtual Channel is currently in the above state.
- bool [isBelow](#) ()
Returns whether the Virtual Channel is currently in the below state.
- double [getCurrentCountrate](#) ()
Get the current count rate averaged within the time_window.
- bool [injectCurrentState](#) ()
Emit a time-tag into the respective channel according to the current state.

Protected Member Functions

- bool [next_impl](#) ([std::vector](#)< [Tag](#) > &incoming_tags, [timestamp_t](#) begin_time, [timestamp_t](#) end_time) override
update iterator state
- void [on_start](#) () override
callback when the measurement class is started

Friends

- class [TriggerOnCountrateImpl](#)

Additional Inherited Members

8.44.1 Detailed Description

Inject trigger events when exceeding or falling below a given count rate within a rolling time window.

Measures the count rate inside a rolling time window and emits tags when a given reference_countrate is crossed. A [TriggerOnCountrate](#) object provides two virtual channels: The above channel is triggered when the count rate exceeds the threshold (transition from below to above). The below channel is triggered when the count rate falls below the threshold (transition from above to below). To avoid the emission of multiple trigger tags in the transition area, the hysteresis count rate modifies the threshold with respect to the transition direction: An event in the above channel will be triggered when the channel is in the below state and rises to reference_countrate + hysteresis or above. Vice versa, the below channel fires when the channel is in the above state and falls to the limit of reference_countrate - hysteresis or below.

The time-tags are always injected at the end of the integration window. You can use the [DelayedChannel](#) to adjust the temporal position of the trigger tags with respect to the integration time window.

The very first tag of the virtual channel will be emitted time_window after the instantiation of the object and will reflect the current state, so either above or below.

8.44.2 Constructor & Destructor Documentation

8.44.2.1 TriggerOnCountrate()

```
TriggerOnCountrate::TriggerOnCountrate (
    TimeTaggerBase * tagger,
    channel_t input_channel,
    double reference_countrate,
    double hysteresis,
    timestamp_t time_window )
```

constructor of a [TriggerOnCountrate](#)

Parameters

<i>tagger</i>	Reference to a TimeTagger object.
<i>input_channel</i>	Channel number of the channel whose count rate will control the trigger channels.
<i>reference_countrate</i>	The reference count rate in Hz that separates the <code>above</code> range from the <code>below</code> range.
<i>hysteresis</i>	The threshold count rate in Hz for transitioning to the <code>above</code> threshold state is <code>countrate >= reference_countrate + hysteresis</code> , whereas it is <code>countrate <= reference_countrate - hysteresis</code> for transitioning to the <code>below</code> threshold state. The hysteresis avoids the emission of multiple trigger tags upon a single transition.
<i>time_window</i>	Rolling time window size in ps. The count rate is analyzed within this time window and compared to the threshold count rate.

8.44.2.2 ~TriggerOnCountrate()

```
TriggerOnCountrate::~~TriggerOnCountrate ( )
```

8.44.3 Member Function Documentation

8.44.3.1 getChannelAbove()

```
channel_t TriggerOnCountrate::getChannelAbove ( )
```

Get the channel number of the `above` channel.

8.44.3.2 getChannelBelow()

```
channel_t TriggerOnCountrate::getChannelBelow ( )
```

Get the channel number of the below channel.

8.44.3.3 getChannels()

```
std::vector<channel_t> TriggerOnCountrate::getChannels ( )
```

Get both virtual channel numbers: [[getChannelAbove\(\)](#), [getChannelBelow\(\)](#)].

8.44.3.4 getCurrentCountrate()

```
double TriggerOnCountrate::getCurrentCountrate ( )
```

Get the current count rate averaged within the `time_window`.

8.44.3.5 injectCurrentState()

```
bool TriggerOnCountrate::injectCurrentState ( )
```

Emit a time-tag into the respective channel according to the current state.

Emit a time-tag into the respective channel according to the current state. This is useful if you start a new measurement that requires the information. The function returns whether it was possible to inject the event. The injection is not possible if the Time Tagger is in overflow mode or the time window has not passed yet. The function call is non-blocking.

8.44.3.6 isAbove()

```
bool TriggerOnCountrate::isAbove ( )
```

Returns whether the Virtual Channel is currently in the above state.

8.44.3.7 isBelow()

```
bool TriggerOnCountrate::isBelow ( )
```

Returns whether the Virtual Channel is currently in the below state.

8.44.3.8 next_impl()

```
bool TriggerOnCountrate::next_impl (
    std::vector< Tag > & incoming_tags,
    timestamp_t begin_time,
    timestamp_t end_time ) [override], [protected], [virtual]
```

update iterator state

Each [Iterator](#) must implement the [next_impl\(\)](#) method. The [next_impl\(\)](#) function is guarded by the update lock.

The backend delivers each [Tag](#) on each registered channel to this callback function.

Parameters

<i>incoming_tags</i>	block of events
<i>begin_time</i>	earliest event in the block
<i>end_time</i>	begin_time of the next block, not including in this block

Returns

true if the content of this block was modified, false otherwise

Implements [IteratorBase](#).

8.44.3.9 on_start()

```
void TriggerOnCountrate::on_start ( ) [override], [protected], [virtual]
```

callback when the measurement class is started

This function is guarded by the update lock.

Reimplemented from [IteratorBase](#).

8.44.4 Friends And Related Function Documentation**8.44.4.1 TriggerOnCountrateImpl**

```
friend class TriggerOnCountrateImpl [friend]
```

The documentation for this class was generated from the following file:

- [Iterators.h](#)

Chapter 9

File Documentation

9.1 Iterators.h File Reference

```
#include <algorithm>
#include <array>
#include <assert.h>
#include <deque>
#include <fstream>
#include <iostream>
#include <limits>
#include <list>
#include <map>
#include <memory>
#include <mutex>
#include <queue>
#include <set>
#include <stdint.h>
#include <stdio.h>
#include <unordered_map>
#include <vector>
#include "TimeTagger.h"
```

Include dependency graph for Iterators.h:



Classes

- class [FastBinning](#)
- class [Combiner](#)
 - Combine some channels in a virtual channel which has a tick for each tick in the input channels.*
- class [CountBetweenMarkers](#)
 - a simple counter where external marker signals determine the bins*
- class [Counter](#)

- a simple counter on one or more channels*
- class [Coincidences](#)
 - a coincidence monitor for one or more channel groups*
- class [Coincidence](#)
 - a coincidence monitor for one or more channel groups*
- class [Countrate](#)
 - count rate on one or more channels*
- class [DelayedChannel](#)
 - a simple delayed queue*
- class [TriggerOnCountrate](#)
 - Inject trigger events when exceeding or falling below a given count rate within a rolling time window.*
- class [GatedChannel](#)
 - An input channel is gated by a gate channel.*
- class [FrequencyMultiplier](#)
 - The signal of an input channel is scaled up to a higher frequency according to the multiplier passed as a parameter.*
- class [Iterator](#)
 - a simple event queue*
- class [TimeTagStreamBuffer](#)
- class [TimeTagStream](#)
 - access the time tag stream*
- class [Dump](#)
 - dump all time tags to a file*
- class [StartStop](#)
 - simple start-stop measurement*
- class [TimeDifferencesImpl< T >](#)
- class [TimeDifferences](#)
 - Accumulates the time differences between clicks on two channels in one or more histograms.*
- class [Histogram2D](#)
 - A 2-dimensional histogram of time differences. This can be used in measurements similar to 2D NRM spectroscopy.*
- class [TimeDifferencesND](#)
 - Accumulates the time differences between clicks on two channels in a multi-dimensional histogram.*
- class [Histogram](#)
 - Accumulate time differences into a histogram.*
- class [HistogramLogBins](#)
 - Accumulate time differences into a histogram with logarithmic increasing bin sizes.*
- class [Correlation](#)
 - cross-correlation between two channels*
- struct [Event](#)
- class [Scope](#)
- class [SynchronizedMeasurements](#)
 - start, stop and clear several measurements synchronized*
- class [ConstantFractionDiscriminator](#)
 - a virtual CFD implementation which returns the mean time between a raising and a falling pair of edges*
- class [FileWriter](#)
 - compresses and stores all time tags to a file*
- class [FileReader](#)
- class [EventGenerator](#)
 - Generate predefined events in a virtual channel relative to a trigger event.*
- class [CustomMeasurementBase](#)
- class [FlimAbstract](#)
- class [FlimBase](#)
- class [FlimFrameInfo](#)
- class [Flim](#)
 - Fluorescence lifetime imaging.*

Macros

- `#define BINNING_TEMPLATE_HELPER(fun_name, binner, ...)`
FastBinning caller helper.

Enumerations

- enum `CoincidenceTimestamp` : `uint32_t` { `CoincidenceTimestamp::Last` = 0, `CoincidenceTimestamp::Average` = 1, `CoincidenceTimestamp::First` = 2, `CoincidenceTimestamp::ListedFirst` = 3 }
- enum `State` { `UNKNOWN`, `HIGH`, `LOW` }

9.1.1 Macro Definition Documentation

9.1.1.1 BINNING_TEMPLATE_HELPER

```
#define BINNING_TEMPLATE_HELPER(
    fun_name,
    binner,
    ... )
```

Value:

```
switch (binner.getMode()) {
case FastBinning::Mode::ConstZero:
    fun_name<FastBinning::Mode::ConstZero>(__VA_ARGS__);
    break;
case FastBinning::Mode::Dividend:
    fun_name<FastBinning::Mode::Dividend>(__VA_ARGS__);
    break;
case FastBinning::Mode::PowerOfTwo:
    fun_name<FastBinning::Mode::PowerOfTwo>(__VA_ARGS__);
    break;
case FastBinning::Mode::FixedPoint_32:
    fun_name<FastBinning::Mode::FixedPoint_32>(__VA_ARGS__);
    break;
case FastBinning::Mode::FixedPoint_64:
    fun_name<FastBinning::Mode::FixedPoint_64>(__VA_ARGS__);
    break;
case FastBinning::Mode::Divide_32:
    fun_name<FastBinning::Mode::Divide_32>(__VA_ARGS__);
    break;
case FastBinning::Mode::Divide_64:
    fun_name<FastBinning::Mode::Divide_64>(__VA_ARGS__);
    break;
}
```

FastBinning caller helper.

9.1.2 Enumeration Type Documentation

9.1.2.1 CoincidenceTimestamp

```
enum CoincidenceTimestamp : uint32_t [strong]
```

type of timestamp for the [Coincidence](#) virtual channel (Last, Average, First, ListedFirst)

Enumerator

Last	
Average	
First	
ListedFirst	

9.1.2.2 State

```
enum State
```


Enumerator

UNKNOWN	
HIGH	
LOW	


9.2 TimeTagger.h File Reference

```
#include <condition_variable>
#include <cstdint>
#include <functional>
#include <limits>
#include <list>
#include <map>
#include <memory>
#include <mutex>
#include <set>
#include <stdint.h>
#include <string>
#include <unordered_set>
#include <vector>
```


Include dependency graph for TimeTagger.h:



This graph shows which files directly or indirectly include this file:



Classes

- class [CustomLogger](#)
- class [TimeTaggerBase](#)
- class [TimeTaggerVirtual](#)
virtual [TimeTagger](#) based on dump files
- class [TimeTagger](#)
backend for the [TimeTagger](#).
- struct [Tag](#)
a single event on a channel
- class [OrderedBarrier](#)
- class [OrderedBarrier::OrderInstance](#)
- class [OrderedPipeline](#)
- class [IteratorBase](#)
Base class for all iterators.

Macros

- `#define TT_API __declspec(dllimport)`
- `#define timestamp_t long long`
- `#define channel_t int`
- `#define TIMETAGGER_VERSION "2.8.2"`
- `#define GET_DATA_1D(function_name, type, argout, attribute) attribute void function_name(std::function<type *(size_t)> argout)`
- `#define GET_DATA_1D_OP1(function_name, type, argout, optional_type, optional_name, optional_default, attribute) attribute void function_name(std::function<type *(size_t)> argout, optional_type optional_name = optional_default)`

- `#define GET_DATA_1D_OP2(function_name, type, argout, optional_type, optional_name, optional_default, optional_type2, optional_name2, optional_default2, attribute)`
- `#define GET_DATA_2D(function_name, type, argout, attribute) attribute void function_name(std::function<type *(size_t, size_t)> argout)`
- `#define GET_DATA_2D_OP1(function_name, type, argout, optional_type, optional_name, optional_default, attribute)`
- `#define GET_DATA_2D_OP2(function_name, type, argout, optional_type, optional_name, optional_default, optional_type2, optional_name2, optional_default2, attribute)`
- `#define GET_DATA_3D(function_name, type, argout, attribute) attribute void function_name(std::function<type *(size_t, size_t, size_t)> argout)`
- `#define LogMessage(level, ...) LogBase(level, __FILE__, __LINE__, __VA_ARGS__);`
- `#define ErrorLog(...) LogMessage(LOGGER_ERROR, __VA_ARGS__);`
- `#define WarningLog(...) LogMessage(LOGGER_WARNING, __VA_ARGS__);`
- `#define InfoLog(...) LogMessage(LOGGER_INFO, __VA_ARGS__);`

Typedefs

- `typedef void(* logger_callback) (LogLevel level, std::string msg)`
- `using _Iterator = IteratorBase`

Enumerations

- `enum Resolution { Resolution::Standard = 0, Resolution::HighResA = 1, Resolution::HighResB = 2, Resolution::HighResC = 3 }`
- `enum ChannelEdge : int32_t { ChannelEdge::NoFalling = 1 << 0, ChannelEdge::NoRising = 1 << 1, ChannelEdge::NoStandard = 1 << 2, ChannelEdge::NoHighRes = 1 << 3, ChannelEdge::All = 0, ChannelEdge::Rising = 1, ChannelEdge::Falling = 2, ChannelEdge::HighResAll = 4, ChannelEdge::HighResRising = 4 | 1, ChannelEdge::HighResFalling = 4 | 2, ChannelEdge::StandardAll = 8, ChannelEdge::StandardRising = 8 | 1, ChannelEdge::StandardFalling = 8 | 2 }`
- `enum LogLevel { LOGGER_ERROR = 40, LOGGER_WARNING = 30, LOGGER_INFO = 10 }`

Functions

- `TT_API std::string getVersion ()`
- `TT_API TimeTagger * createTimeTagger (std::string serial="", Resolution resolution=Resolution::Standard)`
default constructor factory.
- `TT_API TimeTaggerVirtual * createTimeTaggerVirtual ()`
default constructor factory for the createTimeTaggerVirtual class.
- `TT_API void setCustomBitFileName (const std::string &bitFileName)`
set path and filename of the bitfile to be loaded into the FPGA
- `TT_API bool freeTimeTagger (TimeTaggerBase *tagger)`
free a copy of a TimeTagger reference.
- `TT_API std::vector< std::string > scanTimeTagger ()`
fetches a list of all available TimeTagger serials.
- `TT_API std::string getTimeTaggerModel (const std::string &serial)`
- `TT_API void setTimeTaggerChannelNumberScheme (int scheme)`
Configure the numbering scheme for new TimeTagger objects.
- `TT_API int getTimeTaggerChannelNumberScheme ()`
Fetch the currently configured global numbering scheme.

- `TT_API` bool `hasTimeTaggerVirtualLicense` ()
Check if a license for the `TimeTaggerVirtual` is available.
- `TT_API` void `flashLicense` (const std::string &serial, const std::string &license)
- `TT_API` std::string `extractLicenseInfo` (const std::string &license)
- `TT_API` logger_callback `setLogger` (logger_callback callback)
Sets the notifier callback which is called for each log message.
- `TT_API` void `LogBase` (LogLevel level, const char *file, int line, const char *fmt,...)
Raise a new log message. Please use the `XXXLog` macro instead.

Variables

- constexpr `channel_t` `CHANNEL_UNUSED` = -134217728
Constant for unused channel. Magic `channel_t` value to indicate an unused channel. So the iterators either have to disable this channel, or to choose a default one.
- constexpr `channel_t` `CHANNEL_UNUSED_OLD` = -1
- constexpr int `TT_CHANNEL_NUMBER_SCHEME_AUTO` = 0
- constexpr int `TT_CHANNEL_NUMBER_SCHEME_ZERO` = 1
- constexpr int `TT_CHANNEL_NUMBER_SCHEME_ONE` = 2
- constexpr `ChannelEdge` `TT_CHANNEL_RISING_AND_FALLING_EDGES` = `ChannelEdge::All`
- constexpr `ChannelEdge` `TT_CHANNEL_RISING_EDGES` = `ChannelEdge::Rising`
- constexpr `ChannelEdge` `TT_CHANNEL_FALLING_EDGES` = `ChannelEdge::Falling`

9.2.1 Macro Definition Documentation

9.2.1.1 `channel_t`

```
#define channel_t int
```

9.2.1.2 `ErrorLog`

```
#define ErrorLog(  
    ... ) LogMessage (LOGGER_ERROR, __VA_ARGS__);
```

9.2.1.3 `GET_DATA_1D`

```
#define GET_DATA_1D(  
    function_name,  
    type,  
    argout,  
    attribute ) attribute void function_name (std::function<type *(size_t)> argout)
```

This are the default wrapper functions without any overloadings.

9.2.1.4 GET_DATA_1D_OP1

```
#define GET_DATA_1D_OP1(  
    function_name,  
    type,  
    argout,  
    optional_type,  
    optional_name,  
    optional_default,  
    attribute ) attribute void function_name(std::function<type *(size_t)> argout,  
optional_type optional_name = optional_default)
```

9.2.1.5 GET_DATA_1D_OP2

```
#define GET_DATA_1D_OP2(  
    function_name,  
    type,  
    argout,  
    optional_type,  
    optional_name,  
    optional_default,  
    optional_type2,  
    optional_name2,  
    optional_default2,  
    attribute )
```

Value:

```
attribute void function_name(std::function<type *(size_t)> argout, optional_type optional_name =  
    optional_default, \  
        optional_type2 optional_name2 = optional_default2)
```

9.2.1.6 GET_DATA_2D

```
#define GET_DATA_2D(  
    function_name,  
    type,  
    argout,  
    attribute ) attribute void function_name(std::function<type *(size_t, size_t)>  
argout)
```

9.2.1.7 GET_DATA_2D_OP1

```
#define GET_DATA_2D_OP1(  
    function_name,  
    type,  
    argout,  
    optional_type,  
    optional_name,  
    optional_default,  
    attribute )
```

Value:

```
attribute void function_name(std::function<type *(size_t, size_t)> argout,  
    \  
    optional_type optional_name = optional_default)
```

9.2.1.8 GET_DATA_2D_OP2

```
#define GET_DATA_2D_OP2(  
    function_name,  
    type,  
    argout,  
    optional_type,  
    optional_name,  
    optional_default,  
    optional_type2,  
    optional_name2,  
    optional_default2,  
    attribute )
```

Value:

```
attribute void function_name(std::function<type *(size_t, size_t)> argout,  
    \  
    optional_type optional_name = optional_default,  
    \  
    optional_type2 optional_name2 = optional_default2)
```

9.2.1.9 GET_DATA_3D

```
#define GET_DATA_3D(  
    function_name,  
    type,  
    argout,  
    attribute ) attribute void function_name(std::function<type *(size_t, size_t,  
size_t)> argout)
```

9.2.1.10 InfoLog

```
#define InfoLog(  
    ... ) LogMessage(LOGGER\_INFO, __VA_ARGS__);
```

9.2.1.11 LogMessage

```
#define LogMessage(  
    level,  
    ... ) LogBase(level, __FILE__, __LINE__, __VA_ARGS__);
```

9.2.1.12 timestamp_t

```
#define timestamp_t long long
```

9.2.1.13 TIMETAGGER_VERSION

```
#define TIMETAGGER_VERSION "2.8.2"
```

9.2.1.14 TT_API

```
#define TT_API __declspec(dllimport)
```

9.2.1.15 WarningLog

```
#define WarningLog(  
    ... ) LogMessage(LOGGER\_WARNING, __VA_ARGS__);
```

9.2.2 Typedef Documentation

9.2.2.1 _Iterator

```
using \_Iterator = IteratorBase
```

9.2.2.2 logger_callback

```
typedef void(* logger_callback) (LogLevel level, std::string msg)
```

9.2.3 Enumeration Type Documentation

9.2.3.1 ChannelEdge

```
enum ChannelEdge : int32_t [strong]
```

Enum for filtering the channel list returned by getChannelList.

Enumerator

NoFalling	
NoRising	
NoStandard	
NoHighRes	
All	
Rising	
Falling	
HighResAll	
HighResRising	
HighResFalling	
StandardAll	
StandardRising	
StandardFalling	

9.2.3.2 LogLevel

```
enum LogLevel
```

Enumerator

LOGGER_ERROR	
LOGGER_WARNING	
LOGGER_INFO	

9.2.3.3 Resolution

```
enum Resolution [strong]
```

This enum selects the high resolution mode of the Time Tagger series. If any high resolution mode is selected, the hardware will combine 2, 4 or even 8 input channels and average their timestamps. This results in a discretization jitter improvement of factor \sqrt{N} for N combined channels. The averaging is implemented before any filter, buffer or USB transmission. So all of those features are available with the averaged timestamps. Because of hardware limitations, only fixed combinations of channels are supported:

- HighResA: 1 : [1,2], 3 : [3,4], 5 : [5,6], 7 : [7,8], 10 : [10,11], 12 : [12,13], 14 : [14,15], 16 : [16,17], 9, 18
- HighResB: 1 : [1,2,3,4], 5 : [5,6,7,8], 10 : [10,11,12,13], 14 : [14,15,16,17], 9, 18
- HighResC: 5 : [1,2,3,4,5,6,7,8], 14 : [10,11,12,13,14,15,16,17], 9, 18 The inputs 9 and 18 are always available without averaging. The number of channels available will be limited to the number of channels licensed.

Enumerator

Standard	
HighResA	
HighResB	
HighResC	

9.2.4 Function Documentation

9.2.4.1 createTimeTagger()

```
TT_API TimeTagger* createTimeTagger (
    std::string serial = "",
    Resolution resolution = Resolution::Standard )
```

default constructor factory.

Parameters

<i>serial</i>	serial number of FPGA board to use. if empty, the first board found is used.
<i>resolution</i>	enum for how many channels shall be grouped.

See also

[Resolution](#) for details

9.2.4.2 createTimeTaggerVirtual()

```
TT_API TimeTaggerVirtual* createTimeTaggerVirtual ( )
```

default constructor factory for the createTimeTaggerVirtual class.

9.2.4.3 extractLicenseInfo()

```
TT_API std::string extractLicenseInfo (
    const std::string & license )
```

Parses the binary license and return a human readable information about this license.

Parameters

<i>license</i>	the binary license, encoded as a hexadecimal string
----------------	---

Returns

a human readable string containing all information about this license

9.2.4.4 flashLicense()

```
TT_API void flashLicense (
    const std::string & serial,
    const std::string & license )
```

Update the license on the device. Updated license may be fetched by getRemoteLicense. The Time Tagger must not be instancated while updating the license.

Parameters

<i>serial</i>	the serial of the device to update the license. Must not be empty
<i>license</i>	the binary license, encoded as a hexadecimal string

9.2.4.5 freeTimeTagger()

```
TT_API bool freeTimeTagger (
    TimeTaggerBase * tagger )
```

free a copy of a [TimeTagger](#) reference.

Parameters

<i>tagger</i>	the TimeTagger reference to free
---------------	--

9.2.4.6 `getTimeTaggerChannelNumberScheme()`

```
TT_API int getTimeTaggerChannelNumberScheme ( )
```

Fetch the currently configured global numbering scheme.

Please see [setTimeTaggerChannelNumberScheme\(\)](#) for details. Please use [TimeTagger::getChannelNumberScheme\(\)](#) to query the actual used numbering scheme, this function here will just return the scheme a newly created [TimeTagger](#) object will use.

9.2.4.7 `getTimeTaggerModel()`

```
TT_API std::string getTimeTaggerModel (
    const std::string & serial )
```

9.2.4.8 `getVersion()`

```
TT_API std::string getVersion ( )
```

9.2.4.9 `hasTimeTaggerVirtualLicense()`

```
TT_API bool hasTimeTaggerVirtualLicense ( )
```

Check if a license for the [TimeTaggerVirtual](#) is available.

9.2.4.10 `LogBase()`

```
TT_API void LogBase (
    LogLevel level,
    const char * file,
    int line,
    const char * fmt,
    ... )
```

Raise a new log message. Please use the XXXLog macro instead.

9.2.4.11 scanTimeTagger()

```
TT_API std::vector<std::string> scanTimeTagger ( )
```

fetches a list of all available [TimeTagger](#) serials.

This function may return serials blocked by other processes or already disconnected some milliseconds later.

9.2.4.12 setCustomBitFileName()

```
TT_API void setCustomBitFileName (
    const std::string & bitFileName )
```

set path and filename of the bitfile to be loaded into the FPGA

For debugging/development purposes the firmware loaded into the FPGA can be set manually with this function. To load the default bitfile set bitFileName = ""

Parameters

<i>bitFileName</i>	custom bitfile to use for the FPGA.
--------------------	-------------------------------------

9.2.4.13 setLogger()

```
TT_API logger_callback setLogger (
    logger_callback callback )
```

Sets the notifier callback which is called for each log message.

Returns

The old callback

If this function is called with nullptr, the default callback will be used.

9.2.4.14 setTimeTaggerChannelNumberScheme()

```
TT_API void setTimeTaggerChannelNumberScheme (
    int scheme )
```

Configure the numbering scheme for new [TimeTagger](#) objects.

Parameters

<i>scheme</i>	new numbering scheme, must be TT_CHANNEL_NUMBER_SCHEME_AUTO, TT_CHANNEL_NUMBER_SCHEME_ZERO or TT_CHANNEL_NUMBER_SCHEME_ONE
---------------	--

This function sets the numbering scheme for newly created [TimeTagger](#) objects. The default value is `_AUTO`.

Note: [TimeTagger](#) objects are cached internally, so the scheme should be set before the first call of [createTimeTagger\(\)](#).

`_ZERO` will typically allocate the channel numbers 0 to 7 for the 8 input channels. 8 to 15 will be allocated for the corresponding falling events.

`_ONE` will typically allocate the channel numbers 1 to 8 for the 8 input channels. -1 to -8 will be allocated for the corresponding falling events.

`_AUTO` will choose the scheme based on the hardware revision and so based on the printed label.

9.2.5 Variable Documentation

9.2.5.1 CHANNEL_UNUSED

```
constexpr channel_t CHANNEL_UNUSED = -134217728
```

Constant for unused channel. Magic `channel_t` value to indicate an unused channel. So the iterators either have to disable this channel, or to choose a default one.

This value changed in version 2.1. The old value -1 aliases with falling events. The old value will still be accepted for now if the old numbering scheme is active.

9.2.5.2 CHANNEL_UNUSED_OLD

```
constexpr channel_t CHANNEL_UNUSED_OLD = -1
```

9.2.5.3 TT_CHANNEL_FALLING_EDGES

```
constexpr ChannelEdge TT_CHANNEL_FALLING_EDGES = ChannelEdge::Falling
```

9.2.5.4 TT_CHANNEL_NUMBER_SCHEME_AUTO

```
constexpr int TT_CHANNEL_NUMBER_SCHEME_AUTO = 0
```

Allowed values for [setTimeTaggerChannelNumberScheme\(\)](#).

`_ZERO` will typically allocate the channel numbers 0 to 7 for the 8 input channels. 8 to 15 will be allocated for the corresponding falling events.

`_ONE` will typically allocate the channel numbers 1 to 8 for the 8 input channels. -1 to -8 will be allocated for the corresponding falling events.

`_AUTO` will choose the scheme based on the hardware revision and so based on the printed label.

9.2.5.5 TT_CHANNEL_NUMBER_SCHEME_ONE

```
constexpr int TT_CHANNEL_NUMBER_SCHEME_ONE = 2
```

9.2.5.6 TT_CHANNEL_NUMBER_SCHEME_ZERO

```
constexpr int TT_CHANNEL_NUMBER_SCHEME_ZERO = 1
```

9.2.5.7 TT_CHANNEL_RISING_AND_FALLING_EDGES

```
constexpr ChannelEdge TT_CHANNEL_RISING_AND_FALLING_EDGES = ChannelEdge::All
```

9.2.5.8 TT_CHANNEL_RISING_EDGES

```
constexpr ChannelEdge TT_CHANNEL_RISING_EDGES = ChannelEdge::Rising
```

